

DICOM Conformance Statement

syngo[®] MR XA51A

Product Name

MAGNETOM Altea

MAGNETOM Sola

MAGNETOM Sola Fit

MAGNETOM Viato.Mobile



DICOM Conformance Statement Overview

The *syngo*® MR XA51A conforms to the DICOM Standard and supports the network services as described in Table 1: Network Services and the media services as described in Table 2: Media Services

Table 1: Network Services

SOP Classes	SOP Class UID	User of Service (SCU)		Provider of Service (SCP)	
Verification					
Verification	1.2.840.10008.1.1	Yes		Yes	
SOP Classes created by syngo® MR XA51A					
		Create	Send	Store	Display
MR Image Storage	1.2.840.10008.5.1.4.1.1.4	Yes	Yes	Yes	Yes
Enhanced MR Image Storage	1.2.840.10008.5.1.4.1.1.4.1	Yes	Yes	Yes	Yes
MR Spectroscopy Storage	1.2.840.10008.5.1.4.1.1.4.2	Yes	Yes	Yes	Yes
Enhanced MR Color Image Storage	1.2.840.10008.5.1.4.1.1.4.3	Yes	Yes	Yes	Yes
Secondary Capture Image Storage	1.2.840.10008.5.1.4.1.1.7	Yes	Yes	Yes	Yes
Multi-frame Grayscale Word Secondary Capture Image Storage	1.2.840.10008.5.1.4.1.1.7.3	Yes	Yes	Yes	Yes
Grayscale Softcopy Presentation State Storage	1.2.840.10008.5.1.4.1.1.11.1	Yes	Yes	Yes	Yes
Color Softcopy Presentation State Storage	1.2.840.10008.5.1.4.1.1.11.2	Yes	Yes	Yes	Yes
Pseudo-Color Softcopy Presentation State Storage	1.2.840.10008.5.1.4.1.1.11.3	Yes	Yes	Yes	Yes
Raw Data Storage	1.2.840.10008.5.1.4.1.1.66	Yes	Yes	Yes	No
Spatial Registration Storage	1.2.840.10008.5.1.4.1.1.66.1	Yes	Yes	Yes	Yes
Segmentation Storage	1.2.840.10008.5.1.4.1.1.66.4	Yes	Yes	Yes	Yes
Real World Value Mapping Storage	1.2.840.10008.5.1.4.1.1.67	Yes	Yes	Yes	Yes
Enhanced SR Storage	1.2.840.10008.5.1.4.1.1.88.22	Yes	Yes	Yes	Yes
Comprehensive SR Storage	1.2.840.10008.5.1.4.1.1.88.33	Yes	Yes	Yes	Yes

SOP Classes	SOP Class UID	User of Service (SCU)		Provider of Service (SCP)	
Encapsulated PDF Storage	1.2.840.10008.5.1.4.1.1.104.1	Yes	Yes	Yes	Yes
RT Image Storage	1.2.840.10008.5.1.4.1.1.481.1	Yes	Yes	Yes	Yes
RT Dose Storage	1.2.840.10008.5.1.4.1.1.481.2	Yes	Yes	Yes	Yes
RT Structure Set Storage	1.2.840.10008.5.1.4.1.1.481.3	Yes	Yes	Yes	Yes
RT Plan Storage	1.2.840.10008.5.1.4.1.1.481.5	Yes	Yes	Yes	Yes
SOP Classes managed by <i>syngo</i>® MR XA51A					
		Create	Send	Store	Display
Computed Radiography Image Storage	1.2.840.10008.5.1.4.1.1.1	No	Yes	Yes	Yes
Digital X-Ray Image Storage - For Presentation	1.2.840.10008.5.1.4.1.1.1.1	No	Yes	Yes	Yes
Digital X-Ray Image Storage – For Processing	1.2.840.10008.5.1.4.1.1.1.1.1	No	Yes	Yes	Yes
Digital Mammography X-Ray Image Storage – For Presentation	1.2.840.10008.5.1.4.1.1.1.2	No	Yes	Yes	Yes
Digital Mammography X-Ray Image Storage – For Processing	1.2.840.10008.5.1.4.1.1.1.2.1	No	Yes	Yes	Yes
Digital Intra-Oral X-Ray Image - For Presentation	1.2.840.10008.5.1.4.1.1.1.3	No	Yes	Yes	Yes
Digital Intra-Oral X-Ray Image - For Processing	1.2.840.10008.5.1.4.1.1.1.3.1	No	Yes	Yes	Yes
CT Image Storage	1.2.840.10008.5.1.4.1.1.2	No	Yes	Yes	Yes
Enhanced CT Image Storage	1.2.840.10008.5.1.4.1.1.2.1	No	Yes	Yes	Yes
Ultrasound Multi-frame Image Storage	1.2.840.10008.5.1.4.1.1.3.1	No	Yes	Yes	Yes
Ultrasound Image Storage	1.2.840.10008.5.1.4.1.1.6.1	No	Yes	Yes	Yes
Enhanced US Volume Storage	1.2.840.10008.5.1.4.1.1.6.2	No	Yes	Yes	Yes
Multi-frame Single Bit Secondary Capture Image Storage	1.2.840.10008.5.1.4.1.1.7.1	No	Yes	Yes	Yes
Multi-frame Grayscale Byte Secondary Capture Image Storage	1.2.840.10008.5.1.4.1.1.7.2	No	Yes	Yes	Yes

SOP Classes	SOP Class UID	User of Service (SCU)		Provider of Service (SCP)	
Multi-frame True Color Secondary Capture Image Storage	1.2.840.10008.5.1.4.1.1.7.4	No	Yes	Yes	Yes
12-lead ECG Waveform Storage	1.2.840.10008.5.1.4.1.1.9.1.1	No	Yes	Yes	No
General ECG Waveform Storage	1.2.840.10008.5.1.4.1.1.9.1.2	No	Yes	Yes	No
Ambulatory ECG Waveform Storage	1.2.840.10008.5.1.4.1.1.9.1.3	No	Yes	Yes	No
Hemodynamic Waveform Storage	1.2.840.10008.5.1.4.1.1.9.2.1	No	Yes	Yes	No
Cardiac Electrophysiology Waveform Storage	1.2.840.10008.5.1.4.1.1.9.3.1	No	Yes	Yes	No
Basic Voice Audio Waveform Storage	1.2.840.10008.5.1.4.1.1.9.4.1	No	Yes	Yes	No
General Audio Waveform Storage	1.2.840.10008.5.1.4.1.1.9.4.2	No	Yes	Yes	No
Arterial Pulse Waveform Storage	1.2.840.10008.5.1.4.1.1.9.5.1	No	Yes	Yes	No
Respiratory Waveform Storage	1.2.840.10008.5.1.4.1.1.9.6.1	No	Yes	Yes	No
Blending Softcopy Presentation State Storage	1.2.840.10008.5.1.4.1.1.11.4	No	Yes	Yes	Yes
Grayscale Planar MPR Volumetric Presentation State Storage	1.2.840.10008.5.1.4.1.1.11.6	No	Yes	Yes	No
Compositing Planar MPR Volumetric Presentation State Storage	1.2.840.10008.5.1.4.1.1.11.7	No	Yes	Yes	No
Advanced Blending Presentation State Storage	1.2.840.10008.5.1.4.1.1.11.8	No	Yes	Yes	No
Volume Rendering Volumetric Presentation State Storage	1.2.840.10008.5.1.4.1.1.11.9	No	Yes	Yes	No
Segmented Volume Rendering Volumetric Presentation State Storage	1.2.840.10008.5.1.4.1.1.11.10	No	Yes	Yes	No
Multiple Volume Rendering Volumetric Presentation State Storage	1.2.840.10008.5.1.4.1.1.11.11	No	Yes	Yes	No
X-Ray Angiographic Image Storage	1.2.840.10008.5.1.4.1.1.12.1	No	Yes	Yes	Yes
Enhanced XA Image Storage	1.2.840.10008.5.1.4.1.1.12.1.1	No	Yes	Yes	Yes
X-Ray Radiofluoroscopic Image Storage	1.2.840.10008.5.1.4.1.1.12.2	No	Yes	Yes	Yes

SOP Classes	SOP Class UID	User of Service (SCU)	Provider of Service (SCP)		
Enhanced XRF Image Storage	1.2.840.10008.5.1.4.1.1.12.2.1	No	Yes	Yes	Yes
X-Ray 3D Angiographic Image Storage	1.2.840.10008.5.1.4.1.1.13.1.1	No	Yes	Yes	Yes
Breast Tomosynthesis Image Storage	1.2.840.10008.5.1.4.1.1.13.1.3	No	Yes	Yes	Yes
Nuclear Medicine Image Storage	1.2.840.10008.5.1.4.1.1.20	No	Yes	Yes	Yes
Spatial Fiducials Storage	1.2.840.10008.5.1.4.1.1.66.2	No	Yes	Yes	No
Deformable Spatial Registration	1.2.840.10008.5.1.4.1.1.66.3	No	Yes	Yes	No
Segmentation Storage	1.2.840.10008.5.1.4.1.1.66.4	Yes	Yes	Yes	Yes
Surface Segmentation Storage	1.2.840.10008.5.1.4.1.1.66.5	No	Yes	Yes	Yes
Basic Text SR Storage	1.2.840.10008.5.1.4.1.1.88.11	No	Yes	Yes	Yes
Procedure Log Storage Storage	1.2.840.10008.5.1.4.1.1.88.40	No	Yes	Yes	No
Mammography CAD SR Storage	1.2.840.10008.5.1.4.1.1.88.50	No	Yes	Yes	No
Key Object Selection Document Storage	1.2.840.10008.5.1.4.1.1.88.59	No	Yes	Yes	No
X-Ray Radiation Dose SR Storage	1.2.840.10008.5.1.4.1.1.88.67	No	Yes	Yes	No
Radiopharmaceutical Radiation Dose SR	1.2.840.10008.5.1.4.1.1.88.68	No	Yes	Yes	No
Positron Emission Tomography Image Storage	1.2.840.10008.5.1.4.1.1.128	No	Yes	Yes	Yes
RT Beams Treatment Record Storage	1.2.840.10008.5.1.4.1.1.481.4	No	Yes	Yes	No
Radio Therapy Brachy Treatment Record Storage	1.2.840.10008.5.1.4.1.1.481.6	No	Yes	Yes	No
RT Treatment Summary Record Storage	1.2.840.10008.5.1.4.1.1.481.7	No	Yes	Yes	No
RT Ion Plan Storage	1.2.840.10008.5.1.4.1.1.481.8	No	Yes	Yes	No
RT Ion Beams Treatment Record Storage	1.2.840.10008.5.1.4.1.1.481.9	No	Yes	Yes	No
Hanging Protocol Storage	1.2.840.10008.5.1.4.38.1	No	Yes	Yes	No
Transfer (Private SOP Class)					
Syngo Non-Image Storage	1.3.12.2.1107.5.9.1	Yes		Yes	
Storage Commitment					
Storage Commitment Push Model	1.2.840.10008.1.20.1	Yes		No	
Worklist Management					

SOP Classes	SOP Class UID	User of Service (SCU)	Provider of Service (SCP)
Modality Worklist Information Model - FIND	1.2.840.10008.5.1.4.31	Yes	No
Modality Performed Procedure Step	1.2.840.10008.3.1.2.3.3	Yes	No
Query/Retrieve			
Patient Root Query/Retrieve Information Model – FIND	1.2.840.10008.5.1.4.1.2.1.1	Yes	Yes
Patient Root Query/Retrieve - Information Model - MOVE	1.2.840.10008.5.1.4.1.2.1.2	Yes	Yes
Study Root Query/Retrieve - Information Model - FIND	1.2.840.10008.5.1.4.1.2.2.1	Yes	Yes
Study Root Query/Retrieve - Information Model - MOVE	1.2.840.10008.5.1.4.1.2.2.2	Yes	Yes
Patient/Study Only Query/Retrieve - Information Model – FIND	1.2.840.10008.5.1.4.1.2.3.1	Yes	Yes
Patient/Study Only Query/Retrieve - Information Model – MOVE	1.2.840.10008.5.1.4.1.2.3.2	Yes	Yes
Print Management			
Basic Grayscale Print Management Meta SOP Class	1.2.840.10008.5.1.1.9	Yes	No
Basic Color Print Management Meta SOP Class	1.2.840.10008.5.1.1.18	Yes	No
Basic Film Session SOP Class	1.2.840.10008.5.1.1.1	Yes	No
Basic Film Box SOP Class	1.2.840.10008.5.1.1.2	Yes	No
Basic Grayscale Image Box SOP Class	1.2.840.10008.5.1.1.4	Yes	No
Basic Color Image Box SOP Class	1.2.840.10008.5.1.1.4.1	Yes	No
Printer SOP Class	1.2.840.10008.5.1.1.16	Yes	No
Print Job SOP Class	1.2.840.10008.5.1.1.14	Yes	No
Presentation LUT SOP Class	1.2.840.10008.5.1.1.23	Yes	No

Table 2: Media Services

Media Storage Application Profile Write Files (FSC or FSU) Read Files (FSR)

Compact Disk - Recordable

STD-GEN-CD	Yes	Yes
AUG-GEN-CD	Yes	Yes
DVD		
AUG-GEN-DVD	Yes	Yes
AUG- GEN-DVD-J2K	Yes	Yes
STD-GEN-DVD-JPEG	Yes	Yes
STD-GEN-DVD-J2K	Yes	Yes
USB		
AUG- GEN-USB-J2K	Yes	Yes
STD-GEN-USB-J2K	Yes	Yes

Table 3: Implementation Identifying Information

Name	Value
Application Context Name	1.2.840.100008.3.1.1.1
Implementation Class UID	1.3.12.2.1107.5.2
Implementation Version Name	"SYNGO_MR_XA51A"

	3 INTRODUCTION	10
	3.1 Revision History	10
	3.2 Audience	10
	3.3 Remarks	10
	3.4 Definitions, Terms and Abbreviations	12
	3.5 References	12
	4 NETWORKING	13
	4.1 Implementation Model	13
	4.1.1 Application Data Flow	13
	4.1.2 Functional Definitions of Application Entities	15
	4.1.3 Sequencing of Activities	17
	4.2 AE Specifications	20
	4.2.1 Verification AE Specification	20
	4.2.2 Storage AE Specification	21
	4.2.3 Storage Commitment AE Specification	26
	4.2.4 Query/Retrieve AE Specification	31
	4.2.5 Modality Worklist AE Specification	40
	4.2.6 Modality Performed Procedure Step AE Specification	46
	4.2.7 Print AE Specification	49
	4.3 Network Interfaces	58
	4.3.1 Physical Network Interface	58
	4.3.2 Additional Protocols	59
	4.3.3 IPv4 and IPv6 Support	59
	4.4 Configuration	59
	4.4.1 AE Title/Presentation Address Mapping	59
	4.4.2 Parameters	60
	5 MEDIA INTERCHANGE	61
	5.1 Implementation Model	61
	5.1.1 Application Data Flow Diagram	61
	5.1.2 Functional Definitions of AEs	61
	5.1.3 Sequencing of Real-World Activities	62
	5.1.4 File Meta Information for Implementation Class and Version	62
	5.2 AE Specifications	63
	5.2.1 Media Storage AE – Specification	63
	5.3 Augmented and Private Application Profiles	64
	5.3.1 Augmented Application Profiles	64
	5.4 Media Configuration	64

6	SUPPORT OF EXTENDED CHARACTER SETS	65
7	ATTRIBUTE CONFIDENTIALITY PROFILES	68
7.1	De-identification	68
8	SECURITY	80
8.1	Security Profiles	80
8.1.1	Time Synchronization Profiles	80
8.1.2	Basic TLS Secure Transport Connection Profile	80
8.2	Association Level Security	80
8.3	Application Level Security	80
9	ANNEXES	81
9.1	IOD Contents	81
9.1.1	Created SOP Instances	81
9.1.2	Usage of Attributes from received IODs	125
9.1.3	Attribute mapping	126
9.1.4	Coerced / Modified fields	128
9.2	Data Dictionary of Private Attributes	128
9.2.1	MR Related Private Attributes	128
9.3	Coded Terminology and Templates	133
9.3.1	Context Groups	133
9.3.2	Template Specifications	133
9.3.3	Private Code definitions	133
9.4	Grayscale Image Consistency	133
9.5	Standard Extended / Specialized / Private SOP Classes	133
9.5.1	Enhanced MR Image Storage SOP Class	133
9.6	Private Transfer Syntaxes	133
9.7	DICOM Print SCU – detailed status displays	133
9.7.1	Common Status Information	134
9.7.2	Additional DICOM Execution Status Information	138
ANNEX A:	INDEX OF TABLES	140
ANNEX B:	TABLE OF FIGURES	141

3 Introduction

3.1 Revision History

Version	Date	Change
<i>syngo</i> ® MR XA50A	2022-05-19	<i>syngo</i>® MR XA50A version (predecessor versions: <i>syngo</i>® MR XA30A, <i>syngo</i>® MR XA31A and <i>syngo</i>® MR XA40A) New system support: MAGNETOM Avanto Fit, MAGNETOM Free.Max, MAGNETOM Free.Star, MAGNETOM Lumina, MAGNETOM Skyra Fit, MAGNETOM Vida, MAGNETOM Vida Fit IOD Tables added for: Enhanced MR Image, Enhanced MR Color Image, MR Spectroscopy, Raw Data
<i>syngo</i> ® MR XA51A	2022-08-26	<i>syngo</i>® MR XA51A version (predecessor version: <i>syngo</i>® MR XA31A, <i>syngo</i>® MR XA20A) System support: MAGNETOM Altea, MAGNETOM Sola, MAGNETOM Sola Fit Added Echo Number(s) (0018,0086) to MR Echo Macro.
<i>syngo</i> ® MR XA51A	2023-12-08	<i>syngo</i>® MR XA51A second version. New system support: MAGNETOM Viato.Mobile Creation of Color Presentation States and Pseudo-Color Presentation States.
<i>syngo</i> ® MR XA51A	2024-09-11	<i>syngo</i>® MR XA51A third version. Added description of private attributes, changes in de-identification, improved IOD content description.

3.2 Audience

This document is intended for hospital staff, health system integrators, software designers or implementers. It is assumed that the reader has a working understanding of DICOM.

3.3 Remarks

The scope of this DICOM Conformance Statement is to facilitate integration between this product and other DICOM products. The Conformance Statement should be read and understood in conjunction with the DICOM Standard [1]. DICOM by itself does not guarantee interoperability.

The Conformance Statement does, however, facilitate a first-level comparison for interoperability between different applications supporting compatible DICOM functionality.

This Conformance Statement is not supposed to replace validation with other DICOM equipment to ensure proper exchange of intended information. In fact, the user should be aware of the following important issues:

- The comparison of conformance statements is the first step towards assessing interconnectivity and interoperability between *syngo*® MR XA51A and other DICOM conformant equipment.
- Test procedures should be defined and executed to validate the required level of interoperability with specific compatible DICOM equipment, as established by the healthcare facility.

Siemens Healthineers reserves the right to modify the design and specifications contained herein without prior notice. Please contact your local Siemens representative for the most recent product information.

3.4 Definitions, Terms and Abbreviations

Definitions, terms, and abbreviations used in this document are defined within the different parts of the DICOM standard. Additional Abbreviations and terms are as follows:

AE	DICOM Application Entity
AET	Application Entity Title
ASCII	American Standard Code for Information Interchange
DCS	DICOM Conformance Statement
DICOM	Digital Imaging and Communications in Medicine
FSC	File Set Creator
FSR	File Set Reader
FSU	File Set Updater
GSDF	Grayscale Standard Display Function
IOD	DICOM Information Object Definition
ISO	International Standard Organization
n. a.	not applicable
NEMA	National Electrical Manufacturers Association
O	Optional Key Attribute
PDU	DICOM Protocol Data Unit
R	Required Key Attribute
SCU	DICOM Service Class User (DICOM client)
SCP	DICOM Service Class Provider (DICOM Server)
SOP	DICOM Service-Object Pair
SR	Structured Report
TFT	Thin Film Transistor (Display)
TID	Template ID
U	Unique Key Attribute
UID	Unique Identifier
UTF-8	Unicode Transformation Format-8
VR	Value Representation

3.5 References

- [1] Digital Imaging and Communications in Medicine (DICOM), <https://www.dicomstandard.org>
- [2] Integrating the Healthcare Enterprise – IHE Radiology Technical Framework – <http://www.ihe.net>


4 Networking


4.1 Implementation Model

syngo® MR XA51A supports storing DICOM images to remote nodes like workstations or Archiving Systems. Using the Storage Commitment Service it can request safe keeping of previously stored instances from an Archiving system. Additionally, the *syngo*® MR XA51A can query remote notes, retrieve and store selected instances from that node. Using the Modality Worklist service the *syngo*® MR XA51A can query a HIS/RIS for scheduled procedures. Performed procedure status and other procedure data can be returned to the HIS/RIS using the Modality Performed Procedure Step (MPPS) Service. Furthermore, printing of color and grayscale images is supported.

4.1.1 Application Data Flow

The following figures provide a functional overview of the *syngo*® MR XA51A Application Entities (AE). Please do note that it is based on the default configuration and may differ depending on configuration at the customer site.








Figure 1: syngo® MR XA51A DICOM Data Flow diagram

4.1.2 Functional Definitions of Application Entities

The SCP components of the Application Entities of the syngo® MR XA51A operate as background server processes. They exist as soon as the system is powered up and wait for association requests. Upon accepting an association with a negotiated Presentation Context they start to receive and process the requests described in the following sections.

The SCU components of the Application Entity are invoked upon requests from the user interface or indirectly by trigger from internal processes.

4.1.2.1 Functional Definitions of Verification AE

The syngo® MR XA51A supports the Verification service as a SCP and SCU. As a SCU, Verification can be activated from the Administrator Portal during system configuration by sending a C-ECHO-Request.

As a SCP of the Verification Service the syngo® MR XA51A processes and responds to incoming verification requests using the C-ECHO-Response.

4.1.2.2 Functional Definition of Storage of AE

The syngo® MR XA51A Storage SCU is invoked either directly by the user, by an auto-archive trigger or internally by the Query/Retrieve Application Entity that is responsible for processing retrieve requests. The job consists of data describing the composite objects selected for storage and the destination Application Entity Title. An association is negotiated with the destination Application Entity and the image data is transferred using the C-STORE-Request. The transfer status is reported to the initiator of the Storage request.

The Storage SCP component of the *syngo*® MR XA51A starts to receive the Composite Objects and import them into the database after accepting an association with a negotiated Presentation Context. The system responses to the Storage Request immediately after reception of the Data.

4.1.2.3 Functional Definition of the Storage Commitment AE

If configured, the *syngo*® MR XA51A can serve as a SCU for the DICOM Storage Commitment service. Upon successful completion of a storage job, the system uses the N-ACTION-Request to request storage commitment from a remote DICOM Storage Commitment SCP. This can either be the same as the storage destination or a different system depending on the system configuration. Storage Commitment Requests are sent after a configurable delay after storing the objects. The *syngo*® MR XA51A can receive the N-EVENT-REPORT-Request on the same or a different association.

4.1.2.4 Functional Specification of Query/Retrieve AE

The *syngo*® MR XA51A supports DICOM Query/Retrieve as a SCU: The user can initiate a query to a remote node using the C-FIND-Request. After matching the specified keys, the remote Query/Retrieve SCP uses the C-FIND-Response to return the results of its search, which will be displayed to the user. Depending on user action the *syngo*® MR XA51A Query/Retrieve DICOM SCU sends a C-MOVE-Request to initiate a C-STORE sub-operation on the SCP to start an image transfer from remote Storage SCU (running on Query/Retrieve SCP) to the system's Storage SCP.

The *syngo*® MR XA51A supports the following query model:

- Study Root Query Model
- Patient Root Query Model
- Patient/Study only Query Model

Furthermore, the SCU services may issue relational queries, if supported by the remote Query/Retrieve SCP node and required by the querying Application.

The *syngo*® MR XA51A DICOM Query/Retrieve SCP accepts C-FIND Request, queries the local database based on the provided matching keys and returns the matches using the C-FIND-Response. Depending on further request from the remote Query/Retrieve SCU, the *syngo*® MR XA51A responds to C-MOVE-Requests by initiating a C-STORE sub-operation to send image objects to the Storage SCP of the querying system.

4.1.2.5 Functional Definition of Modality Worklist AE

The *syngo*® MR XA51A Modality Worklist SCU issues DICOM Modality Worklist requests using C-FIND-Requests. The results in the C-FIND-Response are stored in internal database. The provided Patient and Procedure information is used for patient registration prior to starting an exam.

4.1.2.6 Functional Definition of Modality Performed Procedure Step SCU AE

The *syngo*® MR XA51A MPPS SCU uses the N-CREATE-Request to inform an Information System that a procedure step is IN PROGRESS.

The *syngo*® MR XA51A MPPS SCU uses the N-SET-Request to inform the Information System about the finalization of the Procedure Step, using either a status of COMPLETED or DISCONTINUED.

4.1.2.7 Functional Definition of Print AE

The Print SCU of the *syngo*® MR XA51A is invoked by the user interface to setup film-sheet layout and whenever an image is ready to be printed on film. The Print SCU will hold and maintain all data needed to compile a complete film-sheet from the data (images, layout, configuration) received. Whenever a film-sheet is ready to print the related data is used to supply the Information to the SOP Classes of the Print Management Service Class. A queue is maintained in order to intermediately store several film-sheets in case of resource problems on printer. The SCU will only supply and require the mandatory SOP Classes of the Print Management Service Class.

4.1.3 Sequencing of Activities

This section describes the sequencing of Real-World Activities performed by the *syngo*® MR XA51A Entities using a UML sequence diagram. Real-World Activities are depicted as vertical bars and arrows show the events exchanged between them.

4.1.3.1 System Configuration




Figure 2: Sequence Diagram for Real World Activities - System Configuration

4.1.3.2 Acquisition Workflow




Figure 3: Sequence Diagram for Real World Activities -Acquisition workflow

4.1.3.3 Printing Workflow




Figure 4: Sequence Diagram for Real World Activities - Printing

4.2 AE Specifications

This section outlines the specifications for each of the Application Entities that are part of the *syngo*® MR XA51A.

4.2.1 Verification AE Specification

4.2.1.1 SOP Classes

The Verification AE of the *syngo*® MR XA51A provides standard conformance to the Verification SOP Class listed in Table 1: Network Services section "Verification" in the "[Conformance Statement Overview](#)".

4.2.1.2 Association Policy

The *syngo*® MR XA51A Admin Portal attempts to open an association for verification request whenever the Verification function is activated.

Table 4: Association Policies

Application Context Name	1.2.840.10008.3.1.1.1
PDU size	32 kB ¹
Maximum number of simultaneous associations as an association acceptor	12 ¹
Maximum number of simultaneous associations as an association initiator	unlimited

4.2.1.2.1 Asynchronous Nature

The *syngo*® MR XA51A supports asynchronous communication (multiple outstanding transactions over a single association). On the SCU side the Window size proposed is infinite. On the SCP Side any size is supported.

Table 5: Asynchronous Nature as an Association Initiator

Maximum number of outstanding asynchronous transactions	10
--	----

4.2.1.2.2 Implementation Identifying Information

For Implementation Identifying Information please refer to Table 3: Implementation Identifying Information in the "[Conformance Statement Overview](#)".

4.2.1.3 Association Initiation Policy

4.2.1.3.1 Activity – "Send Activity"

4.2.1.3.1.1 Description and Sequencing of Activities

The *syngo*® MR XA51A serves as a SCU of the Verification Service Class. A C-ECHO-Request is initiated by the Administrator Portal whenever "Verification" is requested. If an association to a remote Application Entity is successfully established, Verification with the configured AET is requested via the open association. If the C-ECHO Response from the remote Application contains a status other than "Success" this will be indicated to the user and the association is closed.

¹ Default, the value is configurable

4.2.1.3.1.2 Proposed Presentation Contexts

Table 6: Presentation Context Table "Verification" below lists the supported presentation contexts for verification requests.

Table 6: Presentation Context Table "Verification"

Abstract Syntax		Transfer Syntax		Role	Extended Negotiation
Name	UID	Name List	UID List		
Verification	1.2.840.10008.1.1	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None

4.2.1.3.1.3 SOP specific Conformance for SOP classes

The ECHO-SCU provides standard conformance to the Verification Service Class.

4.2.1.4 Association Acceptance Policy

4.2.1.4.1 Activity – "Receive Verification Request"

4.2.1.4.1.1 Description and Sequencing of Activities

The *syngo*® MR XA51A serves as a SCP of the Verification Service Class. If the Verification SCP accepts an association, it will respond to C-ECHO-Requests. If the Called AE Title does not match any pre-configured AE Title shared by SCP, the association will be rejected.

4.2.1.4.1.2 Accepted Presentation Contexts

The *syngo*® MR XA51A DICOM application will accept Presentation Contexts as shown in the following table:

Table 7: Presentation Context Table "Verification"

Abstract Syntax		Transfer Syntax		Role	Extended Negotiation
Name	UID	Name List	UID List		
Verification	1.2.840.10008.1.1	Implicit VR Little Endian	1.2.840.10008.1.2	SCP	None

4.2.1.4.1.3 SOP specific Conformance – Verification SCP

The ECHO-SCP provides standard conformance to the Verification Service Class.

4.2.2 Storage AE Specification

4.2.2.1 SOP Classes

The Storage AE provides Standard Conformance to the SOP Classes listed in "Table 1: Network Services" section "SOP Classes Created by the *syngo*® MR XA51A" and "SOP Classes Managed by the *syngo*® MR XA51A" in the ["Conformance Statement Overview"](#).

4.2.2.2 Association Policy

Table 8: Association Policy

Application Context Name	1.2.840.10008.3.1.1.1
PDU size	32 kB ¹
Maximum number of simultaneous associations as an association acceptor	12 ¹
Maximum number of simultaneous associations as an association initiator	unlimited

The *syngo*® MR XA51A contains a limitation of 512 kB for the maximum PDU size. By default, the PDU size is set to 32kB.

The maximum number of simultaneous receiving associations (SCP) is configurable at run time, based on the system resources available. By default, the maximum number of associations is set to 12.

There is no inherent limit to the number of outgoing associations (SCU), other than limits imposed by the computer operating system.

4.2.2.2.1 Asynchronous Nature

The *syngo*® MR XA51A supports asynchronous communication (multiple outstanding transactions over a single association). On the SCU side the Window size proposed is infinite. On the SCP Side any non-infinite maximum size will be accepted.

Table 9: Asynchronous Nature as an Association Initiator

Maximum number of outstanding asynchronous transactions	10
--	----

4.2.2.2.2 Implementation Identifying Information

For Implementation Identifying Information please refer to

Table 3: Implementation Identifying Information in the [“Conformance Statement Overview”](#).

4.2.2.3 Association Initiation Policy

For general information regarding the association initiation policies please see Chapter 4.2.1.2

4.2.2.3.1 Activity- “Send Verification Request”

The Storage AE supports the Verification SOP Class. For further details please see chapter 4.2.1.2.1.

4.2.2.3.2 Activity “Send Instances”

4.2.2.3.2.1 Description and Sequencing of Activities

The *syngo*® MR XA51A serves as a SCU of the Storage Service Class. The Storage SCU is triggered by the transfer job queue or by an external retrieve request. An association request is sent to the destination AE. Upon successful negotiation of a Presentation Context, the transfer is started. Objects will be transferred sequentially on the same open association.

4.2.2.3.2.2 Proposed Presentation Contexts

syngo® MR XA51A proposes one Presentation Context for each SOP Class/Transfer Syntax combination in the A-ASSOCIATE-RQ. The number of Presentation Contexts in an A-ASSOCIATE-RQ message is limited to 128. If this limit is exceeded, multiple Transfer Syntaxes are offered in one Presentation Context.

¹ Default, the value is configurable

For all Image Objects listed in Table 1 in the Conformance Statement Overview the Transfer Syntaxes marked with “yes” in the Image Objects Column of the table below are proposed in a Presentation Context.

For all Non-Image Objects listed in Table 1 in the Conformance Statement Overview the Transfer Syntaxes marked with “yes” in the Non-Image Objects Column of the table below are proposed in a Presentation Context.

For a distinction between Image and Non-Image Objects please refer to the DICOM Standard PS3.3 Section A.1.4 “Overview of the Composite IOD Module Content [1]”.

Table 10: Proposed Presentation Contexts for Storage

UID value	Transfer Syntax	Image Objects	Non-Image Objects
1.2.840.10008.1.2	Implicit VR Little Endian	Yes	Yes
1.2.840.10008.1.2.1	Explicit VR Little Endian	Yes	Yes
1.2.840.10008.1.2.2	Explicit VR Big Endian (Retired)	Yes	Yes
1.2.840.10008.1.2.4.50	JPEG Baseline (Process 1)	Yes	No
1.2.840.10008.1.2.4.51	JPEG Extended (Process 2 & 4)	Yes	No
1.2.840.10008.1.2.4.57	JPEG Lossless, Non-Hierarchical (Process 14)	Yes	No
1.2.840.10008.1.2.4.70	JPEG Lossless, Non-Hierarchical, First-Order Prediction (Process 14 [Selection Value 1])	Yes	No
1.2.840.10008.1.2.4.90	JPEG 2000 Image Compression (Lossless Only)	Yes	No
1.2.840.10008.1.2.4.91	JPEG 2000 Image Compression	Yes	No
1.2.840.10008.1.2.5	RLE Lossless	Yes	No

Depending on the configuration, the Storage SCU will choose a compressed or uncompressed Transfer Syntax among those accepted by the SCP. The Transfer Syntax chosen is the preferred one among the compressed and uncompressed ones. The preference order is the order of occurrence in the configuration. For each node it is possible to select Transfer Syntaxes, that can be used, and Transfer Syntaxes, that are excluded. The configuration can even be extended, based on the combination of SOP Classes and supported Transfer Syntaxes.

An instance will be JPEG lossless compressed only if it fulfills the following criteria:

- Is an image and not already compressed
- Photometric Interpretation (0028,0004) is either MONOCHROME1, MONOCHROME2, RGB, YBR_FULL or YBR_FULL_422
- Bits Allocated (0028,0100) equal to '16' or '8'
- Bits Stored (0028,0101) equal to '12' or '8'
- High Bit (0028,0102) equal to Bits Stored (0028,0101) - 1
- Pixel Representation (0028,0103) equal to '0'

An instance will be JPEG lossy compressed during transfer only if the following criteria is fulfilled:

- Is an image
- Photometric Interpretation (0028,0004) is either MONOCHROME1, MONOCHROME2 or RGB
- Bits Allocated (0028,0100) equal to '16' or '8'
- Bits Stored (0028,0101) equal to '12' or '8'
- High Bit (0028,0102) equal to Bits Stored (0028,0101) - 1
- Pixel Representation (0028,0103) equal to '0'
- Only lossy transfer syntaxes are supported (Implicit VR Little Endian is not supported) at the remote side

An instance will be JPEG 2000 lossless compressed only if it fulfills the following criteria:

- Is an image and not already compressed
- Photometric Interpretation (0028,0004) is either MONOCHROME, RGB, YBR_FULL or YBR_FULL_422

- Bits Allocated (0028,0100) equal to '16' or '8'

An instance will be RLE lossless compressed only if it fulfills the following criteria:

- Is an image and not already compressed
- Photometric Interpretation (0028,0004) is MONOCHROME, RGB, YBR_FULL or RGB
- Bits Allocated (0028,0100) neither '16' nor '8'

An instance will be JPEG 2000 lossy compressed during transfer only if the following criteria is fulfilled:

- Is an image
- Photometric Interpretation (0028,0004) is MONOCHROME or RGB
- Bits Stored (0028,0101) equal to '12' or '8'
- Only lossy transfer syntaxes are supported (Implicit VR Little Endian is not supported) at the remote side

There is no extended negotiation as an SCU.

4.2.2.3.2.3 *SOP Specific Conformance for SOP Classes*

The *syngo*® MR XA51A does not add or change private attributes by default, even in case objects are compressed or the image header is updated according to IHE [2] Patient Information Reconciliation Profile.

The behavior of *syngo*® MR XA51A when encountering status codes in a C-STORE response is summarized in Table 11

Table 11: DICOM Command Response Status Handling Behavior

Service Status	Further Meaning	Error Code	Behavior
Error	Any other DIMSE Error Status	Any none null Code	Send is continued till the end. Log message is created.
Success	Image is successfully stored	0000	If configured, Storage Commitment is requested for successfully stored instances

Table 12 below indicates the behavior if exceptions occur:

Table 12: DICOM Command Communication Failure Behavior

Exception	Behavior
Association Negotiation Timeout	Log message is created (Timeout configurable; default 30s)
Association Aborted	Send is failed. Log message is created.

4.2.2.3.2.4 *Correction and Rearrangement*

When a Study is moved to a different:

- Procedure received through a DICOM Modality Worklist, the Study Instance UID is overwritten with the Study Instance UID and Accession Number of the Procedure.
- Patient, the system generates a new Study Instance UID.

The system will not update references to the changed Study Instance UIDs, therefore it is possible that there will be broken links between Studies after such move operations.

A configuration setting is available if UIDs should be changed in case of Patient Merge and Correction. Per default the UID change is activated to ensure that the corrected instances are displayed at the PACS. If the UID change is deactivated it is recommended to delete any corrected or rearranged objects from the PACS before attempting to archive them again, to ensure that the PACS system can store them successfully.

When the Patient Position (0018,5100) attribute is corrected, the following attributes are recalculated by the system (no UIDs are changed):

1. Image Position (0020,0032)
2. Image Orientation (0020,0037)
3. Patient Orientation (0020,0020)
4. Data Collection Center (Patient) (0018,9313) (CT only)
5. Reconstruction Target Center (Patient) (0018,9318) (CT only)
6. Positioner Primary Angle (0018,1510) (XA only)
7. Positioner Secondary Angle (0018,1511) (XA only)

Also, the value of the Slice Location (0020,1041) attribute is emptied and a new Frame of Reference UID (0020,0052) is generated for the corrected series.

When the Patient Birth Date or the Study Date is corrected, the system recalculates the Patient Age.

A new item containing attributes that were removed or replaced by other values is added to the Original Attribute Sequence (0400,0561).

4.2.2.4 Association Acceptance Policy

4.2.2.4.1 Activity – “Receive Instances”

4.2.2.4.1.1 Description and Sequencing of Activities

The *syngo*® MR XA51A serves as a SCP of the Storage Service Class. The storage SCP accepts incoming C-Store Request from any configured AE Title, receives supported objects transmitted on that association and stores them in the local database.

4.2.2.4.1.2 Accepted Presentation Contexts

When receiving an association request from a remote node, *syngo*® MR XA51A accepts all presentation context containing a transfer syntax configured for that node. If multiple transfer syntaxes are proposed within one presentation context, *syngo*® MR XA51A selects it based on the configured preference order configured for that node. The preference order is the order of occurrence of the transfer syntaxes in the configuration. For each node it is possible to select Transfer Syntaxes, that can be used, and Transfer Syntaxes, that are excluded. The configuration can even be extended, based on the combination of SOP Classes and supported Transfer Syntaxes.

Table 10 lists all Transfer Syntaxes that are supported for the Transfer Objects (see “Table 1: Network Services” section “SOP Classes Created by the *syngo*® MR XA51A” and “SOP Classes Managed by the *syngo*® MR XA51A” in the [“Conformance Statement Overview”](#)).

There is no Extended Negotiation as an SCP.

4.2.2.4.1.3 SOP-specific Conformance Statement for Storage SOP classes

The *syngo*® MR XA51A conforms to the Full Storage Class at Level 2.

In case of a successful C-STORE operation, the image has successfully been received in the negotiated transfer syntax.

The Storage AE of the *syngo*® MR XA51A returns the status “success” when the data is received, and a minimal image header validation has been performed.

The following header attributes must be available and filled:

- SOP Class UID,
- Study Instance UID,
- Series Instance UID and
- SOP Instance UID.

Table 13 below list the status codes that the *syngo*® MR XA51A can return:

Table 13: Storage C-STORE Response Status

Service Status	Further Meaning	Error Code	Reason
Success	Success	0000	Image received correctly (success notification is done after receiving, before indexing and storing)
Failure	Out-of-resource	A700	No resource left in the Short Term Storage
Failure	Unable to Process	Cxxx	Error during instance reception
Failure	Data set does not match SOP Class	A9xx	The data set is not conform to the SOP Class contained in the resource.

Restriction: Depending on response configuration successful operation does not guarantee storage on disk and storage of header data in the database.

4.2.2.4.1.4 Other SOP specific behavior

If an image is received that is already stored in the database - identified by the SOP Instance UID - the new image will be ignored. The existing instance is not superseded.

4.2.3 Storage Commitment AE Specification

4.2.3.1 SOP Classes

The Storage Commitment AE of the *syngo*® MR XA51A provides standard conformance to the SOP Class listed in “Table 1: Network Services” section "Storage Commitment" in the [“Conformance Statement Overview”](#).

Table 14: Association Policies

Application Context Name	1.2.840.10008.3.1.1.1
PDU size	32 kB ¹
Maximum number of simultaneous associations as an association acceptor	12 ¹
Maximum number of simultaneous associations as an association initiator	unlimited

The *syngo*® MR XA51A contains a limitation of 512 kB for the maximum PDU size. By default, the PDU size is set to 32kB.

The maximum number of simultaneous receiving associations (SCP) is configurable at run time, based on the system resources available. By default, the maximum number of associations is set to 12.

There is no inherent limit to the number of outgoing associations (SCU), other than limits imposed by the computer operating system.

¹ Default, the value is configurable

4.2.3.1.1 Asynchronous Nature

The syngo® MR XA51A supports asynchronous communication (multiple outstanding transactions over a single association). On the SCU side the Window size proposed is infinite. On the SCP Side any non-infinite maximum size will be accepted.

Table 15: Asynchronous Nature as an Association Initiator

Maximum number of outstanding asynchronous transactions	10
---	----

4.2.3.1.2 Implementation Identifying Information

For Implementation Identifying Information please refer to “

Table 3: Implementation Identifying Information” in the [“Conformance Statement Overview”](#).

4.2.3.2 Association Initiation Policy

4.2.3.2.1 Activity “Send Initial Storage Commitment Request”

4.2.3.2.1.1 Description and Sequencing of Activities

The syngo® MR XA51A serves as a SCU of the Storage Commitment Service Class. After successful transfer of Imaging Objects to a configured Archive, the Storage Commitment SCU initiates an N-Action Request, if Storage Commitment is configured. This request will be sent on a different association than the storage request.

The Storage Commitment Request will be sent out with a delay, in order to ensure that the remote node properly indexes received instances. The delay time is configurable with a default delay of 10 minutes.

The system may issue one N-ACTION Request for a complete set (bundle) of instances or issue one N-ACTION-Request per instance. This behavior is configurable; the default value is “bundled”.

The syngo® MR XA51A will accept the N-Event-Report-Request on the same association if sent immediately after the N-ACTION-Response. However, it will not wait for it. The association is closed after three seconds.

4.2.3.2.1.2 Proposed Presentation Contexts

The syngo® MR XA51A DICOM application supports the presentation contexts listed in the following table for the Storage Commitment Service Class.

Table 16: Proposed Presentation Contexts for Storage Commitment

Abstract Syntax		Transfer Syntax		Role	Ext. Neg.
Name	UID	Name List	UID List		
Storage Commitment Push Model	1.2.840.10008.1.20.1	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		

4.2.3.2.1.3 SOP specific Conformance for SOP classes

The behavior of syngo® MR XA51A when encountering status codes in an N-ACTION response is summarized in Table 17:

Table 17: DICOM Command Response Status Handling Behavior

Service Status	Further Meaning	Error Code	Behavior
Error	Any failure that occurs	Any none null Code	Failure reported to user; corresponding object(s) will be marked as "Archived failed"
Success	All Instances are available on the remote node	0000	Success reported to user; in case failures exist, the corresponding instances will be marked as "Archived failed"

Table 18 below indicates the behavior if exceptions occur:

Table 18: DICOM Command Communication Failure Behavior

Exception	Behavior
Association Negotiation Timeout	Failure reported to user (Timeout configurable; default 30s); the request will be retried
Association Aborted	Failure reported to user; the request will be retried

4.2.3.3 Association Acceptance Policy

For general information regarding the association acceptance policies please see Chapter 4.2.1.3.

4.2.3.3.1 Activity – "Receive Verification Request"

The Storage Commitment AE supports the Verification SOP Class. For further details please see chapter 4.2.1.4.1.

4.2.3.3.2 Activity "Receive Reply to Initial Storage Commitment Request"

4.2.3.3.2.1 Description and Sequencing of Activities

The syngo® MR XA51A supports the reverse role negotiation of the Storage Commitment Service Class as the SCU. It accepts incoming N-EVENT-REPORT-RQ, if they do not arrive on the same association as the N-ACTION-RQ.

The syngo® MR XA51A has a configurable expiration timeout for the TransactionUID. By default, the TransactionUID is 60 minutes.

4.2.3.3.2.2 Accepted Presentation Contexts

The syngo® MR XA51A DICOM application supports the presentation contexts listed in the following table for the Storage Commitment Service Class.

Table 19: Presentation Context Table "Update Flag Information"

Abstract Syntax		Transfer Syntax		Role	Ext. Neg.
Name	UID	Name List	UID List		
Storage	1.2.840.10008.1.20.1	Explicit VR Little Endian	1.2.840.10008.1.2.1	SCP	None
Commitment Push		Explicit VR Big Endian	1.2.840.10008.1.2.2		
Model		Implicit VR Little Endian	1.2.840.10008.1.2		

4.2.3.3.2.3 SOP-specific Conformance Statement for Storage Commitment SOP classes

The Storage Commitment SCU provides standard conformance to the Storage Commitment SOP Class.

4.2.3.3.2.3.1 Storage Commitment Failure Conditions

Table 20 lists conditions upon which an error code is sent in the Failure Reason (0008,1197) Attribute in the Failed SOP Sequence (0008,1198) of the N-EVEN-REPORT-RQ.

Table 20: Storage Commitment Failure Behaviour

Status Code	Description	Behaviour
0110	Processing failure: A general failure in processing the operation was encountered.	
0122	No such object instance: One or more of the elements in the Referenced SOP Instance Sequence was not available.	The modules itself does not handle the Status Codes. Following processing is in place: 1. Logging 2. Tracing 3. Providing the Status Codes to the user of the module All the incoming Status Codes are logged. All the incoming Status Codes can be traced. The activity provides for the users an API to get all the Status Codes
0119	Class / Instance conflict: The SOP Class of an element in the Referenced SOP Instance Sequence did not correspond to the SOP Class registered for this SOP Instance at the SCP.	
0122	Referenced SOP Class not supported: Storage Commitment has been requested for a SOP Instance with a SOP Class that is not supported by the SCP	
0131	Duplicate transaction UID: The Transaction UID of the Storage Commitment Request is already in use.	
0213	Resource limitation: The SCP does not currently have enough resources to store the requested SOP Instance(s).	

4.2.3.3.3 Activity "Receive Initial Storage Commitment Request"

4.2.3.3.3.1 Description and Sequencing of Activities

When receiving an initial Storage Commitment request (N-ACTION-RQ) the syngo® MR XA51A will accept it with an N-ACTION-RSP and trigger a check in the database for the required instances.

Information about success or failure of Storage Commitment will be signaled via the N-EVENT-REPORT primitive.

The SCU is responsible for creating a unique Transaction UID. The SCP will not check whether the UID is already in use or not.

4.2.3.3.3.2 Accepted Presentation Contexts

The syngo® MR XA51A DICOM application supports the presentation contexts listed in the following table for the Storage Commitment Service Class.

Table 21: Acceptable Presentation Contexts for Activity "Receive Commitment Request"

Abstract Syntax		Transfer Syntax		Role	Ext. Neg.
Name	UID	Name List	UID List		
Storage Commitment Push Model	1.2.840.10008.1.20.1	Explicit VR Little Endian	1.2.840.10008.1.2.1	SCP	None
		Explicit VR Big Endian	1.2.840.10008.1.2.2		
		Implicit VR Little Endian	1.2.840.10008.1.2		

4.2.3.3.3.3 SOP-specific Conformance for Storage Commitment SOP classes

There are only 2 different return status codes for the commitment request itself. They indicate only whether the request was successfully received or not.

Table 22: DICOM Command Response Status Handling Behavior

Service Status	Further Meaning	Error Code	Behavior
Success	Success	0000	Image received correctly (success notification is done after receiving, before indexing and storing)
Failure	Unable to Process	Cxxx	Error during instance reception
Failure	Data set does not match SOP Class	A9xx	The data set is not conform to the SOP Class contained in the resource.

4.2.4 Query/Retrieve AE Specification

4.2.4.1 SOP Classes

The Query/Retrieve AE provides Standard Conformance to the SOP Classes listed in “Table 1: Network Services” section “Query/Retrieve” in the [“Conformance Statement Overview”](#).

4.2.4.2 Association Policy

Table 23: Association Policies

Application Context Name	1.2.840.10008.3.1.1.1
PDU size	32 kB ¹
Maximum number of simultaneous associations as an association acceptor	12 ¹
Maximum number of simultaneous associations as an association initiator	unlimited

The syngo® MR XA51A contains a limitation of 512 kB for the maximum PDU size. By default, the PDU size is set to 32kB.

The maximum number of simultaneous receiving associations (SCP) is configurable at run time, based on the system resources available. By default, the maximum number of associations is set to 12.

There is no inherent limit to the number of outgoing associations (SCU), other than limits imposed by the computer operating system.

4.2.4.2.1 Asynchronous Nature

The syngo® MR XA51A supports asynchronous communication (multiple outstanding transactions over a single association). On the SCU side the Window size proposed is infinite. On the SCP Side any non-infinite maximum size will be accepted.

Table 24: Asynchronous Nature as an Association Initiator

Maximum number of outstanding asynchronous transactions	10
--	----

4.2.4.2.2 Implementation Identifying Information

For Implementation Identifying Information please refer to Table 3: Implementation Identifying Information in the [“Conformance Statement Overview”](#).

4.2.4.3 Association Initiation Policy

For general information regarding the association initiation policies please see Chapter 4.2.1.2

4.2.4.3.1 Activity “Send Verification Request”

The Query/Retrieve AE supports the Verification SOP Class. For further details please see chapter 4.2.1.2.1

4.2.4.3.2 Activity “Send Query Request” for Instances

4.2.4.3.2.1 Description and Sequencing of Activities

The syngo® MR XA51A serves as a SCU for the following SOP Classes

- Patient Root Q/R Information Model – FIND SOP Class

¹ Default, the value is configurable

- Study Root Q/R Information Model – FIND SOP Class
- Patient/Study only Q/R Information Model – FIND SOP Class.

Using the attributes specified by the user as Query Keys (in accordance with the query model) the Query SCU initiates a C-FIND RQ and displays the responses to the user.

4.2.4.3.2.2 Proposed Presentation Contexts

The syngo® MR XA51A will propose Presentation Contexts as shown in the following table:

Table 25: Proposed Presentation Contexts for Query

Abstract Syntax		Transfer Syntax		Role	Ext. Neg.
Name	UID	Name List	UID List		
Patient Root Query/Retrieve Information Model – FIND	1.2.840.10008.5.1.4.1.2.1.1	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	Yes
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		
Study Root Query/ Retrieve Information Model – FIND	1.2.840.10008.5.1.4.1.2.2.1	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	Yes
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		
Patient/Study Only Query/ Retrieve Information Model – FIND	1.2.840.10008.5.1.4.1.2.3.1	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		

Table 26: Extended Negotiation as an SCU

Name	UID	Extended Negotiation
Patient Root Query/Retrieve Information Model – FIND	1.2.840.10008.5.1.4.1.2.1.1	Relational Query will be negotiated as defined in DICOM PS3.4
Study Root Query/Retrieve Information Model – FIND	1.2.840.10008.5.1.4.1.2.2.1	Relational Query will be negotiated as defined in DICOM PS3.4

4.2.4.3.2.3 SOP Specific Conformance Statement to Query SOP classes

The syngo® MR XA51A checks for the following status codes in the Query SCP's C-FIND-RSP:

Table 27: DICOM Command Response Status Handling Behavior

Service Status	Further Meaning	Error Code	Behavior
Failure	e.g. Out of Resources; Cancellation; Identifier does not match SOP Class; Unable to process	Any non null Code	Failure reported to user

Pending	All optional keys are supported the same manner as Required Keys.	FF00	Pending state is indicated to user
	Matching Operation continues; some of the optional keys were not supported the same way as the required keys	FF01	Pending state is indicated to user
Success	Query has been performed successfully.	0000	Success reported to user

Table 28 below indicates the behavior if exceptions occur:

Table 28: DICOM Command Communication Failure Behavior

Exception	Behavior
Timeout	Failure reported to user (Timeout configurable; default 30s)
Association Aborted	Failure reported to user

The *syngo*® MR XA51A supports the following query levels:

- Study
- Series

Matching Keys on Instance Level is not supported by the *syngo*® MR XA51A as SCU.

The following table lists the various attributes at Study and Series level, which can be used for hierarchical queries as well as return values for display. The display capabilities are highly configurable and “yes” indicates that it is possible to configure display of the data:

Table 29: Attributes supported for Study/Series Query - SCU

Attribute Name	Tag	Type	User input	UI
Study Level				
Patient's Name	(0010,0010)	O	enter value	Yes
Patient ID	(0010,0020)	O	enter value	Yes
Issuer of Patient ID	(0010,0021)	O	enter value	Yes
Patient's Birth Date	(0010,0030)	O	enter value	Yes
Patient's Birth Time	(0010,0032)	O	enter value	Yes
Patient's Sex	(0010,0040)	O	enter value	Yes
Accession Number	(0008,0050)	O	enter value	Yes
Study ID	(0020,0010)	O	enter value	Yes
Study Instance UID	(0020,000D)	U	enter value	Yes
Study Date	(0008,0020)	O	enter value	Yes
Study Time	(0008,0030)	O	enter value	Yes
Referring Physician's Name	(0008,0090)	O	enter value	Yes
Study Description	(0008,1030)	O	enter value	Yes
Number of Study related Instances	(0020,1208)	O	-	Yes

Attribute Name	Tag	Type	User input	UI
Modalities in Study	(0008,0061)	O	enter value	Yes
Number of Study Related Series	(0020,1206)	O	-	Yes
Series Level				
Modality	(0008,0060)	O	enter value	Yes
Series Date	(0008,0021)	O	enter value	Yes
Series Time	(0008,0031)	O	enter value	Yes
Number of Series related Instances	(0020,1209)	O	-	Yes
Series Number	(0020,0011)	O	enter value	Yes
Series Description	(0008,103E)	O	enter value	Yes
Request Attributes Sequence \ Requested Procedure ID	(0040,0275) \ (0040,1001)	O	enter value	Yes
Request Attributes Sequence \ Scheduled Procedure Step ID	(0040,0275) \ (0040,0009)	O	enter value	Yes
Performed Procedure Step Start Date	(0040,0244)	O	enter value	Yes
Performed Procedure Step Start Time	(0040,0245)	O	enter value	Yes
Series Instance UID	(0020,000E)	U	-	Yes

4.2.4.3.3 Activity "Send Move Request"

4.2.4.3.3.1 Description and Sequencing of Activities

The *syngo*® MR XA51A serves as a SCU for the following SOP Classes

- Patient Root Q/R Information Model – MOVE SOP Class
- Study Root Q/R Information Model – MOVE SOP Class
- Patient/Study only Q/R Information Model – MOVE SOP Class.

The C-MOVE-RQ is used to retrieve the selected imaging objects. The Retrieve AE supports the query model Patient Root, Study Root, Patient/Study Root.

4.2.4.3.3.2 Proposed Presentation Contexts

The *syngo*® MR XA51A proposes Presentation Contexts shown in the following table:

Table 30: Proposed Presentation Contexts for Retrieve and Activity "Send Move Request"

Abstract Syntax		Transfer Syntax		Role	Ext. Neg.
Name	UID	Name List	UID List		
Patient Root Query/Retrieve Information Model – MOVE	1.2.840.10008.5.1.4.1.2.1.2	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		
	1.2.840.10008.5.1.4.1.2.2.2	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None

Study Root Query/Retrieve Information Model – MOVE		Explicit VR Little Endian	1.2.840.10008.1.2.1	SCU	None
		Explicit VR Big Endian	1.2.840.10008.1.2.2		
Patient/Study Only Query/Retrieve Information Model – MOVE	1.2.840.10008.5.1.4.1.2.3.2	Implicit VR Little Endian	1.2.840.10008.1.2		
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		

4.2.4.3.3.3 SOP Specific Conformance Statement for Move SCU Classes

The behavior of *syngo*® MR XA51A when encountering status codes in a C-MOVE RSP is summarized in Table 31

Table 31: DICOM Command Response Status Handling Behavior

Service Status	Further Meaning	Error Code	Behavior
Error	e.g. Out of Resources; Cancellation; Identifier does not match SOP Class; Unable to process; Move destination unknown	Any none null Code	Failure reported to user
Pending	Move Operation continues	FF00	Operation continues in background
Success	Move has been performed successfully.	0000	Success reported to user

Table 32 below indicates the behavior if exceptions occur:

Table 32: DICOM Command Communication Failure Behavior

Exception	Behavior
Timeout	Failure reported to user (Timeout configurable; default 30s)
Association Aborted	Failure reported to user

4.2.4.4 Association Acceptance Policy

The *syngo*® MR XA51A provides standard conformance as an SCP of the C-FIND and C-MOVE SOP Classes.

Latency

The *syngo*® MR XA51A handles the Query/Retrieve equally using the *first come first served* principle. Latency can occur if the hardware capacity is not sufficient for serving all incoming requests immediately. Both factors, that can lead to latency (hardware capacity and number of incoming request) must be managed by the user of the *syngo*® MR XA51A.

The *syngo*® MR XA51A does not support Storage Media File-Set ID and UID attributes in the N-ACTION message.

4.2.4.4.1 Activity “Receive Query Request”

4.2.4.4.1.1 Description and Sequencing of Activities

The *syngo*® MR XA51A serves as an SCP for the following SOP Classes

- Patient Root Q/R Information Model – FIND SOP Class

- Study Root Q/R Information Model – FIND SOP Class
- Patient/Study Only Q/R Information Model – FIND SOP Class

Using the attributes specified by the user as Query Keys (in accordance with the query model) the Query SCP accepts a C-FIND-RQ and provides the responses for the requesting node.

4.2.4.4.1.2 Accepted Presentation Contexts

The *syngo*® MR XA51A DICOM application supports the presentation contexts listed in the following table for the Query/Retrieve Service Class:

Table 33: Acceptable Presentation Contexts for “Receive Query Request”

Abstract Syntax		Transfer Syntax		Role	Ext. Neg.
Name	UID	Name List	UID List		
Patient Root Query/ Retrieve Information Model – FIND	1.2.840.10008.5.1.4.1.2.1.1	Implicit VR Little Endian	1.2.840.10008.1.2	SCP	Yes
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		
Study Root Query/ Retrieve Information Model – FIND	1.2.840.10008.5.1.4.1.2.2.1	Implicit VR Little Endian	1.2.840.10008.1.2	SCP	Yes
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		
Patient/Study Only Query/ Retrieve Information Model – FIND	1.2.840.10008.5.1.4.1.2.3.1	Implicit VR Little Endian	1.2.840.10008.1.2	SCP	None
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		

Table 34: Extended Negotiation as an SCP

Name	UID	Extended Negotiation
Patient Root Query/Retrieve Information Model – FIND	1.2.840.10008.5.1.4.1.2.1.1	Relational Query will be negotiated as defined in DICOM PS3.4
Study Root Query/Retrieve Information Model – FIND	1.2.840.10008.5.1.4.1.2.2.1	Relational Query will be negotiated as defined in DICOM PS3.4

4.2.4.4.1.3 SOP-specific Conformance for Query/Retrieve SOP classes

The *syngo*® MR XA51A provides one of the following status codes in the C-FIND-RSP:

Table 35: DICOM Command Response Status Handling Behavior

Service Status	Further Meaning	Error Code
Failure	e.g. Out of Resources; Cancellation; Identifier does not match SOP Class; Unable to process	Any none null Code
Pending	All optional keys are supported the same manner as Required Keys.	FF00
	Matching Operation continues; some of the optional keys were not supported the same way as the required keys	FF01
Success	Query has been performed successfully.	0000

The *syngo*® MR XA51A supports the following query levels:

- Study
- Series

Matching Keys on Instance Level is not supported by the *syngo*® MR XA51A as SCP.

The following table lists the various attributes at Study and Series level, which can be used for hierarchical queries as well as return values for display.

Table 36: Attributes supported for Study/Series Query – SCP

Attribute Name	Tag	Type	User input	UI
Study Level				
Patient's Name	(0010,0010)	O	enter value	Yes
Patient ID	(0010,0020)	O	enter value	Yes
Issuer of Patient ID	(0010,0021)	O	enter value	Yes
Patient's Birth Date	(0010,0030)	O	enter value	Yes
Patient's Birth Time	(0010,0032)	O	enter value	Yes
Patient's Sex	(0010,0040)	O	enter value	Yes
Accession Number	(0008,0050)	O	enter value	Yes
Study ID	(0020,0010)	O	enter value	Yes
Study Instance UID	(0020,000D)	U	enter value	Yes
Study Date	(0008,0020)	O	enter value	Yes
Study Time	(0008,0030)	O	enter value	Yes
Referring Physician's Name	(0008,0090)	O	enter value	Yes
Study Description	(0008,1030)	O	enter value	Yes
Number of Study related Instances	(0020,1208)	O	-	Yes
Modalities in Study	(0008,0061)	O	enter value	Yes
Number of Study Related Series	(0020,1206)	O	-	Yes
Series Level				

Attribute Name	Tag	Type	User input	UI
Modality	(0008,0060)	O	enter value	Yes
Series Date	(0008,0021)	O	enter value	Yes
Series Time	(0008,0031)	O	enter value	Yes
Number of Series related Instances	(0020,1209)	O	-	Yes
Series Number	(0020,0011)	O	enter value	Yes
Series Description	(0008,103E)	O	enter value	Yes
Request Attributes Sequence \ Requested Procedure ID	(0040,0275) \ (0040,1001)	O	enter value	Yes
Request Attributes Sequence \ Scheduled Procedure Step ID	(0040,0275) \ (0040,0009)	O	enter value	Yes
Performed Procedure Step Start Date	(0040,0244)	O	enter value	Yes
Performed Procedure Step Start Time	(0040,0245)	O	enter value	Yes
Series Instance UID	(0020,000E)	U	-	Yes

4.2.4.4.2 Activity “Receive Move Request”

4.2.4.4.2.1 Description and Sequencing of Activities

The syngo® MR XA51A serves as an SCP for the following SOP Classes

- Patient Root Query/Retrieve Information Model – MOVE SOP Class
- Study Root Query/Retrieve Information Model – MOVE SOP Class
- Patient/Study Only Query/Retrieve Information Model – MOVE SOP Class

The C-MOVE-RQ is used to retrieve the selected imaging objects. The Retrieve AE supports the query model Patient Root, Study Root, Patient/Study Root.

4.2.4.4.2.2 Accepted Presentation Contexts

The syngo® MR XA51A accepts Presentation Contexts shown in the following table:

Table 37: Acceptable Presentation Contexts for Retrieve and Activity “MOVE SCP”

Abstract Syntax		Transfer Syntax		Role	Ext. Neg.
Name	UID	Name List	UID List		
Patient Root Query/Retrieve Information Model – MOVE	1.2.840.10008.5.1.4.1.2.1.2	Implicit VR Little Endian	1.2.840.10008.1.2	SCP	None
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		
Study Root Query/Retrieve Information Model – MOVE	1.2.840.10008.5.1.4.1.2.2.2	Implicit VR Little Endian	1.2.840.10008.1.2	SCP	None
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		
Patient/Study Root Query/Retrieve Information Model – MOVE	1.2.840.10008.5.1.4.1.2.3.2	Implicit VR Little Endian	1.2.840.10008.1.2	SCP	None
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		

4.2.4.4.2.3 SOP-specific Conformance for MOVE SOP classes

The behavior of syngo® MR XA51A when encountering status codes in a C-MOVE-RSP is summarized in Table 38

Table 38: DICOM Command Response Status Handling Behavior

Service Status	Further Meaning	Error Code
Error	e.g. Out of Resources; Cancellation; Identifier does not match SOP Class; Unable to process; Move destination unknown	Any none null Code
Pending	Move Operation continues	FF00
Success	Move has been performed successfully.	0000

4.2.5 Modality Worklist AE Specification

4.2.5.1 SOP Classes

The Modality Worklist AE provides Standard Conformance to the SOP Class “Modality Worklist Information Model – FIND” as it is listed in “Table 1: Network Services” in the [“Conformance Statement Overview”](#).

4.2.5.2 Association Policy

Table 39: Association Policies

Application Context Name	1.2.840.10008.3.1.1.1
PDU size	32 kB ¹
Maximum number of simultaneous associations as an association acceptor	12 ¹
Maximum number of simultaneous associations as an association initiator	unlimited

The *syngo*® MR XA51A contains a limitation of 512 kB for the maximum PDU size. By default, the PDU size is set to 32kB.

The maximum number of simultaneous receiving associations (SCP) is configurable at run time, based on the system resources available. By default, the maximum number of associations is set to 12.

There is no inherent limit to the number of outgoing associations (SCU), other than limits imposed by the computer operating system.

4.2.5.2.1 Asynchronous Nature

The *syngo*® MR XA51A supports asynchronous communication (multiple outstanding transactions over a single association). On the SCU side the Window size proposed is infinite. On the SCP Side any non-infinite maximum size will be accepted.

Table 40: Asynchronous Nature as an Association Initiator

Maximum number of outstanding asynchronous transactions	10
--	----

4.2.5.2.2 Implementation Identifying Information

For Implementation Identifying Information please refer to Table 3: Implementation Identifying Information

Table 3: Implementation Identifying Information in the [“Conformance Statement Overview”](#).

4.2.5.3 Association Initiation Policy

4.2.5.3.1 Activity “Querying a Remote Node” for Modality Worklist

4.2.5.3.1.1 Description and Sequencing of Activities

The *syngo*® MR XA51A serves as a SCU of the Modality Worklist service. It performs worklist queries by issuing a C-FIND-RQ at regular intervals. In addition, a worklist request can be triggered manually.

4.2.5.3.1.2 Proposed Presentation Contexts

The *syngo*® MR XA51A will propose Presentation Contexts as shown in the following table:

¹ Default, the value is configurable

Table 41: Proposed Presentation Contexts for Worklist

Abstract Syntax		Transfer Syntax		Ext.	
Name	UID	Name List	UID List	Role	Neg.
Modality Worklist- FIND	1.2.840.10008.5.1.4.31	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		

4.2.5.3.1.3 SOP Specific Conformance for SOP Classes

Search Key Attributes of the Worklist C-FIND

The *syngo*® MR XA51A Modality Worklist SCU supports “broad worklist queries” with all required search keys. The following tables describe the “broad query” search keys that the SCU supports. The list is configurable in ‘DICOM Modality Worklist Query’.

Table 42: Broad Query search keys

Attribute Name	Tag	Matching Key Type	Query Value
Scheduled Procedure Step			
Scheduled Procedure Step Sequence	(0040,0100)	R	
>Modality	(0008,0060)	R	<configured by Modality> or “*”
>Scheduled Station AE Title	(0040,0001)	R	<own AET> or “*” ¹
>Scheduled Procedure Step Start Date	(0040,0002)	R	Range from UI 2
>Scheduled Station Name	(0040,0010)	O	
>Scheduled Procedure Step Location	(0040,0011)	O	
>Scheduled Procedure Step Status	(0040,0020)	O	
>Scheduled Performing Physician’s Name	(0040,0006)	O	
Requested Procedure Description	(0032,1060)	O	
Requested Procedure Priority	(0040,1003)	O	
Patient Transport Arrangements	(0040,1004)	O	
Requested Procedure Comments	(0040,1400)	O	
Requested Procedure Code Sequence	(0032,1064)	O	
>Code Value	(0008,0100)	O	
Requesting Physician	(0032,1032)	O	

¹ This depends on user configuration (Administration Portal->Technical Configuration->DICOM Nodes->Local DICOM Node->Worklist) if the “own AET” is provided or not.

² A time window can be configured by defining how many days to look into the past and into the future (Administration Portal-> Technical Configuration->DICOM Nodes->Local DICOM Node->Worklist)

Attribute Name	Tag	Matching Key Type	Query Value
Referring Physicians Name	(0008,0090)	O	
Current Patient Location	(0038,0300)	O	
Pregnancy Status	(0010, 21C0)	O	
Medical Alerts	(0010,2000)	O	
Allergies	(0010,2110)	O	

Return Key Attributes of the Modality Worklist C-FIND

The *syngo*® MR XA51A Modality Worklist SCU supports worklist queries with return key attributes of all types. The following tables describe the return keys that the SCU supports.

An “yes” in the **UI** column indicates that the attribute may be visualized when browsing the Worklist results with the Browser. The Browser display is additionally influenced by the related Browser configuration.

Table 43: Modality Worklist C-Find Return keys

Attribute Name	Tag	Return Key Type	UI	Notes
SOP Common				
Specific Character Set	(0008,0005)	1C	No	
Scheduled Procedure Step				
Scheduled Procedure Step Sequence	(0040,0100)	1	No	
>Modality	(0008,0060)	1	Yes	
>Scheduled Station AE Title	(0040,0001)	1		“Scheduled Station AE Title” is taken as default for “Performed Station AE Title”
>Scheduled Procedure Step Start Date	(0040,0002)	1	Yes	
>Scheduled Procedure Step Start Time	(0040,0003)	1	Yes	
>Scheduled Procedure Step End Date	(0040,0004)	3	No	
>Scheduled Procedure Step End Time	(0040,0005)	3	No	
>Scheduled Performing Physician’s Name	(0040,0006)	1	Yes	“Scheduled Performing Physician’s Name” is taken as default for “Performing Physician’s Name”
>Scheduled Procedure Step Description	(0040,0007)	1C	Yes	“Scheduled Procedure Step Description” is taken as default for “Performed Procedure Step Description”
>Scheduled Protocol Code Sequence	(0040,0008)	1C	No	Uses universal sequence match “Scheduled Protocol Code Sequence” is taken as default for “Performed Protocol Code Sequence”
>>Code Value	(0008,0100)	1C	No	

Attribute Name	Tag	Return	UI	Notes
		Key Type		
>>Coding Scheme Designator	(0008,0102)	1C	No	
>>Coding Scheme Version	(0008,0103)	3	No	
>>Code Meaning	(0008,0104)	3	No	
>>Mapping Resource	(0008,0105)	3	No	
>>Context Group Version	(0008,0106)	3	No	
>>Context Group Local Version	(0008,0107)	3	No	
>>Context Group Extension Flag	(0008,010B)	3	No	
>>Context Group Extension Creator UID	(0008,010D)	3	No	
>>Context Identifier	(0008,010F)	3	No	
>Scheduled Procedure Step ID	(0040,0009)	1	Yes	"Scheduled Procedure Step ID" is taken as default for "Performed Procedure Step ID"
>Scheduled Station Name	(0040,0010)	2	Yes	
>Scheduled Procedure Step Location	(0040,0011)	2	No	"Scheduled Procedure Step Location" is taken as default for "Performed Location"
>Scheduled Procedure Step Status	(0040,0020)	3	No	
>Comments on the Scheduled Procedure Step	(0040,0400)	3	No	
Requested Procedure				
Study Date	(0008,0020)	3	No	
Study Time	(0008,0030)	3	No	
Referenced Study Sequence	(0008,1110)	2	No	Uses universal sequence match
>Referenced SOP Class UID	(0008,1150)	1C	No	
>Referenced SOP Instance UID	(0008,1155)	1C	No	
Study Instance UID	(0020,000D)	1	No	
Requested Procedure Description	(0032,1060)	1C	Yes	
				Uses universal sequence match
Requested Procedure Code Sequence	(0032,1064)	1C	No	"Requested Procedure Code Sequence" is taken as default for "Procedure Code Sequence"
>Code Value	(0008,0100)	1C	No	
>Coding Scheme Designator	(0008,0102)	1C	No	
>Coding Scheme Version	(0008,0103)	3	No	
>Code Meaning	(0008,0104)	3	No	
>>Mapping Resource	(0008,0105)	3	No	

Attribute Name	Tag	Return		Notes
		Key	UI	
		Type		
>>Context Group Version	(0008,0106)	3	No	
>>Context Group Local Version	(0008,0107)	3	No	
>>Context Group Extension Flag	(0008,010B)	3	No	
>>Context Group Extension Creator UID	(0008,010D)	3	No	
>>Context Identifier	(0008,010F)	3	No	
Requested Procedure ID	(0040,1001)	1	Yes	"Requested Procedure ID" is taken as default for "Study ID"
Reason for the Requested Procedure	(0040,1002)	3	No	
Requested Procedure Priority	(0040,1003)	2	Yes	
Patient Transport Arrangements	(0040,1004)	2	No	
Confidentiality Code	(0040,1008)	3	No	
Reporting Priority	(0040,1009)	3	Yes	
Names of intended Recipients of Results	(0040,1010)	3	No	
Requested Procedure Comments	(0040,1400)	3	No	
Imaging Service Request				
Accession Number	(0008,0050)	2	Yes	
Referring Physician's Name	(0008,0090)	2	Yes	
Requesting Physician	(0032,1032)	2	Yes	
Requesting Service	(0032,1033)	3	No	
Issuing Date of Imaging Service Request	(0040,2004)	3	No	
Issuing Time of Imaging Service Request	(0040,2005)	3	No	
Placer Order Number / Imaging Service Request	(0040,2016)	3	No	Old tag (0040,2006) is retired and not used.
Filler Order Number / Imaging Service Request	(0040,2017)	3	No	Old tag (0040,2007) is retired and not used.
Order entered by ...	(0040,2008)	3	No	
Order Enterer's location	(0040,2009)	3	No	
Order Callback Phone Number	(0040,2010)	3	No	
Imaging Service Request Comments	(0040,2400)	3	No	
Visit Identification				
Admission ID	(0038,0010)	2	Yes	
Issuer of Admission ID	(0038,0011)	3	No	
Institution Name	(0008,0080)	3	No	
Institution Address	(0008,0081)	3	No	
Visit Status				

Attribute Name	Tag	Return	UI	Notes
		Key Type		
Current Patient Location	(0038,0300)	2	Yes	
Visit Admission				
Admitting Diagnosis Description	(0008,1080)	3	Yes	
Admitting Date	(0038,0020)	3	No	
Patient Identification				
Patient's Name	(0010,0010)	1	Yes	
Patient ID	(0010,0020)	1	Yes	
Issuer of Patient ID	(0010,0021)	3	No	
Other Patient IDs	(0010,1000)	3	Yes	
Other Patient Names	(0010,1001)	3	Yes	
Patient's Birth Name	(0010,1005)	3	No	
Patient Demographic				
Patient's Birth Date	(0010,0030)	2	Yes	
Patient's Birth Time	(0010,0032)	3	No	
Patient's Sex	(0010,0040)	2	Yes	
Patient's Insurance Plan Code Sequence	(0010,0050)	3	No	Uses universal sequence match
>Code Value	(0008,0100)	1C	No	
>Coding Scheme Designator	(0008,0102)	1C	No	
>Coding Scheme Version	(0008,0103)	3	No	
>Code Meaning	(0008,0104)	3	No	
Patient's Age	(0010,1010)	3	No	
Patient's Size	(0010,1020)	3	Yes	
Patient's Weight	(0010,1030)	2	Yes	
Patient's Address	(0010,1040)	3	Yes	
Military Rank	(0010,1080)	3	Yes	
Branch of Service	(0010,1081)	3	No	
Ethnic Group	(0010,2160)	3	Yes	
Patient Comments	(0010,4000)	3	Yes	
Patient Medical				
Medical Alerts	(0010,2000)	2	Yes	
Allergies	(0010,2110)	2	Yes	
Pregnancy Status	(0010,21C0)	2	Yes	
Smoking Status	(0010,21A0)	3	Yes	
Last Menstrual Date	(0010,21D0)	3	Yes	

Attribute Name	Tag	Return	UI	Notes
		Key Type		
Additional Patient History	(0010,21B0)	3	Yes	
Special Needs	(0038,0050)	2	Yes	

The behavior of the *syngo*® MR XA51A when encountering status codes in a C-FIND RSP is summarized in Table 44.

Table 44: DICOM Command Response Status Handling Behavior

Service Status	Further Meaning	Error Code	Behavior
Error	e.g. Out of Resources; Cancellation; Identifier does not match SOP Class; Unable to process	Any none null Code	Failure reported to user
Pending	All optional keys are supported the same manner as Required Keys.	FF00	Pending state is indicated to user
	Matching Operation continues; some of the optional keys were not supported the same way as the required keys	FF01	Pending state is indicated to user
Success	Query has been performed successfully.	0000	Success reported to user

Table 45 below indicates the behavior if exceptions occur:

Table 45: DICOM Command Communication Failure Behavior

Exception	Behavior
Timeout	Failure reported to user (Timeout configurable; default 30s)
Association Aborted	Failure reported to user

4.2.5.4 Association Acceptance Policy

The *syngo*® MR XA51A does not provide the functionality of a SCP of the Modality Worklist – Find SOP Class.

4.2.6 Modality Performed Procedure Step AE Specification

4.2.6.1 SOP Classes

The Modality Performed Procedure Step AE provides Standard Conformance to the SOP Class “Modality Performed Procedure Step” as it is listed in “Table 1: Network Services” section “Worklist Management” in the [“Conformance Statement Overview”](#).

4.2.6.2 Association Policy

Table 46: Association Policies

Application Context Name	1.2.840.10008.3.1.1.1
--------------------------	-----------------------

PDU size	32 kB ¹
Maximum number of simultaneous associations as an association acceptor	12 ¹
Maximum number of simultaneous associations as an association initiator	unlimited

The syngo® MR XA51A contains a limitation of 512 kB for the maximum PDU size. By default, the PDU size is set to 32kB.

The maximum number of simultaneous receiving associations (SCP) is configurable at run time, based on the system resources available. By default, the maximum number of associations is set to 12.

There is no inherent limit to the number of outgoing associations (SCU), other than limits imposed by the computer operating system.

4.2.6.2.1 Asynchronous Nature

The syngo® MR XA51A supports asynchronous communication (multiple outstanding transactions over a single association). On the SCU side the Window size proposed is infinite. On the SCP Side any non-infinite maximum size will be accepted.

Table 47: Asynchronous Nature as an Association Initiator

Maximum number of outstanding asynchronous transactions	10
--	----

4.2.6.2.2 Implementation Identifying Information

For Implementation Identifying Information please refer to Table 3: Implementation Identifying Information in the [“Conformance Statement Overview”](#).

4.2.6.3 Association Initiation Policy

4.2.6.3.1 Activity “Create Modality Performed Procedure Step”

4.2.6.3.1.1 Description and Sequencing of Activities

The syngo® MR XA51A serves as a SCU of the Modality Performed Procedure Step SOP Class. It sends N-CREATE-RQ to inform the Information System that a Procedure Step has been started.

4.2.6.3.1.2 Accepted Presentation Contexts

The syngo® MR XA51A proposes Presentation Contexts as shown in the following table:

Table 48: Acceptable Presentation Contexts Activity “Create MPPS”

Abstract Syntax		Transfer Syntax		Ext.	
Name	UID	Name List	UID List	Role	Neg.
Modality Performed Procedure Step	1.2.840.10008.3.1.2.3.3	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		

¹ Default, the value is configurable

4.2.6.3.1.3 SOP specific Conformance for MPPS SOP class

The behavior of *syngo*® MR XA51A when encountering status codes in an N-CREATE-RSP is summarized in Table 49:

Table 49: MPPS N-CREATE-RSP Status Handling Behavior

Service Status	Further Meaning	Error Code	Behavior
Error	MPPS creation request could not be processed.	Any none null Code	MPPS is not created.
Success	MPPS creation request processed successfully.	0000	MPPS is created.

4.2.6.3.2 Activity “Update Modality Performed Procedure Step”

4.2.6.3.2.1 Description and Sequencing of Activities

When the procedure step has been finished, the *syngo*® MR XA51A sends N-SET-RQ to inform the Information System about the finalization of the procedure step (COMPLETED or DISCONTINUED). Table 50 shows the Discontinuation Reasons supported.

Table 50: Modality PPS Discontinuation Reasons supported

Code Value	Code Meaning
110500	Doctor cancelled procedure
110501	Equipment failure
110502	Incorrect procedure ordered
110503	Patient allergic to media/contrast
110504	Patient died
110505	Patient refused to continue procedure
110506	Patient taken for treatment or surgery
110507	Patient did not arrive
110508	Patient pregnant
110509	Change of procedure for correct charging
110510	Duplicate order
110511	Nursing unit cancel
110512	Incorrect side ordered
110513	Discontinued for unspecified reason
110514	Incorrect worklist entry selected
110515	Patient condition prevented continuing
110516	Equipment change
110500	Doctor cancelled procedure

4.2.6.3.2.2 Proposed Presentation Contexts

The *syngo*® MR XA51A proposes Presentation Contexts as shown in the following table:

Table 51: Acceptable Presentation Contexts Activity “Update MPPS”

Abstract Syntax		Transfer Syntax		Role	Ext. Neg.
Name	UID	Name List	UID List		
Modality Performed Procedure Step	1.2.840.10008.3.1.2.3.3	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
		Explicit VR Little Endian	1.2.840.10008.1.2.1		
		Explicit VR Big Endian	1.2.840.10008.1.2.2		

4.2.6.3.2.3 SOP specific Conformance for MPPS SOP class

The behavior of *syngo*® MR XA51A when encountering status codes in an N-SET-RSP is summarized in Table 52:

Table 52: MPPS N-SET Response Status Handling Behavior

Service Status	Further Meaning	Error Code	Behavior
Error	MPPS update request could not be processed.	Any none null Code	MPPS is not updated.
Success	MPPS update request could processed successfully.	0000	MPPS is updated.

4.2.6.4 Association Acceptance Policy

The *syngo*® MR XA51A does not provide the functionality of a SCP of the Modality Performed Procedure Step SOP Class.

4.2.7 Print AE Specification

4.2.7.1 SOP Classes

The Print AE provides Standard Conformance to the SOP Classes listed in “Table 1: Network Services” section “Print Management” in the [“Conformance Statement Overview”](#).

4.2.7.2 Association Policy

Table 53: Association Policies

Application Context Name	1.2.840.10008.3.1.1.1
PDU size	32 kB ¹
Maximum number of simultaneous associations as an association acceptor	12 ¹

¹ Default, the value is configurable

Maximum number of simultaneous associations as an association initiator	unlimited
--	-----------

The syngo® MR XA51A contains a limitation of 512 kB for the maximum PDU size. By default, the PDU size is set to 32kB.

The maximum number of simultaneous receiving associations (SCP) is configurable at run time, based on the system resources available. By default, the maximum number of associations is set to 12.

There is no inherent limit to the number of outgoing associations (SCU), other than limits imposed by the computer operating system.

4.2.7.2.1 Asynchronous Nature

The syngo® MR XA51A supports asynchronous communication (multiple outstanding transactions over a single association). On the SCU side the Window size proposed is infinite. On the SCP Side any non-infinite maximum size will be accepted.

Table 54: Asynchronous Nature as an Association Initiator

Maximum number of outstanding asynchronous transactions	10
--	----

4.2.7.3 Association Initiation Policy

4.2.7.3.1 Activity Print Film

4.2.7.3.1.1 Description and Sequencing of Activities

Whenever a film-sheet is prepared by the user, it is forwarded to the Printer Job queue. As soon as the associated Printer device is available the job is activated and an association is established.

After the film sheet is internally processed, converted to a Standard/1,1 layout and the page image is sent to the printer, the status is controlled by awaiting any N-EVENT-REPORT message throughout the transfer until the last image or film-sheet is sent.

If the response from the remote application contains a status other than Success or Warning the printing is stopped and the job status is set to Aborted.

4.2.7.3.1.2 Proposed Presentation Context

The syngo® MR XA51A proposes Presentation Contexts as shown in the following table:

Table 55: Presentation Contexts for the Activity "Print Film"

Abstract Syntax		Transfer Syntax		Role	Ext. Neg.
Name	UID	Name List	UID List		
Basic Grayscale Print Management Meta SOP Class	1.2.840.10008.5.1.1.9	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
Basic Color Print Management Meta SOP Class	1.2.840.10008.5.1.1.18	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
Basic Film Session SOP Class	1.2.840.10008.5.1.1.1	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
Basic Film Box SOP Class	1.2.840.10008.5.1.1.2	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
Basic Grayscale Image Box SOP Class	1.2.840.10008.5.1.1.4	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None

Basic Color Image Box SOP Class	1.2.840.10008.5.1.1.4.1	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
Printer SOP Class	1.2.840.10008.5.1.1.16	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
Print Job SOP Class	1.2.840.10008.5.1.1.14	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None
Presentation LUT SOP Class	1.2.840.10008.5.1.1.23	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None

4.2.7.3.1.3 SOP Specific Conformance

The *syngo*® MR XA51A Print SCU conforms to the DICOM Basic Grayscale Print Management Meta SOP Class and the Basic Color Print Management Meta SOP Class.

The application uses a configuration platform to define the properties of the connected DICOM SCP, e.g.:

- supported film sizes of the connected DICOM SCP
- supported film formats of the DICOM SCP

The printing is only suspended in the case of a failure return status of the SCP.

Basic Film Session SOP Class

The Basic Film Session information object definition describes all the user-defined parameters, which are common for all the films of a film session. The Basic Film Session refers to one or more Basic Film Boxes that are printed on one hardcopy printer.

The *syngo*® MR XA51A Print Management SCU supports the following DIMSE Service elements for the Basic Film Session SOP Class as SCU:

- N-CREATE
- N-DELETE

The Basic Film Session SOP Class N-CREATE-RQ (SCU) uses the attributes listed in the table below:

Table 56: Attributes for the N-CREATE-RQ of the Basic Film Session

Attribute Name	Tag	Usage SCU	Supported Values
Number of Copies	(2000,0010)	U	1
Medium Type	(2000,0030)	U	BLUE FILM
			CLEAR FILM
			PAPER
			MAMMO BLUE FILM
			MAMMO CLEAR FILM

The Affected SOP Instance UID received with N-CREATE-RSP message will be kept internally and used for later requests (e.g. N-DELETE-RQ) on the Basic Film Session.

The Basic Film Session SOP class interprets the status codes (from N-CREATE-RSP messages) listed in the table below:

Table 57: N-CREATE-RSP Status Handling Behavior for the Basic Film Session

Service Status	Further Meaning	Error Codes	Behavior
Warning	Memory Allocation not supported	B600	Print job continues, warning is logged
Success	Film session successfully created	0000	Print job continues

The N-DELETE-RQ on the Basic Film Session SOP Class is used to remove the complete Basic Film Session SOP Instance hierarchy.

Basic Film Box SOP Class

The Basic Film Box information object definition describes all user-defined parameters of one film of the film session including presentation parameters, which are common for all images on a given film sheet.

The Basic Film Box refers to one or more Image Boxes.

The *syngo*® MR XA51A Print Management SCU supports the following DIMSE Service elements for the Basic Film Box SOP Class as SCU:

- N-CREATE
- N-ACTION
- N-DELETE

The Basic Film Box SOP Class N-CREATE-RQ message uses the attributes listed below. The actual values for each attribute depend on DICOM printer configuration within the *syngo*® MR XA51A DICOM Print Management SCU:

Table 58: Attributes for the N-CREATE-RQ of the Basic Film Session

Attribute Name	Tag	Usage SCU	Supported Values
Image Display Format	(2010,0010)	M	STANDARD\1,1
Referenced Film Session Sequence	(2010,0500)	M	
> Referenced SOP Class UID	(0008,1150)	M	1.2.840.10008.5.1.1.1
> Referenced SOP Instance UID	(0008,1155)	M	
Film Orientation	(2010,0040)	M	PORTRAIT, LANDSCAPE
Film Size ID	(2010,0050)	M	8INX10IN, 10INX12IN, 10INX14IN, 11INX14IN, 14INX14IN, 14INX17IN, 24CMX24CM, 24CMX30CM
Magnification Type	(2010,0060)	M	BILINEAR, CUBIC, NONE, REPLICATE
Border Density	(2010,0100)	U	BLACK, WHITE
Max Density	(2010,0130)	U	0 < Value
Min Density	(2010,0120)	U	0 < Value < 50
Required if Presentation LUT is present			
Reflective Ambient Light	(2010,0160)	U	0 < Value
Illumination	(2010,015E)	U	0 < Value
Referenced Presentation LUT Sequence	(2050,0500)	U	

For Page Mode printing, the Image Display format used is Standard\1,1.

The N-CREATE-RSP message from the Print SCP includes the Referenced Image Box Sequence with SOP Class/Instance UID pairs which will be kept internally to be further used for the subsequent Basic Image Box SOP Class N-SET-RQ messages.

When all Image Boxes (including parameters) for the film-sheet have been set, the *syngo*® MR XA51A print manager will issue an N-ACTION-RQ message with the SOP Instance UID of the Basic Film Box and the Action Type ID of 1.

The affected SOP Instance UID received with N-CREATE-RSP message will be kept internally and used for later requests (e.g., N-DELETE-RQ) on the Basic Film Box.

The Basic Film Box SOP class interprets the status codes listed in the tables below:

Table 59: N-CREATE-RSP Status Handling Behavior for Basic Film Box

Service Status	Meaning	Error Codes	Behavior
Failure	There is an existing Film Box that has not been printed and N-ACTION at the Film Session level is not supported. A new Film Box will not be created when a previous Film Box has not been printed	C616	Print job is marked as failed and the reason is logged
Warning	Requested Min Density or Max Density outside of printer's operating range. The printer will use its respective minimum or maximum density value instead	B605	Print job continues and warning is logged
Success	Film Box successfully created	0000	Print job continues

Table 60: N-ACTION-RSP Status Handling Behavior for Basic Film Box

Service Status	Meaning	Error Codes	Behavior
Failure	Unable to create print job, print queue is full	C602	Print job is marked as failed and the reason is logged
	Image size is larger than images box size	C603	Print job is marked as failed and the reason is logged
	Combined Print Image size is larger than the Image Box size	C613	Print job is marked as failed and the reason is logged
Warning	Film box does not contain image box (empty page)	B603	Print job continues and warning is logged
	Image size is larger than image box size, the image has been demagnified	B604	Print job continues and warning is logged
	Image size is larger than the Image Box size. The Image has been cropped to fit.	B609	Print job continues and warning is logged
	Image size or Combined Print Image size is larger than the Image Box size. Image or Combined Print Image has been decimated to fit.	B60A	Print job continues and warning is logged
Success	Film accepted for printing	0000	Print job continues

Basic Grayscale Image Box SOP Class

The Basic Grayscale Image Box information object definition is the presentation of an image and image related data in the image area of a film. The Basic Image Box information describes the presentation parameters and image pixel data, which apply to a single image of a sheet of film.

The Grayscale Image Box SOP Class uses only the N-SET-RQ with the attributes listed in the table below:

Table 61: Attributes for N-SET-RQ of Basic Grayscale Image Box

Attribute Name	Tag	Usage SCU	Supported Values
Image Position	(2020,0010)	M	1
Basic Grayscale Image Sequence	(2020,0110)	M	
> Samples per Pixel	(0028,0002)	M	1
> Photometric Interpretation	(0028,0004)	M	MONOCHROME2
> Rows	(0028,0010)	M	
> Columns	(0028,0011)	M	
> Pixel Aspect Ratio	(0028,0034)	M	
> Bits Allocated	(0028,0100)	M	8,16
> Bits Stored	(0028,0101)	M	8,12
> High Bit	(0028,0102)	M	7,11
> Pixel Representation	(0028,0103)	M	0
> Pixel Data	(7FE0,0010)	M	

The Basic Grayscale Image Box SOP class interprets the status codes as listed below:

Table 62: N-SET-RSP Status Handling Behavior for the Basic Grayscale Image Box SOP Class

Service Status	Further Meaning	Error Codes	Behavior
Failure	Image contains more pixel than printer can print in Image Box	C603	Print job is marked as failed and the reason is logged
	Insufficient memory in printer to store the image	C605	Print job is marked as failed and the reason is logged
	Combined Print Image size is larger than the Image Box size	C613	Print job is marked as failed and the reason is logged
Warning	Image size is larger than image box size, the image has been demagnified.	B604	Print job continues and the reason is logged
	Requested MinDensity or MaxDensity outside of Printer's operating range	B605	Print job continues and the reason is logged
	Image size is larger than the Image Box size. The Image has been cropped to fit.	B609	Print job continues and warning is logged
	Image size or Combined Print Image size is larger than the Image Box size. Image or Combined Print Image has been decimated to fit.	B60A	Print job continues and warning is logged
Success	Image successfully stored in Image Box	0000	Print job continues

Basic Color Image Box SOP Class

The Basic Color Image Box information object definition is the presentation of an image and image related data in the image area of a film. The Basic Image Box information describes the presentation parameters and image pixel data, which apply to a single image of a sheet of film.

The Color Image Box SOP Class uses only the N-SET-RQ with the attributes listed below:

Table 63: Attributes for N-SET-RQ of Basic Color Image Box

Attribute Name	Tag	Usage SCU	Supported Values
Image Position	(2020,0010)	M	1
Basic Color Image Sequence	(2020,0111)	M	
> Samples per Pixel	(0028,0002)	M	3
> Photometric Interpretation	(0028,0004)	M	RGB
> Planar Configuration	(0028,0006)	M	0
> Rows	(0028,0010)	M	
> Columns	(0028,0011)	M	
> Pixel Aspect Ratio	(0028,0034)	M	
> Bits Allocated	(0028,0100)	M	8
> Bits Stored	(0028,0101)	M	8
> High Bit	(0028,0102)	M	7
> Pixel Representation	(0028,0103)	M	0
> Pixel Data	(7FE0,0010)	M	

The Color Image Box SOP class interprets the status codes listed below:

Table 64: N-SET-RSP Status Handling Behavior for the Color Grayscale Image Box

Service Status	Meaning	Error Codes	Behavior
Failure	Image contains more pixel than printer can print in Image Box	C603	Print job is marked as failed and the reason is logged
	Insufficient memory in printer to store the image	C605	Print job is marked as failed and the reason is logged
	Combined Print Image size is larger than the Image Box size	C613	Print job is marked as failed and the reason is logged
Warning	Image size larger than image box size	B604	Print job continues and the reason is logged
	Image size is larger than the Image Box size. The Image has been cropped to fit.	B609	Print job continues and warning is logged
	Image size or Combined Print Image size is larger than the Image Box size. Image or Combined Print Image has been decimated to fit.	B60A	Print job continues and warning is logged
Success	Image successfully stored in Image Box	0000	Print job continues

Presentation LUT SOP Class

The objective of the Presentation LUT is to realize image hardcopy printing tailored for specific modalities, applications and user preferences.

The output of the Presentation LUT is Presentation Values (P-Values). P-Values are approximately related to human perceptual response. They are intended to facilitate common input for hardcopy. P-Values are intended to be independent of the specific class or characteristics of the hardcopy device.

The *syngo*® MR XA51A Print Management SCU supports the following DIMSE Service elements for the Basic Film Session SOP Class as SCU:

- N-CREATE
- N-DELETE

The Presentation LUT SOP Class uses only the N-CREATE-RQ with the attributes listed below:

Table 65: Attributes for N-CREATE-RQ of Presentation LUT SOP Class

Attribute Name	Tag	Usage SCU	Supported Values
Presentation LUT Shape	(2050,0020)	U	IDENTITY

The affected SOP Instance UID received with N-CREATE-RSP message will be kept internally and is used for later requests on the Basic Film Box (N-CREATE-RQ) and on the Presentation LUT (N-DELETE-RQ).

The Presentation LUT SOP class interprets the status codes listed below:

Table 66: N-CREATE-RSP Status Handling Behavior for the Presentation LUT SOP Class

Service Status	Further Meaning	Error Codes	Behavior
Warning	Requested MinDensity or MaxDensity outside of HCD's operating range. HCD will use its respective minimum or maximum density value instead.	B605	Print job continues and the reason is logged
Success	Presentation LUT successfully created	0000	Print job continues

Printer SOP Class

The Printer SOP Class provides the possibility to monitor the status of the hardcopy printer in a synchronous and in an asynchronous way.

When used synchronously the *syngo*® MR XA51A Print SCU uses the N-GET-RQ to request information about the printer status. It uses the attributes listed in the table below.

Table 67: Attributes for N-GET-RQ of the Printer SOP Class

Attribute Name	Tag	Usage SCP	Supported Values
Printer Status	(2110,0010)	M	NORMAL, FAILURE, WARNING
Printer Status Info	(2110,0020)	M	See table in chapter 9.7 for possible values.

The command communication failure behavior listed below applies to all SOP classes used for the "Print Film" activity:

Table 68: DICOM Command Communication Failure Behavior

Exception	Behavior
Timeout	Failure reported to user (Timeout configurable; default 30s)
Association Aborted	Failure reported to user

4.2.7.4 Association Acceptance Policy

4.2.7.4.1 Activity Print Film

4.2.7.4.1.1 Description and Sequencing of Activities

The syngo® MR XA51A supports the reverse role negotiation of the Printer SOP Class. Receiving the N-EVENT-REPORT-RQ from a printer the syngo® MR XA51A is asynchronously informed about changes of the printer status.

4.2.7.4.1.2 Accepted Presentation Context

The syngo® MR XA51A accepts Presentation Contexts as shown in the following table:

Table 69: Presentation Contexts for the Activity “Print Film”

Abstract Syntax		Transfer Syntax		Role	Ext.
Name	UID	Name List	UID List		Neg.
Printer SOP Class	1.2.840.10008.5.1.1.16	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None

4.2.7.4.1.3 SOP Specific Conformance

The arguments of the N-EVENT-REPORT-RQ are defined in the table below:

Table 70: Attributes for the N-EVENT-REPORT-RQ of the Printer SOP Class

Event-type Name	Event	Attributes	Tag	Usage SCU
Normal	1	-	-	-
Warning	2	Printer Status Info	(2110,0020)	U
Failure	3	Printer Status Info	(2110,0020)	U

4.2.7.4.2 Activity Print Management

4.2.7.4.2.1 Description and Sequencing of Activities

The syngo® MR XA51A supports the reverse role negotiation of the Print Job SOP Class. Receiving the N-EVENT-REPORT-RQ from a printer the syngo® MR XA51A is asynchronously informed about the status of a print job for monitoring its progress.

4.2.7.4.2.2 Accepted Presentation Context

The syngo® MR XA51A accepts Presentation Contexts as shown in the following table:

Table 71: Presentation Contexts for the Activity "Print Management"

Abstract Syntax		Transfer Syntax		Role	Ext.
Name	UID	Name List	UID List		Neg.
Print Job SOP Class	1.2.840.10008.5.1.1.14	Implicit VR Little Endian	1.2.840.10008.1.2	SCU	None

4.2.7.4.2.3 SOP Specific Conformance

Attributes that can be handled by the Print AE of the product are listed in the table below.

Table 72: Attributes for the N-EVENT-REPORT-RQ of the Print Job SOP Class

Event-type Name	Event	Attributes	Tag	Usage SCU
Pending	1	Execution Status Info	(2100,0030)	U
		Print Job ID	(2100,0010)	-- (Print Queue Management SOP Class not supported)
		Film Session Label	(2000,0050)	U
		Printer Name	(2110,0030)	U
Printing	2	Execution Status Info	(2100,0030)	U
		Print Job ID	(2100,0010)	-- (Print Queue Management SOP Class not supported)
		Film Session Label	(2000,0050)	U
		Printer Name	(2110,0030)	U
Done	3	Execution Status Info	(2100,0030)	U
		Print Job ID	(2100,0010)	-- (Print Queue Management SOP Class not supported)
		Film Session Label	(2000,0050)	U
		Printer Name	(2110,0030)	U
Failure	4	Execution Status Info	(2100,0030)	U
		Print Job ID	(2100,0010)	-- (Print Queue Management SOP Class not supported)
		Film Session Label	(2000,0050)	U
		Printer Name	(2110,0030)	U

4.3 Network Interfaces

4.3.1 Physical Network Interface

The *syngo*® MR XA51A provides DICOM 3.0 TCP/IP network communication support as defined in Part 8 of the DICOM Standard. The network communication is independent from the physical medium over which TCP/IP executes; it inherits this from the Windows OS system upon which it executes.

4.3.2 Additional Protocols

None

4.3.3 IPv4 and IPv6 Support

IPv4 and IPv6 are supported. Regarding IPv6 please note, that the complete networking infrastructure in the hospital (firewalls, DNS-Servers, ...) must support IPv6 to get a functioning communication.

4.4 Configuration

4.4.1 AE Title/Presentation Address Mapping

AE Titles shall be unique within the hospital. A common way to achieve that is to use the hostname as part of the AE Titles. The string can be up to 16 characters and must not contain any extended characters. Only 7-bit ASCII characters (excluding Control Characters) are allowed according to the DICOM Standard.

4.4.1.1 Local AE Titles

The *syngo*® MR XA51A allows to configure AE Titles, Ports and Services in any wished way. Default delivery is that all services are using the same AE title and only one port number. In case the connected systems cannot handle this default, the customer service engineer is able to configure for each service its own AE title and Port number.

Table 73: AE Titles

Parameter	Configurable	Default Value
Default AE title	Yes	hostname in uppercase characters; limited to 16 characters
Default Basic Port	Yes	104
Default Secure Port	Yes	2762

4.4.1.2 Remote AE Title/Presentation Address Mapping

4.4.1.2.1 Remote Association Initiators

All relevant remote applications that may setup DICOM associations towards *syngo*® MR XA51A need to be configured in *syngo*® MR XA51A, before the association can be established. This behavior is configurable, but it is recommended, not to change this behavior.

The mapping of external AE Titles to TCP/IP addresses and ports is configurable and initially set at the time of installation by Installation Personnel. Changes can later on also be performed by the local system administrator. The Application Entity Titles and supported transfer syntaxes need to be known for configuration.

To enable a fast and efficient configuration possibility Siemens will deliver templates for known configuration examples, so that the behavior (usage of one AE title, default port numbers, supported services) is determined already through the template.

Remote Application Entities can be configured without restarting the process.

4.4.1.2.2 Remote Association Acceptors

For remote applications that shall be able to accept DICOM associations from *syngo*® MR XA51A, the following information needs to be available:

- Application Entity Title
- Host Name / IP address on which the remote application service runs
- Port number on which the remote application accepts association requests.

The remote system will be indicated in the UI of *syngo*® MR XA51A with a logical name, that is also entered when configuring the node in the administration UI.

To enable a fast and efficient configuration possibility Siemens will deliver templates for known configuration examples, so that the behavior (usage of one AE title, default port numbers, supported services) is determined already through the template.

Remote Application Entities can be configured without restarting the process.

4.4.1.3 Secure DICOM Communication

The system supports configuring the DICOM communication to use secure channel (TLS) between *syngo*® MR XA51A and configured remote nodes. As a security measure the certificate thumbprint or certificate trust chain of the remote nodes shall be added (pinned) to the *syngo*® MR XA51A system to authorize the incoming connection.

Detailed instructions how to set up secure DICOM communication are available in the Administrator Online Help.

Note: The default DICOM port will change to 2762.

If the certificate of remote node contains Enhanced Key Usage (Extended Key Usage) field, then:

- If the remote node acts as DICOM SCP it shall contain Server Authentication (1.3.6.1.5.5.7.3.1)
- If the remote node acts as a DICOM SCU it shall contain Client Authentication (1.3.6.1.5.5.7.3.2)

Otherwise *syngo*® MR XA51A will not accept the certificate.

4.4.2 Parameters

The next table lists configuration parameters, which are true for all Application Entities.

Table 74: Parameter List

Parameter	Configurable	Default Value
PDU size	Yes	32768 Bytes
time-out for accepting/rejecting an association request	Yes	30 s
time-out for responding to an association open/close request	Yes	30 s
time-out for accepting a message over network	Yes	30 s
time-out for waiting for data between TCP/IP-packets	Yes	5 s
time-outs for waiting for a Service Request/Response message from the remote node (Storage SCP/SCU)	Yes	30 s
time-outs for waiting for a Service Request/Response message from the remote node (Query/Retrieve SCP/SCU)	Yes	30 s
time-out for waiting for a C-MOVE-RSP	No	1200 s
number of image collection before saving to database	Yes	20
max matches query limit	Yes	100
max number of parallel receiving associations	Yes	12
DICOM UID change when data is corrected	Yes (by administrator)	Yes

5 Media Interchange

5.1 Implementation Model

5.1.1 Application Data Flow Diagram




Figure 5: Media Interchange Application Data Flow Diagram

The *syngo*® MR XA51A provides the functionality to Import or Export DICOM Instances from and to the File System. During export, a DICOMDIR may also be generated (user selection). A complete ISO Image ready-to-burn can also be generated. All SOP Classes defined in Table 1: Network Services are supported for the Import/Export functionality.

5.1.2 Functional Definitions of AEs

The *syngo*® MR XA51A application is capable of

- provide browsing windows for Import from and Export to the File System
- creating a new File-set in the File System (Export to ...)
- importing SOP Instances from the medium onto local storage
- writing the File-sets DICOMDIR information into the file system and joining it to an ISO image.

5.1.3 Sequencing of Real-World Activities

Whenever data is written to an external media, *syngo*® MR XA51A creates a DICOMDIR from the selected data and creates an ISO image of the selected data on the local hard disk. Depending on the selected data and options (selected media size, with or without compression) either General Purpose CD profile, DVD-J2K, BD-J2K profile is used.




Figure 6: Sequence diagram – Media creation

5.1.4 File Meta Information for Implementation Class and Version

This section describes the values assigned to the File Meta Information attributes (see part PS 3.10) that pertain to the Implementation Class and Version. The implementation Class UID and the Implementation Version name in the File Meta Header are the same as the values specified for networking.

Table 75: Implementation Class/Version Name - Media Interchange

File Meta Information Version	0001
Implementation Class UID	1.3.12.2.1107.5.8.2
Implementation Version Name	SYNGO_MR_XA51A

5.2 AE Specifications

5.2.1 Media Storage AE – Specification

The *syngo*® MR XA51A provides conformance to the following Application Profiles as an FSC as well as an FSR. The FSU role is only supported on a non-optical storage device (e.g. USB stick).

In addition, augmented conformance is provided to store extra data objects important for the full feature support of the *syngo*®-based products. Details are listed below:

Table 76: Media - Application Profiles and Real-World Activities

Application Profiles Supported	Real-World Activity	Role	Service Class Option
AUG-GEN-CD			
AUG-GEN-DVD	Browse Directory Information Import into Application Export to local Archive Media	FSR, FSC	Interchange
AUG- GEN-DVD-J2K			
AUG- GEN-USB-J2K		FSR, FSC, FSU	
STD-GEN-CD			
STD-GEN-DVD-JPEG	Browse Directory Information Import into Application Export to local Archive Media	FSR, FSC	Interchange
STD-GEN-DVD-J2K			
STD-GEN-USB-J2K		FSR, FSC, FSU	

5.2.1.1 Real-World Activities

5.2.1.1.1 Activity “Browse Directory Information”

The *syngo*® MR XA51A acts as FSR using the interchange option when requested to read the media directory.

The *syngo*® MR XA51A will read the DICOMDIR and insert those directory entries that are valid for the application profiles supported, into a local database. The database then is used for browsing media contents.

Note: The “Icon Image Sequence” is also supported in DICOMDIR. But only those Icon Images with “Bits Allocated” (0028,0100) equal to 8 and size of 64x64 or 128x128 pixels are imported into database and are visible in the Browser.

5.2.1.1.2 Real World Activity “Import into Application”

The *syngo*® MR XA51A application acts as FSR using the interchange option when requested to read SOP Instances from the medium into the application.

The SOP Instance selected from the media directory will be copied into the running Application. Only SOP Instances, that are valid for the application profile supported and supported by *syngo*® MR XA51A can be retrieved from media.

5.2.1.1.3 Real-World Activity “Export to local Archive Media”

The *syngo*® MR XA51AApplication acts as FSU (for media with existing DICOM file-set) or FSC (media not initialized) using the interchange option when requested to copy SOP Instances from the local storage to local Archive Medium. The activity as FSU is only possible as long as the local burning SW of *syngo*® MR XA51A has not already processed the generated ISO file.

The *syngo*® MR XA51A application will receive a list of SOP Instances to be copied to the local archive medium. Depending on the profile selected (Standard: uncompressed, with DICOMDIR; Patient: compressed with DICOMDIR) the SOP Instances will be taken, and an ISO file is being generated that includes the DICOMDIR and the corresponding objects.

It is then up to *syngo*® MR XA51A local configuration (if equipped with a local media burner) to burn the ISO file to the appropriate media.

5.2.1.2 SOP Classes and Transfer Syntaxes

These Application Profiles are based on the Media Storage Service Class with the Interchange Option. The *syngo*® MR XA51A provides Standard Conformance to the SOP Classes listed in "Table 1: Network Services" section "SOP Classes Created by the *syngo*® MR XA51A" and "SOP Classes Managed by the *syngo*® MR XA51A" in the "[Conformance Statement Overview](#)".

Using the Application Profiles supporting compression (AUG- GEN-DVD-J2K, AUG- GEN-USB-J2K, STD-GEN-DVD-J2K, STD-GEN-USB-J2K) the following Transfer Syntaxes are supported:

Table 77: Transfer Syntaxes for STD-GEN-DVD-J2K and STD-GEN-USB-J2K

UID value	Transfer Syntax	Image Objects	Non-Image Objects
1.2.840.10008.1.2.1	Explicit VR Little Endian	Yes	Yes
1.2.840.10008.1.2.4.50	JPEG Baseline (Process 1) lossy compressed	Yes	No
1.2.840.10008.1.2.4.51	JPEG Extended (Process 2 & 4) lossy compressed	Yes	No
1.2.840.10008.1.2.4.70	JPEG Lossless, Non-Hierarchical, First-Order Prediction (Process 14) lossless compressed	Yes	No
1.2.840.10008.1.2.4.90	JPEG 2000 Image Compression (Lossless Only) compressed	Yes	No
1.2.840.10008.1.2.4.91	JPEG 2000 Image Compression lossy compressed	Yes	No
1.2.840.10008.1.2.5	RLE Lossless compressed	Yes	No

Using the Application Profiles that do not support compression (AUG- GEN-DVD, AUG- GEN-USB, STD-GEN-DVD, STD-GEN-USB) only Explicit VR Little Endian (1.2.840.10008.1.2.1) is supported.

5.3 Augmented and Private Application Profiles

5.3.1 Augmented Application Profiles

N/A

5.4 Media Configuration

None

6 Support of Extended Character Sets

The syngo® MR XA51A DICOM application supports the following character sets as defined in the four tables below:

Table 78: Single-Byte Character Sets without Code Extension

Character Set Description	Defined Term	ISO registration number	Character Set
Default repertoire	None	ISO-IR 6	ISO 646:
Latin alphabet No. 1	ISO_IR 100	ISO-IR 100	Supplementary set
		ISO-IR 6	ISO 646:
Latin alphabet No. 2	ISO_IR 101	ISO-IR 101	Supplementary set
		ISO-IR 6	ISO 646
Latin alphabet No. 3	ISO_IR 109	ISO-IR 109	Supplementary set
		ISO-IR 6	ISO 646
Latin alphabet No. 4	ISO_IR 110	ISO-IR 110	Supplementary set
		ISO-IR 6	ISO 646
Cyrillic	ISO_IR 144	ISO-IR 144	Supplementary set
		ISO-IR 6	ISO 646
Arabic	ISO_IR 127	ISO-IR 127	Supplementary set
		ISO-IR 6	ISO 646
Greek	ISO_IR 126	ISO-IR 126	Supplementary set
		ISO-IR 6	ISO 646
Hebrew	ISO_IR 138	ISO-IR 138	Supplementary set
		ISO-IR 6	ISO 646
Latin alphabet No. 5	ISO_IR 148	ISO-IR 148	Supplementary set
		ISO-IR 6	ISO 646
Japanese	ISO_IR 13	ISO-IR 13	JIS X 0201: Katakana
		ISO-IR 14	JIS X 0201: Romaji
Thai	ISO_IR166	ISO-IR166	TIS 620-253 (1990)
		ISO-IR 6	ISO 646

Table 79: Single-Byte Characters Sets with Code Extension

Character Set Description	Defined Term	Standard for Code Extension	ESC sequence	ISO registration number	Character Set
Default repertoire	ISO 2022 IR 6	ISO 2022	ESC 02/08 04/02	ISO-IR 6	ISO 646
Latin alphabet No.1	ISO 2022 IR 100	ISO 2022	ESC 02/13 04/01	ISO-IR 100	Supplementary set
		ISO 2022	ESC 02/08 04/02	ISO-IR 6	ISO 646
Latin alphabet No.2	ISO 2022 IR 101	ISO 2022	ESC 02/13 04/02	ISO-IR 101	Supplementary set
		ISO 2022	ESC 02/08 04/02	ISO-IR 6	ISO 646
Latin alphabet No.3	ISO 2022 IR 109	ISO 2022	ESC 02/13 04/03	ISO-IR 109	Supplementary set
		ISO 2022	ESC 02/08 04/02	ISO-IR 6	ISO 646
Latin alphabet No.4	ISO 2022 IR 110	ISO 2022	ESC 02/13 04/04	ISO-IR 110	Supplementary set
		ISO 2022	ESC 02/08 04/02	ISO-IR 6	ISO 646

Multi-Byte Character Sets without Code Extension

Table 80: Multi-Byte Character Sets without Code Extension

Character Set Description	Defined Term	ISO registration number	Character Set
Unicode	ISO_IR 192	ISO 10646	Unicode in UTF-8
Chinese	GB18030	GB18030	GB 18030-2000 (China Association for Standardization)

Table 81: Multi-Byte Character Sets with Code Extension

Character Set Description	Defined Term	Standard for Code Extension	ESC sequence	ISO registration number	Character Set
Japanese	ISO 2022 IR 159	ISO 2022	ESC 02/04 02/08 04/04	ISO-IR 159	JIS X 0212: Supplementary Kanji set
				ISO-IR 87	
Korean	ISO 2022 IR 149	ISO 2022	ESC 02/04 02/09 04/03	ISO-IR 149	KS X 1001: Hangul and Hanja

All specific Character Sets (SCS) listed above are supported for incoming Data. When creating new Instances, the system will use the default SCS (or SCS List) configured on the machine.

When there is a mismatch between the given character set in attribute (0008,0005) and the characters in an IOD received by the system, then the following measures are taken to make the characters DICOM conform:

- Convert each illegal character to '?'

There are three categories of character sets which have to be differentiated because of their different encoding formats:

- Conventional ISO character sets: ISO_IR 6, ISO 2022 IR 6, ISO_IR 100, etc.
→ encoded in ISO 2022
- ISO_IR 192 → encoded in UTF-8
- GB18030 → encoded in GB18030

It is not possible to recognize the following mismatches automatically on receiving or importing:

- An attribute value is encoded in ISO_IR 192 ↔ (0008,0005) contains a conventional ISO character set as primary character set
- An attribute value is encoded in GB18030 ↔ (0008,0005) contains a conventional ISO character set as primary character set
- An attribute value is encoded in ISO 2022 ↔ (0008,0005) contains ISO_IR 192
- An attribute value is encoded in ISO 2022 ↔ (0008,0005) contains GB18030

An IOD that contains one of the above mentioned inconsistencies is not DICOM conform. As these kinds of inconsistencies cannot be recognized by the system, the IOD will not be rejected but the character data might be corrupted.

The *syngo*® MR XA51A supports Kanji characters in the byte zones after 74 (79, 7A, 7B and 7C).

7 Attribute confidentiality profiles

7.1 De-identification

The *syngo*® MR XA51A application can de-identify attributes, when exporting to Media. Three different levels of de-identification are supported:

- Full de-identification
- Reduced de-identification
- Service de-identification

The user needs to select the appropriate de-identification level during export.

Handling public attributes during de-identification:

- Attributes listed in Table 82: Application Level Confidentiality Profile attributes (standard tags) will be de-identified as specified for the different levels. Attributes not listed in the table are not PII / PHI relevant and will not be de-identified.

Handling private attributes during de-identification:

- Full de-identification: private attributes are not included in anonymized studies
- Reduced de-identification: private attributes are not included in anonymized studies except for the tags listed in Table 83
- Service de-identification: all private attributes are included in anonymized studies except for the tags listed in Table 83

In the following table for attributes marked with:

- 'Yes' - data are anonymized
- 'No' - data are kept

Table 82: Application Level Confidentiality Profile attributes (standard tags)

DICOM Tag	Attribute Name	Full	Reduced	Service
(0000,1000)	Affected SOP Instance UID	Yes	No	No
(0000,1001)	Requested SOP Instance UID	Yes	No	No
(0002,0003)	Media Storage SOP Instance UID	Yes	No	No
(0004,1511)	Referenced SOP Instance UID in File	Yes	No	No
(0008,0014)	Instance Creator UID	Yes	No	No
(0008,0015)	Instance Coercion DateTime	Yes	No	No
(0008,0018)	SOP Instance UID	Yes	Yes	Yes
(0008,0020)	Study Date	Yes	No	No
(0008,0021)	Series Date	Yes	No	No
(0008,0022)	Acquisition Date	Yes	No	No
(0008,0023)	Content Date	Yes	No	No
(0008,0024)	Overlay Date	Yes	No	No
(0008,0025)	Curve Date	Yes	No	No
(0008,002A)	Acquisition DateTime	Yes	No	No
(0008,0030)	Study Time	Yes	No	No
(0008,0031)	Series Time	Yes	No	No
(0008,0032)	Acquisition Time	Yes	No	No

DICOM Tag	Attribute Name	Full	Reduced	Service
(0008,0033)	Content Time	Yes	No	No
(0008,0034)	Overlay Time	Yes	No	No
(0008,0035)	Curve Time	Yes	No	No
(0008,0050)	Accession Number	Yes	Yes	No
(0008,0058)	Failed SOP Instance UID List	Yes	No	No
(0008,0080)	Institution Name	Yes	Yes	No
(0008,0081)	Institution Address	Yes	Yes	No
(0008,0082)	Institution Code Sequence	Yes	Yes	No
(0008,0090)	Referring Physician's Name	Yes	Yes	Yes
(0008,0092)	Referring Physician's Address	Yes	Yes	Yes
(0008,0094)	Referring Physician's Telephone Numbers	Yes	Yes	Yes
(0008,0096)	Referring Physician's Identification Sequence	Yes	Yes	No
(0008,010D)	Context Group Extension Creator UID	Yes	No	No
(0008,0201)	Timezone Offset From UTC	Yes	No	No
(0008,1010)	Station Name	Yes	Yes	Yes
(0008,1030)	Study Description	Yes	Yes	No
(0008,103E)	Series Description	Yes	Yes	No
(0008,1040)	Institutional Department Name	Yes	Yes	No
(0008,1048)	Physician(s) of Record	Yes	Yes	Yes
(0008,1049)	Physician(s) of Record Identification Sequence	Yes	Yes	No
(0008,1050)	Performing Physicians' Name	Yes	Yes	Yes
(0008,1052)	Performing Physicians' Identification Sequence	Yes	Yes	No
(0008,1060)	Name of Physician(s) Reading Study	Yes	Yes	Yes
(0008,1062)	Physician Reading Study Identification Sequence	Yes	Yes	No
(0008,1070)	Operators' Name	Yes	Yes	Yes
(0008,1072)	Operators' Identification Sequence	Yes	Yes	No
(0008,1080)	Admitting Diagnoses Description	Yes	Yes	No
(0008,1084)	Admitting Diagnoses Code Sequence	Yes	Yes	No
(0008,1110)	Referenced Study Sequence	Yes	No	No
(0008,1111)	Referenced Performed Procedure Step Sequence	Yes	No	No
(0008,1120)	Referenced Patient Sequence	Yes	Yes	No
(0008,1140)	Referenced Image Sequence	Yes	No	No
(0008,1155)	Referenced SOP Instance UID	Yes	No	No
(0008,1195)	Transaction UID	Yes	No	No
(0008,2111)	Derivation Description	Yes	No	No
(0008,2112)	Source Image Sequence	Yes	No	No

DICOM Tag	Attribute Name	Full	Reduced	Service
(0008,3010)	Irradiation Event UID	Yes	No	No
(0008,4000)	Identifying Comments	Yes	Yes	No
(0008,9123)	Creator Version UID	Yes	No	No
(0010,0010)	Patient's Name	Yes	Yes	Yes
(0010,0020)	Patient ID	Yes	Yes	Yes
(0010,0021)	Issuer of Patient ID	Yes	Yes	No
(0010,0030)	Patient's Birth Date	Yes	Yes	Yes
(0010,0032)	Patient's Birth Time	Yes	Yes	No
(0010,0040)	Patient's Sex	Yes	No	No
(0010,0050)	Patient's Insurance Plan Code Sequence	Yes	Yes	Yes
(0010,0101)	Patient's Primary Language Code Sequence	Yes	Yes	Yes
(0010,0102)	Patient's Primary Language Modifier Code Sequence	Yes	Yes	Yes
(0010,1000)	Other Patient IDs	Yes	Yes	Yes
(0010,1001)	Other Patient Names	Yes	Yes	Yes
(0010,1002)	Other Patient IDs Sequence	Yes	Yes	Yes
(0010,1005)	Patient's Birth Name	Yes	Yes	Yes
(0010,1010)	Patient's Age	Yes	No	No
(0010,1020)	Patient's Size	Yes	No	No
(0010,1030)	Patient's Weight	Yes	No	No
(0010,1040)	Patient Address	Yes	Yes	Yes
(0010,1050)	Insurance Plan Identification	Yes	Yes	No
(0010,1060)	Patient's Mother's Birth Name	Yes	Yes	Yes
(0010,1080)	Military Rank	Yes	Yes	No
(0010,1081)	Branch of Service	Yes	Yes	No
(0010,1090)	Medical Record Locator	Yes	Yes	No
(0010,1100)	Referenced Patient Photo Sequence	Yes	Yes	No
(0010,2000)	Medical Alerts	Yes	Yes	No
(0010,2110)	Allergies	Yes	Yes	No
(0010,2150)	Country of Residence	Yes	Yes	No
(0010,2152)	Region of Residence	Yes	Yes	No
(0010,2154)	Patient's Telephone Number	Yes	Yes	Yes
(0010,2160)	Ethnic Group	Yes	No	No
(0010,2180)	Occupation	Yes	Yes	No
(0010,21A0)	Smoking Status	Yes	No	No
(0010,21B0)	Additional Patient's History	Yes	Yes	Yes
(0010,21C0)	Pregnancy Status	Yes	No	No

DICOM Tag	Attribute Name	Full	Reduced	Service
(0010,21D0)	Last Menstrual Date	Yes	No	No
(0010,21F0)	Patient's Religious Preference	Yes	Yes	No
(0010,2203)	Patient Sex Neutered	Yes	No	No
(0010,2297)	Responsible Person	Yes	Yes	No
(0010,2299)	Responsible Organization	Yes	Yes	No
(0010,4000)	Patient Comments	Yes	Yes	Yes
(0018,0010)	Contrast Bolus Agent	Yes	Yes	No
(0018,1000)	Device Serial Number	Yes	Yes	No
(0018,1002)	Device UID	Yes	No	No
(0018,1004)	Plate ID	Yes	Yes	No
(0018,1005)	Generator ID	Yes	Yes	No
(0018,1007)	Cassette ID	Yes	Yes	No
(0018,1008)	Gantry ID	Yes	Yes	No
(0018,1030)	Protocol Name	Yes	Yes	No
(0018,1400)	Acquisition Device Processing Description	Yes	Yes	No
(0018,2042)	Target UID	Yes	No	No
(0018,4000)	Acquisition Comments	Yes	Yes	No
(0018,700A)	Detector ID	Yes	Yes	No
(0018,9424)	Acquisition Protocol Description	Yes	Yes	No
(0018,9516)	Start Acquisition DateTime	Yes	No	No
(0018,9517)	End Acquisition DateTime	Yes	No	No
(0018,A003)	Contribution Description	Yes	Yes	No
(0020,000D)	Study Instance UID	Yes	Yes	Yes
(0020,000E)	Series Instance UID	Yes	Yes	Yes
(0020,0010)	Study ID	Yes	Yes	No
(0020,0052)	Frame of Reference UID	Yes	No	No
(0020,0200)	Synchronization Frame of Reference UID	Yes	No	No
(0020,3401)	Modifying Device ID	Yes	Yes	No
(0020,3404)	Modifying Device Manufacturer	Yes	Yes	No
(0020,3406)	Modified Image Description	Yes	Yes	No
(0020,4000)	Image Comments	Yes	Yes	No
(0020,9158)	Frame Comments	Yes	Yes	No
(0020,9161)	Concatenation UID	Yes	No	No
(0020,9164)	Dimension Organization UID	Yes	No	No
(0028,1199)	Palette Color Lookup Table UID	Yes	No	No
(0028,1214)	Large Palette Color Lookup Table UID	Yes	No	No

DICOM Tag	Attribute Name	Full	Reduced	Service
(0028,4000)	Image Presentation Comments	Yes	Yes	No
(0032,0012)	Study ID Issuer	Yes	Yes	No
(0032,1020)	Scheduled Study Location	Yes	Yes	No
(0032,1021)	Scheduled Study Location AE Title	Yes	Yes	No
(0032,1030)	Reason for Study	Yes	Yes	No
(0032,1032)	Requesting Physician	Yes	Yes	No
(0032,1033)	Requesting Service	Yes	Yes	No
(0032,1060)	Requested Procedure Description	Yes	Yes	No
(0032,1070)	Requested Contrast Agent	Yes	Yes	No
(0032,4000)	Study Comments	Yes	Yes	No
(0038,0004)	Referenced Patient Alias Sequence	Yes	Yes	No
(0038,0010)	Admission ID	Yes	Yes	No
(0038,0011)	Issuer of Admission ID	Yes	Yes	No
(0038,001E)	Scheduled Patient Institution Residence	Yes	Yes	No
(0038,0020)	Admitting Date	Yes	No	No
(0038,0021)	Admitting Time	Yes	No	No
(0038,0040)	Discharge Diagnosis Description	Yes	Yes	No
(0038,0050)	Special Needs	Yes	Yes	No
(0038,0060)	Service Episode ID	Yes	Yes	No
(0038,0061)	Issuer of Service Episode ID	Yes	Yes	No
(0038,0062)	Service Episode Description	Yes	Yes	No
(0038,0300)	Current Patient Location	Yes	Yes	No
(0038,0400)	Patient's Institution Residence	Yes	Yes	No
(0038,0500)	Patient State	Yes	Yes	No
(0038,4000)	Visit Comments	Yes	Yes	No
(0040,0001)	Scheduled Station AE Title	Yes	Yes	No
(0040,0002)	Scheduled Procedure Step Start Date	Yes	No	No
(0040,0003)	Scheduled Procedure Step Start Time	Yes	No	No
(0040,0004)	Scheduled Procedure Step End Date	Yes	No	No
(0040,0005)	Scheduled Procedure Step End Time	Yes	No	No
(0040,0006)	Scheduled Performing Physician Name	Yes	Yes	No
(0040,0007)	Scheduled Procedure Step Description	Yes	Yes	No
(0040,000B)	Scheduled Performing Physician Identification Sequence	Yes	Yes	No
(0040,0010)	Scheduled Station Name	Yes	Yes	No
(0040,0011)	Scheduled Procedure Step Location	Yes	Yes	No
(0040,0012)	Pre-Medication	Yes	Yes	No

DICOM Tag	Attribute Name	Full	Reduced	Service
(0040,0241)	Performed Station AE Title	Yes	Yes	No
(0040,0242)	Performed Station Name	Yes	Yes	No
(0040,0243)	Performed Location	Yes	Yes	No
(0040,0244)	Performed Procedure Step Start Date	Yes	No	No
(0040,0245)	Performed Procedure Step Start Time	Yes	No	No
(0040,0250)	Performed Procedure Step End Date	Yes	No	No
(0040,0251)	Performed Procedure Step End Time	Yes	No	No
(0040,0253)	Performed Procedure Step ID	Yes	Yes	No
(0040,0254)	Performed Procedure Step Description	Yes	Yes	No
(0040,0275)	Request Attributes Sequence	Yes	Yes	No
(0040,0280)	Comments on Performed Procedure Step	Yes	Yes	No
(0040,0555)	Acquisition Context Sequence	Yes	Yes	No
(0040,1001)	Requested Procedure ID	Yes	Yes	No
(0040,1004)	Patient Transport Arrangements	Yes	Yes	No
(0040,1005)	Requested Procedure Location	Yes	Yes	No
(0040,1010)	Names of Intended Recipient of Results	Yes	Yes	No
(0040,1011)	Intended Recipients of Results Identification Sequence	Yes	Yes	No
(0040,1101)	Person Identification Code Sequence	Yes	Yes	No
(0040,1102)	Person Address	Yes	Yes	No
(0040,1103)	Person Telephone Numbers	Yes	Yes	No
(0040,1400)	Requested Procedure Comments	Yes	Yes	No
(0040,2001)	Reason for Imaging Service Request	Yes	Yes	No
(0040,2008)	Order Entered By	Yes	Yes	No
(0040,2009)	Order Enterer Location	Yes	Yes	No
(0040,2010)	Order Callback Phone Number	Yes	Yes	No
(0040,2016)	Placer Order Number of Imaging Service Request	Yes	Yes	No
(0040,2017)	Filler Order Number of Imaging Service Request	Yes	Yes	No
(0040,2400)	Imaging Service Request Comments	Yes	Yes	No
(0040,3001)	Confidentiality Constraint on Patient Data Description	Yes	Yes	No
(0040,4005)	Scheduled Procedure Step Start DateTime	Yes	No	No
(0040,4010)	Scheduled Procedure Step Modification DateTime	Yes	No	No
(0040,4011)	Expected Completion Date Time	Yes	No	No
(0040,4023)	Referenced General Purpose Scheduled Procedure Step Transaction UID	Yes	No	No
(0040,4025)	Scheduled Station Name Code Sequence	Yes	Yes	No
(0040,4027)	Scheduled Station Geographic Location Code Sequence	Yes	Yes	No
(0040,4028)	Performed Station Name Code Sequence	Yes	Yes	No

DICOM Tag	Attribute Name	Full	Reduced	Service
(0040,4030)	Performed Station Geographic Location Code Sequence	Yes	Yes	No
(0040,4034)	Scheduled Human Performers Sequence	Yes	Yes	No
(0040,4035)	Actual Human Performers Sequence	Yes	Yes	No
(0040,4036)	Human Performers Organization	Yes	Yes	No
(0040,4037)	Human Performers Name	Yes	Yes	No
(0040,4050)	Performed Procedure Step Start DateTime	Yes	No	No
(0040,4051)	Performed Procedure Step End DateTime	Yes	No	No
(0040,4052)	Procedure Step Cancellation DateTime	Yes	No	No
(0040,A027)	Verifying Organization	Yes	Yes	No
(0040,A073)	Verifying Observer Sequence	Yes	Yes	No
(0040,A075)	Verifying Observer Name	Yes	Yes	No
(0040,A078)	Author Observer Sequence	Yes	Yes	No
(0040,A07A)	Participant Sequence	Yes	Yes	No
(0040,A07C)	Custodial Organization Sequence	Yes	Yes	No
(0040,A088)	Verifying Observer Identification Code Sequence	Yes	Yes	No
(0040,A123)	Person Name	Yes	Yes	No
(0040,A124)	UID	Yes	Yes	No
(0040,A171)	Observation UID	Yes	No	No
(0040,A172)	Referenced Observation UID (Trial)	Yes	No	No
(0040,A192)	Observation Date (Trial)	Yes	No	No
(0040,A193)	Observation Time (Trial)	Yes	No	No
(0040,A307)	Current Observer (Trial)	Yes	Yes	No
(0040,A352)	Verbal Source (Trial)	Yes	Yes	No
(0040,A353)	Address (Trial)	Yes	Yes	No
(0040,A354)	Telephone Number (Trial)	Yes	Yes	Yes
(0040,A358)	Verbal Source Identifier Code Sequence (Trial)	Yes	Yes	No
(0040,A402)	Observation Subject UID (Trial)	Yes	No	No
(0040,A730)	Content Sequence	Yes	Yes	No
(0040,DB0C)	Template Extension Organization UID	Yes	No	No
(0040,DB0D)	Template Extension Creator UID	Yes	No	No
(0070,0001)	Graphic Annotation Sequence	Yes	Yes	No
(0070,0084)	Content Creator's Name	Yes	Yes	No
(0070,0086)	Content Creator's Identification Code Sequence	Yes	Yes	No
(0070,031A)	Fiducial UID	Yes	No	No
(0088,0140)	Storage Media Fileset UID	Yes	No	No
(0088,0200)	Icon Image Sequence	Yes	Yes	No

DICOM Tag	Attribute Name	Full	Reduced	Service
(0088,0904)	Topic Title	Yes	Yes	No
(0088,0906)	Topic Subject	Yes	Yes	No
(0088,0910)	Topic Author	Yes	Yes	No
(0088,0912)	Topic Keywords	Yes	Yes	No
(0400,0100)	Digital Signature UID	Yes	Yes	No
(0400,0402)	Referenced Digital Signature Sequence	Yes	Yes	No
(0400,0403)	Referenced SOP Instance MAC Sequence	Yes	Yes	No
(0400,0404)	MAC	Yes	Yes	No
(0400,0550)	Modified Attributes Sequence	Yes	Yes	No
(0400,0561)	Original Attributes Sequence	Yes	Yes	Yes
(2030,0020)	Text String	Yes	Yes	No
(3006,0024)	Referenced Frame of Reference UID	Yes	No	No
(3006,00C2)	Related Frame of Reference UID	Yes	No	No
(3008,0105)	Source Serial Number	Yes	No	No
(300A,0013)	Dose Reference UID	Yes	No	No
(300E,0008)	Reviewer Name	Yes	Yes	No
(4000,0010)	Arbitrary	Yes	Yes	No
(4000,4000)	Text Comments	Yes	Yes	No
(4008,0042)	Results ID Issuer	Yes	Yes	No
(4008,0102)	Interpretation Recorder	Yes	Yes	No
(4008,010A)	Interpretation Transcriber	Yes	Yes	No
(4008,010B)	Interpretation Text	Yes	Yes	No
(4008,010C)	Interpretation Author	Yes	Yes	No
(4008,0111)	Interpretation Approver Sequence	Yes	Yes	No
(4008,0114)	Physician Approving Interpretation	Yes	Yes	No
(4008,0115)	Interpretation Diagnosis Description	Yes	Yes	No
(4008,0118)	Results Distribution List Sequence	Yes	Yes	No
(4008,0119)	Distribution Name	Yes	Yes	No
(4008,011A)	Distribution Address	Yes	Yes	No
(4008,0202)	Interpretation ID Issuer	Yes	Yes	No
(4008,0300)	Impressions	Yes	Yes	No
(4008,4000)	Results Comments	Yes	Yes	No
(50xx,xxxx)	Curve Data	Yes	Yes	No
(60xx,0100)	Overlay Bits Allocated	Yes	Yes	No
(60xx,0102)	Overlay Bit Position	Yes	Yes	No
(60xx,3000)	Overlay Data	Yes	Yes	No

DICOM Tag	Attribute Name	Full	Reduced	Service
(60xx,4000)	Overlay Comments	Yes	Yes	No
(FFFA,FFFA)	Digital Signatures Sequence	Yes	Yes	Yes
(FFFC,FFFC)	Data Set Trailing Padding	Yes	Yes	Yes

Table 83: Application Level Confidentiality Profile Attributes (private tags)

DICOM Tag	Attribute Name	Full	Reduced	Service
(0021,SIEMENS MR SDR 01,01)	Creator Identifier	No	No	No
(0021,SIEMENS MR SDR 01,02)	Application Identifier	No	No	No
(0021, SIEMENS MR SDS 01, 04)	SliceArrayConcatenations	No	No	No
(0021, SIEMENS MR SDS 01, 05)	RelTablePosition	Yes	No	No
(0021, SIEMENS MR SDS 01, 06)	CoilForGradient	Yes	No	No
(0021, SIEMENS MR SDS 01, 07)	LongModelName	Yes	No	No
(0021, SIEMENS MR SDS 01, 08)	GradientMode	No	No	No
(0021, SIEMENS MR SDS 01, 09)	PATModeText	no	No	No
(0021, SIEMENS MR SDS 01, 0A)	SW_korr_faktor	Yes	No	No
(0021, SIEMENS MR SDS 01, 0B)	RfPowerErrorIndicator	Yes	No	No
(0021, SIEMENS MR SDS 01, 0C)	PositivePCSDirections	No	No	No
(0021, SIEMENS MR SDS 01, 0D)	ProtocolChangeHistory	Yes	No	No
(0021, SIEMENS MR SDS 01, 0F)	Stim_lim	Yes	No	No
(0021, SIEMENS MR SDS 01, 10)	MrProtocolVersion	Yes	No	No
(0021, SIEMENS MR SDS 01, 11)	PhaseGradientAmplitude	Yes	No	No
(0021, SIEMENS MR SDS 01, 12)	ReadoutOS	Yes	No	No
(0021, SIEMENS MR SDS 01, 13)	t_puls_max	Yes	No	No
(0021, SIEMENS MR SDS 01, 14)	NumberOfPrescans	Yes	No	No
(0021, SIEMENS MR SDS 01, 16)	dBdt_thresh	Yes	No	No
(0021, SIEMENS MR SDS 01, 17)	SelectionGradientAmplitude	Yes	No	No
(0021, SIEMENS MR SDS 01, 18)	RFSWDMostCriticalAspect	Yes	No	No
(0021, SIEMENS MR SDS 01, 19)	MR Phoenix Protocol	Yes	No	No
(0021, SIEMENS MR SDS 01, 1A)	CoilString	No	No	No
(0021, SIEMENS MR SDS 01, 1B)	SliceResolution	No	No	No
(0021, SIEMENS MR SDS 01, 1C)	Stim_max_online	Yes	No	No
(0021, SIEMENS MR SDS 01, 1D)	Operation_mode_flag	Yes	No	No
(0021, SIEMENS MR SDS 01, 22)	SequenceFileOwner	Yes	No	No
(0021, SIEMENS MR SDS 01, 23)	RfWatchdogMask	Yes	No	No
(0021, SIEMENS MR SDS 01, 25)	TablePositionOrigin	Yes	No	No
(0021, SIEMENS MR SDS 01, 26)	MiscSequenceParam	Yes	No	No
(0021, SIEMENS MR SDS 01, 27)	Isocentered	Yes	No	No
(0021, SIEMENS MR SDS 01, 2A)	CoilId	Yes	No	No
(0021, SIEMENS MR SDS 01, 2B)	PatReinPattern	Yes	No	No
(0021, SIEMENS MR SDS 01, 2C)	Sed	Yes	No	No
(0021, SIEMENS MR SDS 01, 2D)	SARMostCriticalAspect	Yes	No	No

DICOM Tag	Attribute Name	Full	Reduced	Service
(0021, SIEMENS MR SDS 01, 2E)	Stim_mon_mode	Yes	No	No
(0021, SIEMENS MR SDS 01, 2F)	GradientDelayTime	Yes	No	No
(0021, SIEMENS MR SDS 01, 30)	ReadoutGradientAmplitude	Yes	No	No
(0021, SIEMENS MR SDS 01, 31)	AbsTablePosition	Yes	No	No
(0021, SIEMENS MR SDS 01, 32)	RFSWDOperationMode	Yes	No	No
(0021, SIEMENS MR SDS 01, 33)	CoilForGradient2	No	No	No
(0021, SIEMENS MR SDS 01, 34)	Stim_faktor	Yes	No	No
(0021, SIEMENS MR SDS 01, 35)	Stim_max_ges_norm_online	Yes	No	No
(0021, SIEMENS MR SDS 01, 36)	dBdt_max	Yes	No	No
(0021, SIEMENS MR SDS 01, 37)	FlowCompensation	No	No	No
(0021, SIEMENS MR SDS 01, 38)	TransmitterCalibration	Yes	No	No
(0021, SIEMENS MR SDS 01, 3D)	PhaseSliceOversampling	No	No	No
(0021, SIEMENS MR SDS 01, 44)	B1rms	No	No	No
(0021, SIEMENS MR SDS 01, 45)	B1rmsSupervision	No	No	No
(0021, SIEMENS MR SDS 01, 46)	TalesReferencePower	Yes	No	No
(0021, SIEMENS MR SDS 01, 48)	DICOMImageFlavor	No	No	No
(0021, SIEMENS MR SDS 01, 49)	DICOMAcquisitionContrast	No	No	No
(0021, SIEMENS MR SDS 01, 50)	RFEchoTrainLength	Yes	No	No
(0021, SIEMENS MR SDS 01, 51)	GradientEchoTrainLength	Yes	No	No
(0021, SIEMENS MR SDS 01, 53)	Laterality4MF	No	No	No
(0021, SIEMENS MR SDS 01, 5A)	ScanningSequence	No	No	No
(0021, SIEMENS MR SDS 01, 5B)	SequenceVariant	No	No	No
(0021, SIEMENS MR SDS 01, 5C)	MeasurementOptions	No	No	No
(0021, SIEMENS MR SDS 01, 5D)	ScanRegionPositionIso	No	No	No
(0021, SIEMENS MR SDS 01, 5E)	FieldOfViewText	No	No	No
(0021, SIEMENS MR SDS 01, 5F)	RelativeTablePositionText	No	No	No
(0021, SIEMENS MR SDS 01, FE)	Series Data Sequence	No	No	No
(0021, SIEMENS MR SDI 02, 03)	SliceMeasurementDuration	Yes	No	No
(0021, SIEMENS MR SDI 02, 04)	TimeAfterStart	Yes	No	No
(0021, SIEMENS MR SDI 02, 06)	ICE_Dims	Yes	No	No
(0021, SIEMENS MR SDI 02, 1A)	RFSWDDDataType	Yes	No	No
(0021, SIEMENS MR SDI 02, 1B)	PhaseEncodingDirectionPositive	Yes	No	No
(0021, SIEMENS MR SDI 02, 22)	VoxelThickness	Yes	No	No
(0021, SIEMENS MR SDI 02, 24)	MultistepIndex	Yes	No	No
(0021, SIEMENS MR SDI 02, 33)	EchoColumnPosition	Yes	No	No
(0021, SIEMENS MR SDI 02, 41)	GSWDDDataType	Yes	No	No

DICOM Tag	Attribute Name	Full	Reduced	Service
(0021, SIEMENS MR SDI 02, 42)	RealDwellTime	Yes	No	No
(0021, SIEMENS MR SDI 02, 45)	ImaAbsTablePosition	Yes	No	No
(0021, SIEMENS MR SDI 02, 48)	EchoPartitionPosition	Yes	No	No
(0021, SIEMENS MR SDI 02, 49)	EchoLinePosition	Yes	No	No
(0021, SIEMENS MR SDI 02, 4F)	ImaCoilString	No	No	No
(0021, SIEMENS MR SDI 02, 51)	SequenceMask	Yes	No	No
(0021, SIEMENS MR SDI 02, 56)	ImaPATModeText	No	No	No
(0021, SIEMENS MR SDI 02, 58)	AcquisitionMatrixText	No	No	No
(0021, SIEMENS MR SDI 02, 5E)	ProtocolSliceNumber	Yes	No	No
(0021, SIEMENS MR SDI 02, 67)	ExamDataRole	Yes	No	No
(0021, SIEMENS MR SDI 02, 70)	DataSetInfo	Yes	No	No
(0021, SIEMENS MR SDI 02, 71)	UsedChannelString	Yes	No	No
(0021, SIEMENS MR SDI 02, 75)	ImageType4MF	No	No	No
(0021, SIEMENS MR SDI 02, 76)	ImageHistory	No	No	No
(0021, SIEMENS MR SDI 02, 77)	SequenceInfo	Yes	No	No
(0021, SIEMENS MR SDI 02, 78)	ImageTypeVisible	No	No	No
(0021, SIEMENS MR SDI 02, 79)	DistortionCorrectionType	No	No	No
(0021, SIEMENS MR SDI 02, 88)	SliceCenterDistancefromIsoCenter	No	No	No
(0021, SIEMENS MR SDI 02, 89)	FrameInversionTime	No	No	No
(0021, SIEMENS MR SDI 02, 8A)	FrameNumberInSeries	No	No	No
(0021, SIEMENS MR SDI 02, 8B)	SlicePositionText	No	No	No
(0021, SIEMENS MR SDI 02, 8C)	MorphoQCThreshold	Yes	No	No
(0021, SIEMENS MR SDI 02, 8D)	MorphoQCIndex	Yes	No	No
(0021, SIEMENS MR SDI 02, 8E)	DICOM_Dims	Yes	No	No
(0021, SIEMENS MR SDI 02, FE)	Image Data Sequence	No	No	No

8 Security

8.1 Security Profiles

8.1.1 Time Synchronization Profiles

Time Synchronization Profiles: The *syngo*® MR XA51A acts as an NTP Client in the Maintain Time Transaction.

8.1.2 Basic TLS Secure Transport Connection Profile

Basic TLS Secure Transport Connection Profile supports TLS version 1.0, 1.1 and 1.2 protocols with the following features:

Table 84: Secure Transport Connection Profiles

Supported TLS Feature	Mechanism
Entity Authentication	RSA based certificates
Exchange of Master Secrets	RSA
Data Integrity	SHA
Privacy	Triple DES EDE, CBC

The default secure DICOM port is 2762 (can be reconfigured).

8.2 Association Level Security

It is possible to configure whether the SCP will only answer to known AETs or to any AET.

8.3 Application Level Security

- User must login with own password
- For configuration and Maintenance, Service Technician must login with a separate password.

9 Annexes

9.1 IOD Contents

9.1.1 Created SOP Instances

9.1.1.1 Enhanced MR Image IOD

This chapter describes the DICOM attributes of Enhanced MR Image Instances performed by the MR acquisition.

IE	Module	Reference	Presence of Module
Patient	Patient	see chapter 9.1.1.1.1	always
Study	General Study	see chapter 9.1.1.1.2	always
	Patient Study	see chapter 9.1.1.1.3	always
Series	General Series	see chapter 9.1.1.1.4	always
	MR Series	see chapter 9.1.1.1.5	always
Frame of Reference	Frame of Reference	see chapter 9.1.1.1.6	always
Equipment	General Equipment	see chapter 9.1.1.1.7	always
	Enhanced General Equipment	see chapter 9.1.1.1.8	always
Image	Image Pixel	see chapter 9.1.1.1.9	always
	Enhanced Contrast/Bolus	see chapter 9.1.1.1.10	always
	Multi-frame Functional Groups	see chapter 9.1.1.1.11	always
	Multi-frame Dimension	see chapter 9.1.1.1.12	always
	Cardiac Synchronization	see chapter 9.1.1.1.14	in case of cardiac triggering
	Respiratory Synchronization	see chapter 9.1.1.1.15	in case of respiratory triggering
	Bulk Motion Synchronization	see chapter 9.1.1.1.16	in case of bulk motion triggering
	Supplemental Palette Color Lookup Table	see chapter 9.1.1.1.17	in case of Color LUTs
	Acquisition Context	see chapter 9.1.1.1.18	always
	Enhanced MR Image	see chapter 9.1.1.1.19	always
	MR Pulse Sequence	see chapter 9.1.1.1.20	always
	SOP Common	see chapter 9.1.1.1.22	always (with SOP Class UID for Enhanced MR Image)
	Common Instance Reference	see chapter 9.1.1.1.23	always
	SIEMENS MR Common	see chapter 9.2.1.7	always

9.1.1.1.1 Patient Module

Attribute Name	Tag	Supported Values
Patient's Name	(0010,0010)	RIS defined or set by creator
Patient ID	(0010,0020)	RIS defined or set by creator
Issuer of Patient ID	(0010,0021)	RIS defined
Patient's Birth Date	(0010,0030)	RIS defined or set by creator
Patient's Birth Time	(0010,0032)	RIS defined or set by creator
Patient's Sex	(0010,0040)	RIS defined or set by creator
Other Patient IDs	(0010,1000)	RIS defined or set by creator
Other Patient Names	(0010,1001)	RIS defined or set by creator
Ethnic Group	(0010,2160)	RIS defined or set by creator
Patient Comments	(0010,4000)	RIS defined or set by creator
Other Patient Names	(0010,1001)	RIS defined or set by creator
Patient Identity Removed	(0012,0062)	set by creator

9.1.1.1.2 General Study Module

Attribute Name	Tag	Supported Values
Study Instance UID	(0020,000D)	RIS defined or set by creator
Study Date	(0008,0020)	set by creator
Study Time	(0008,0030)	set by creator
Referring Physician's Name	(0008,0090)	RIS defined or set by creator
Requesting Physician	(0032,1032)	RIS defined or set by creator
Study ID	(0020,0010)	set by creator
Accession Number	(0008,0050)	RIS defined or set by creator
Study Description	(0008,1030)	set by creator
Procedure Code Sequence	(0008,1032)	RIS defined
>Code Value	(0008,0100)	RIS defined
>Code Scheme Designator	(0008,0102)	RIS defined
>Code Meaning	(0008,0104)	RIS defined

9.1.1.1.3 Patient Study Module

Attribute Name	Tag	Supported Values
Patient's Age	(0010,1010)	RIS defined or set by creator
Patient's Size	(0010,1020)	RIS defined or set by creator
Patient's Weight	(0010,1030)	RIS defined or set by creator

9.1.1.1.4 General Series Module

Attribute Name	Tag	Supported Values
Modality	(0008,0060)	MR
Series Instance UID	(0020,000E)	set by creator
Series Number	(0020,0011)	set by creator
Series Date	(0008,0021)	set by creator
Series Time	(0008,0031)	set by creator
Performing Physicians' Name	(0008,1050)	RIS defined or set by creator
Protocol Name	(0018,1030)	set by creator
Series Description	(0008,103E)	set by creator
Referenced Performed Procedure Step Sequence	(0008,1111)	set by creator
>Referenced SOP Class UID	(0008,1150)	set by creator
>Referenced SOP Instance UID	(0008,1155)	set by creator
Body Part Examined	(0018,0015)	set by creator
Patient Position	(0018,5100)	set by creator
Request Attributes Sequence	(0040,0275)	RIS defined
>Requested Procedure ID	(0040,1001)	RIS defined
>Accession Number	(0008,0050)	RIS defined
>Study Instance UID	(0020,000D)	RIS defined
>Requested Procedure Description	(0032,1060)	RIS defined
>Scheduled Procedure Step ID	(0040,0009)	RIS defined
>Scheduled Procedure Step Description	(0040,0007)	RIS defined
> Referenced Study Sequence	(0008,1110)	RIS defined
>> Referenced SOP Class UID	(0008,1150)	RIS defined
>> Referenced SOP Instance UID	(0008,1155)	RIS defined
> Requested Procedure Code Sequence	(0032,1064)	RIS defined
>> Code Value	(0008,0100)	RIS defined
>> Code Scheme Designator	(0008,0102)	RIS defined
>> Code Meaning	(0008,0104)	RIS defined
> Scheduled Protocol Code Sequence	(0040,0008)	RIS defined
>> Code Value	(0008,0100)	RIS defined
>> Code Scheme Designator	(0008,0102)	RIS defined
>> Code Meaning	(0008,0104)	RIS defined
Performed Procedure Step ID	(0040,0253)	set by creator
Performed Procedure Step Start Date	(0040,0244)	set by creator
Performed Procedure Step Start Time	(0040,0245)	set by creator
Performed Procedure Step Description	(0040,0254)	set by creator

9.1.1.1.5 **MR Series Module**

Attribute Name	Tag	Supported Values
Modality	(0008,0060)	MR

9.1.1.1.6 **Frame of Reference Module**

Attribute Name	Tag	Supported Values
Frame of Reference UID	(0020,0052)	set by creator
Position Reference Indicator	(0020,1040)	empty

9.1.1.1.7 **General Equipment Module**

Attribute Name	Tag	Supported Values
Manufacturer	(0008,0070)	Siemens Healthineers
Institution Name	(0008,0080)	RIS defined or set by creator
Station Name	(0008,1010)	set by creator
Institution Address	(0008,0081)	RIS defined set by creator
Institutional Department Name	(0008,1040)	set by creator
Manufacturer's Model Name	(0008,1090)	set by creator
Device Serial Number	(0018,1000)	set by creator
Software Versions	(0018,1020)	set by creator

9.1.1.1.8 **Enhanced General Equipment Module**

Attribute Name	Tag	Supported Values
Manufacturer	(0008,0070)	Siemens Healthineers

9.1.1.1.9 **Image Pixel Module**

Attribute Name	Tag	Supported Values
Samples per Pixel	(0028,0002)	1
Photometric Interpretation	(0028,0004)	MONOCHROME2
Rows	(0028,0010)	set by creator
Columns	(0028,0011)	set by creator
Bits Allocated	(0028,0100)	16

Attribute Name	Tag	Supported Values
Bits Stored	(0028,0101)	12 or 16
High Bit	(0028,0102)	11 or 15
Pixel Representation	(0028,0103)	0
Pixel Data	(7FE0,0010)	set by creator
Smallest Image Pixel Value	(0028,0106)	set by creator
Largest Image Pixel Value	(0028,0107)	set by creator

9.1.1.1.10 Enhanced Contrast/Bolus Module

Attribute Name	Tag	Supported Values
Contrast/Bolus Agent Sequence	(0018,0012)	set by creator
>Code Value	(0008,0100)	set by creator
>Code Scheme Designator	(0008,0102)	set by creator
>Code Meaning	(0008,0104)	set by creator
>Contrast/Bolus Agent Number	(0018,9337)	1
>Contrast/Bolus Administration Route Sequence	(0018,0014)	set by creator
>>Code Value	(0008,0100)	set by creator
>>Code Scheme Designator	(0008,0102)	set by creator
>>Code Meaning	(0008,0104)	set by creator
>Contrast/Bolus Ingredient Code Sequence	(0018,9338)	set by creator
>>Code Value	(0008,0100)	set by creator
>>Code Scheme Designator	(0008,0102)	set by creator
>>Code Meaning	(0008,0104)	set by creator
>Contrast/Bolus Volume	(0018,1041)	set by creator
>Contrast/Bolus Ingredient Concentration	(0018,1049)	set by creator

9.1.1.1.11 Multi-frame Functional Groups Module

Attribute Name	Tag	Supported Values
Shared Functional Group Sequence	(5200,9229)	set by creator
> Include one or more Functional Group Macros		
Per-frame Functional Group Sequence	(5200,9230)	set by creator
> Include one or more Functional Group Macros		
Instance Number	(0020,0013)	set by creator
Content Date	(0008,0023)	set by creator
Content Time	(0008,0033)	set by creator
Number of Frames	(0028,0008)	set by creator

9.1.1.1.12 Multi-frame Dimension Module

Attribute Name	Tag	Supported Values
Dimension Organization Sequence	(0020,9221)	set by creator
Dimension Index Sequence	(0020,9222)	set by creator

9.1.1.1.13 Enhanced MR Image Functional Groups

Functional Group	Attribute Name	Tag	Supported Values
Macro			
Pixel Measures	Pixel Measures Sequence	(0028,9110)	set by creator
	>Pixel Spacing	(0018,0030)	set by creator
	>Slice Thickness	(0028,0050)	set by creator
Frame Content	Frame Content Sequence	(0020,9111)	set by creator
	>Frame Acquisition Number	(0020,9156)	set by creator
	>Frame Reference Date Time	(0018,9151)	set by creator
	>Frame Acquisition Date Time	(0018,9074)	set by creator
	>Frame Acquisition Duration	(0018,9220)	set by creator
	>Dimension Index Values	(0020,9157)	set by creator
	>Temporal Position Index	(0020,9128)	set by creator
	>Stack ID	(0020,9056)	set by creator
	>In-Stack Position Number	(0020,9057)	set by creator
	>Frame Comments	(0020,9158)	set by creator
Plane Position	Plane Position Sequence	(0020,9113)	set by creator
	>Image Position (Patient)	(0020,0032)	set by creator
Plane Orientation	Plane Orientation Sequence	(0020,9116)	set by creator
	>Image Orientation (Patient)	(0020,0037)	set by creator
Referenced Image	Referenced Image Sequence	(0008,1140)	set by creator
	>Referenced SOP Class UID	(0008,1150)	set by creator
	>Referenced SOP Instance UID	(0008,1155)	set by creator
	>Referenced Frame Number	(0008,1160)	set by creator
	>Purpose of Referenced Code Sequence	(0040,A170)	set by creator
	>>Code Value	(0008,0100)	e.g. 121311
	>>Coding Scheme Designator	(0008,0102)	e.g. DCM
	>>Code Meaning	(0008,0104)	e.g. Localizer
Derivation Image	Derivation Image Sequence	(0008,9124)	set by creator
	>Derivation Code Sequence	(0008,9215)	set by creator
	>>Code Value	(0008,0100)	set by creator
	>>Coding Scheme Designator	(0008,0102)	set by creator
	>>Code Meaning	(0008,0104)	set by creator
	>Source Image Sequence	(0008,2112)	set by creator
	>>Referenced SOP Class UID	(0008,1150)	set by creator
	>>Referenced SOP Instance UID	(0008,1155)	set by creator
	>>Referenced Frame Number	(0008,1160)	set by creator
	>>Purpose of Referenced Code Sequence	(0040,A170)	set by creator

Functional Group Macro	Attribute Name	Tag	Supported Values
	>>>Code Value	(0008,0100)	set by creator
	>>>Coding Scheme Designator	(0008,0102)	set by creator
	>>>Code Meaning	(0008,0104)	set by creator
Cardiac Synchronization	Cardiac Synchronization Sequence	(0018,9118)	set by creator
	>Nominal Percentage of Cardiac Phase	(0020,9241)	set by creator
	>Nominal Cardiac Trigger Delay Time	(0020,9153)	set by creator
	>Actual Cardiac Trigger Delay Time	(0020,9252)	set by creator
	>Nominal Cardiac Trigger Time Prior to R-peak	(0020,9154)	set by creator
	>Actual Cardiac Trigger Time Prior to R-peak	(0020,9155)	set by creator
	>Intervals Acquired	(0018,1083)	set by creator
	>Intervals Rejected	(0018,1084)	set by creator
	>Heart Rate	(0018,1088)	set by creator
	>R-R Interval Time Nominal	(0020,9251)	set by creator
	>Low R-R Value	(0018,1081)	set by creator
	>High R-R Value	(0018,1082)	set by creator
Frame Anatomy	Frame Anatomy Sequence	(0020,9071)	set by creator
	>Frame Laterality	(0020,9072)	set by creator
	>Anatomic Region Sequence	(0008,2218)	set by creator
	>>Code Value	(0008,0100)	set by creator
	>>Coding Scheme Designator	(0008,0102)	set by creator
	>>Code Meaning	(0008,0104)	set by creator
Pixel Value Transformation	Pixel Value Transformation Sequence	(0028,9145)	set by creator
	>Rescale Intercept	(0028,1052)	set by creator
	>Rescale Slope	(0028,1053)	set by creator
	>Rescale Type	(0028,1054)	set by creator
Frame VOI LUT	Frame VOI LUT Sequence	(0028,9132)	set by creator
	>Window Center	(0028,1050)	set by creator
	>Window Width	(0028,1051)	set by creator
Real World Value Mapping	Real World Value Mapping Sequence	(0040,9096)	set by creator
	>Real World Value Intercept	(0040,9224)	set by creator
	>Real World Value Slope	(0040,9225)	set by creator
	>Measurement Units Code Sequence	(0040,08EA)	set by creator
	>>Code Value	(0008,0100)	set by creator
	>>Coding Scheme Designator	(0008,0102)	set by creator
	>>Code Meaning	(0008,0104)	set by creator
Contrast/Bolus Usage	Contrast/Bolus Usage Sequence	(0018,9341)	set by creator
	>Contrast/Bolus Agent Number	(0018,9337)	1
	>Contrast/Bolus Agent Administered	(0018,9342)	set by creator
	>Contrast/Bolus Agent Detected	(0018,9343)	set by creator
	>Contrast/Bolus Agent Phase	(0018,9344)	set by creator
MR Image Frame Type	MR Image Frame Type Sequence	(0018,9226)	set by creator
	>Frame Type	(0008,9007)	set by creator
	>Pixel Presentation	(0008,9205)	set by creator
	>Volumetric Properties	(0008,9206)	set by creator
	>Volume Based Calculation Technique	(0008,9207)	set by creator
	>Complex Image Component	(0008,9208)	set by creator
	>Acquisition Contrast	(0008,9209)	set by creator

Functional Group	Attribute Name	Tag	Supported Values
Macro			
	>Functional Settling Phase Frames Present	(0018,9622)	set by creator
MR Timing and Related Parameters	MR Timing and Related Parameters Sequence	(0018,9112)	set by creator
	>Repetition Time	(0018,0080)	set by creator
	>Flip Angle	(0018,1314)	set by creator
	>Echo Train Length	(0018,0091)	set by creator
	>RF Echo Train Length	(0018,9240)	set by creator
	>Gradient Echo Train Length	(0018,9241)	set by creator
	>Specific Absorption Rate Sequence ³	(0018,9239)	set by creator
	>>Specific Absorption Rate Definition	(0018,9179)	set by creator
	>>Specific Absorption Rate Value	(0018,9181)	set by creator
	>Gradient Output Type ³	(0018,9180)	set by creator
	>Gradient Output ³	(0018,9182)	set by creator
	>Operation Mode Sequence ³	(0018,9176)	set by creator
	>>Operating Mode Type	(0018,9177)	set by creator
	>>Operating Mode	(0018,9178)	set by creator
MR FOV/Geometry	MR FOV/Geometry Sequence	(0018,9125)	set by creator
	>In-plane Phase Encoding Direction	(0018,1312)	set by creator
	>MR Acquisition Frequency Encoding Steps	(0018,9058)	set by creator
	>MR Acquisition Phase Encoding Steps in-plane	(0018,9231)	set by creator
	>MR Acquisition Phase Encoding Steps out-of-plane	(0018,9232)	set by creator
	>Percent Sampling	(0018,0093)	set by creator
	>Percent Phase Field of View	(0018,0094)	set by creator
MR Echo	MR Echo Sequence	(0018,9114)	set by creator
	>Echo Number(s)	(0018,0086)	set by creator
	>Effective Echo Time	(0018,9082)	set by creator
MR Modifier	MR Modifier Sequence	(0018,9115)	set by creator
	>Inversion Recovery	(0018,9009)	set by creator
	>Inversion Times	(0018,9079)	set by creator
	>Flow Compensation	(0018,9010)	set by creator
	>Flow Compensation Direction	(0018,9183)	set by creator
	>Spoiling	(0018,9016)	set by creator
	>T2 Preparation	(0018,9021)	set by creator
	>Spectrally Selected Excitation	(0018,9026)	set by creator
	>Spatial Pre-saturation	(0018,9027)	set by creator
	>Partial Fourier	(0018,9081)	set by creator
	>Partial Fourier Direction	(0018,9036)	set by creator
	>Parallel Acquisition	(0018,9077)	set by creator
	>Parallel Acquisition Technique	(0018,9078)	set by creator
	>Parallel Reduction Factor In-plane	(0018,9069)	set by creator
	>Parallel Reduction Factor out-of-plane	(0018,9155)	set by creator
MR Imaging Modifier	MR Imaging Modifier Sequence	(0018,9006)	set by creator
	>Magnetization Transfer	(0018,9020)	set by creator
	>Blood Signal Nulling	(0018,9022)	set by creator
	>Tagging	(0018,9028)	set by creator
	>Tag Spacing First Dimension	(0018,9030)	set by creator
	>Tag Spacing Second Dimension	(0018,9218)	set by creator
	>Tag Angle First Axis	(0018,9019)	set by creator

³ Specific Absorption Rate Sequence, Gradient Output Type, Gradient Output, and Operating Mode Sequence are not set for GRASP reconstructed images due to technical reasons. The values can be found in the related preview images of the GRASP acquisition.

Functional Group	Attribute Name	Tag	Supported Values
Macro			
	>Tag Angle Second Axis	(0018,9219)	set by creator
	>Tag Thickness	(0018,9035)	set by creator
	>Tagging Delay	(0018,9184)	set by creator
	>Transmitter Frequency	(0018,9098)	set by creator
	>Pixel Bandwidth	(0018,0095)	set by creator
MR Receive Coil	MR Receive Coil Sequence	(0018,9042)	set by creator
	>Receive Coil Name	(0018,1250)	set by creator
	>Receive Coil Manufacturer Name	(0018,9041)	set by creator
	>Receive Coil Type	(0018,9043)	set by creator
	>Quadrature Receive Coil	(0018,9044)	set by creator
	>Multi-Coil Definition Sequence	(0018,9045)	set by creator
	>>Multi-Coil Element Name	(0018,9047)	set by creator
	>>Multi-Coil Element Used	(0018,9048)	set by creator
MR Transmit Coil	MR Transmit Coil Sequence	(0018,9049)	set by creator
	>Transmit Coil Name	(0018,1251)	set by creator
	>Transmit Coil Manufacturer Name	(0018,9050)	set by creator
	>Transmit Coil Type	(0018,9051)	set by creator
MR Diffusion	MR Diffusion Sequence	(0018,9117)	set by creator
	>Diffusion b-value	(0018,9087)	set by creator
	>Diffusion Directionality	(0018,9075)	set by creator
	>Diffusion Gradient Direction Sequence	(0018,9076)	set by creator
	>>Diffusion Gradient Orientation	(0018,9089)	set by creator
	>Diffusion b-matrix Sequence	(0018,9601)	set by creator
	>>Diffusion b-value XX	(0018,9602)	set by creator
	>>Diffusion b-value XY	(0018,9603)	set by creator
	>>Diffusion b-value XZ	(0018,9604)	set by creator
	>>Diffusion b-value YY	(0018,9605)	set by creator
	>>Diffusion b-value YZ	(0018,9606)	set by creator
	>>Diffusion b-value ZZ	(0018,9607)	set by creator
MR Averages	MR Averages Sequence	(0018,9119)	set by creator
	>Number of Averages	(0018,0083)	set by creator
MR Velocity Encoding	MR Velocity Encoding Sequence	(0018,9197)	set by creator
	>Velocity Encoding Direction	(0018,9090)	set by creator
	>Velocity Encoding Minimum Value	(0018,9091)	set by creator
	>Velocity Encoding Maximum Value	(0018,9217)	set by creator
MR Arterial Spin Labeling	MR Arterial Spin Labeling Sequence	(0018,9251)	set by creator
	>ASL Technique Description	(0018,9252)	set by creator
	>ASL Context	(0018,9257)	set by creator
	>ASL Slab Sequence	(0018,9260)	set by creator
	>>ASL Slab Number	(0018,9253)	set by creator
	>>ASL Slab Thickness	(0018,9254)	set by creator
	>>ASL Slab Orientation	(0018,9255)	set by creator
	>>ASL Mid Slab Position	(0018,9256)	set by creator
	>>ASL Pulse Train Duration	(0018,9258)	set by creator
	>ASL Crusher Flag	(0018,9259)	set by creator
	>ASL Crusher Flow Limit	(0018,925A)	set by creator
	>ASL Crusher Description	(0018,925B)	set by creator
	>ASLBolus Cut-off Flag	(0018,925C)	set by creator
	>ASLBolus Cut-off Timing Sequence	(0018,925D)	set by creator

Functional Group	Attribute Name	Tag	Supported Values
Macro			
	>>ASL Bolus Cut-off Delay Time	(0018,925F)	set by creator
	>>ASL Bolus Cut-off Technique	(0018,925E)	set by creator
SIEMENS MR Shared	<i>include Table 91: Attributes of SIEMENS MR</i>		
SIEMENS MR Frame	<i>include Table 93: Attributes of SIEMENS MR</i>		

9.1.1.1.14 Cardiac Synchronization Module

Attribute Name	Tag	Supported Values
Cardiac Synchronization Technique	(0018,9037)	set by creator
Cardiac Signal Source	(0018,9085)	set by creator
Cardiac RR Interval Specified	(0018,9070)	set by creator
Low R-R Value	(0018,1081)	set by creator
High R-R Value	(0018,1082)	set by creator
Intervals Acquired	(0018,1083)	set by creator
Intervals Rejected	(0018,1084)	set by creator

9.1.1.1.15 Respiratory Synchronization Module

Attribute Name	Tag	Supported Values
Respiratory Motion Compensation Technique	(0018,9170)	set by creator

9.1.1.1.16 Bulk Motion Synchronization Module

Attribute Name	Tag	Supported Values
Bulk Motion Compensation Technique	(0018,9172)	set by creator
Bulk Motion Signal Source	(0018,9173)	set by creator

9.1.1.1.17 Supplemental Palette Color Lookup Table Module

Attribute Name	Tag	Supported Values
Red Palette Color Lookup Table Descriptor	(0028,1101)	set by creator
Green Palette Color Lookup Table Descriptor	(0028,1102)	set by creator
Blue Palette Color Lookup Table Descriptor	(0028,1103)	set by creator
Red Palette Color Lookup Table Data	(0028,1201)	set by creator

Attribute Name	Tag	Supported Values
Green Palette Color Lookup Table Data	(0028,1202)	set by creator
Blue Palette Color Lookup Table Data	(0028,1203)	set by creator

9.1.1.1.18 Acquisition Context Module

Attribute Name	Tag	Supported Values
Acquisition Context Sequence	(0040,0555)	TID 99_3100

9.1.1.1.18.1 MR Acquisition Context TID 99_3100

The MR Acquisition Context TID 99_3100 is used in the Acquisition Context Sequence (0040,0555) of Enhanced MR Images.

Type: Extensible

VT	Concept Name	VM	Req Type	Value Set Constraint
CODE	EV (A-52, 99SMS_CTMR, "MR Technique")	1	M	DCID(A-200)

9.1.1.1.18.2 MR Technique Context Group A-200

Type: Extensible

Coding Scheme Designator (0008,0102)	Coding Scheme Version (0008,0103)	Code Value (0008,0100)	Code Meaning (0008,0104)
99SMS_CTMR	1.0	A-200	GRASP
99SMS_CTMR	1.0	A-202	FastView
99SMS_CTMR	1.0	A-204	Angio
99SMS_CTMR	1.0	A-206	BOLD
99SMS_CTMR	1.0	A-208	Diffusion
99SMS_CTMR	1.0	A-210	DTI
99SMS_CTMR	1.0	A-212	Perfusion
99SMS_CTMR	1.0	A-214	TWIST

9.1.1.1.19 Enhanced MR Image Module

Attribute Name	Tag	Supported Values
Acquisition Number	(0020,0012)	set by creator

Attribute Name	Tag	Supported Values
Acquisition Date Time	(0008,002A)	set by creator
Acquisition Duration	(0018,9073)	set by creator
Content Qualification	(0018,9004)	set by creator
Resonant Nucleus	(0018,9100)	set by creator
k-space Filtering	(0018,9064)	set by creator
Magnetic Field Strength	(0018,0087)	set by creator
Applicable Safety Standard Agency	(0018,9174)	set by creator
Image Comments	(0020,4000)	set by creator
Image Type	(0008,0008)	set by creator
Pixel Presentation	(0008,9205)	set by creator
Volumetric Properties	(0008,9206)	set by creator
Volume Based Calculation Technique	(0008,9207)	set by creator
Complex Image Component	(0008,9208)	set by creator
Acquisition Contrast	(0008,9209)	set by creator
Samples per Pixel	(0028,0002)	1
Photometric Interpretation	(0028,0004)	MONOCHROME2
Bits Allocated	(0028,0100)	16
Bits Stored	(0028,0101)	12 or 16
High Bit	(0028,0102)	11 or 15
Pixel Representation	(0028,0103)	0
Burned In Annotation	(0028,0301)	NO
Lossy Image Compression	(0028,2110)	00
Presentation LUT Shape	(2050,0020)	IDENTITY

9.1.1.1.20 MR Pulse Sequence Module

Attribute Name	Tag	Supported Values
Pulse Sequence Name	(0018,9005)	set by creator
MR Acquisition Type	(0018,0023)	set by creator
Echo Pulse Sequence	(0018,9008)	set by creator
Multiple Spin Echo	(0018,9011)	set by creator
Multi-planar Excitation	(0018,9012)	set by creator
Phase Contrast	(0018,9014)	set by creator
Velocity Encoding Acquisition Sequence	(0018,9092)	set by creator
> Velocity Encoding Direction	(0018,9090)	set by creator
Time of Flight Contrast	(0018,9015)	set by creator
Arterial Spin Labeling Contrast	(0018,9250)	set by creator
Steady State Pulse Sequence	(0018,9017)	set by creator
Echo Planar Pulse Sequence	(0018,9018)	set by creator

Attribute Name	Tag	Supported Values
Saturation Recovery	(0018,9024)	set by creator
Spectral Selected Suppression	(0018,9025)	set by creator
Oversampling Phase	(0018,9029)	set by creator
Geometry of k-Space Traversal	(0018,9032)	set by creator
Rectilinear Phase Encode Reordering	(0018,9034)	set by creator
Segmented k-Space Traversal	(0018,9033)	set by creator
Coverage of k-Space	(0018,9094)	set by creator
Number of k-Space Trajectories	(0018,9093)	set by creator

9.1.1.1.21 ICC Profile Module

Attribute Name	Tag	Supported Values
ICC Profile	(0028,2000)	set by creator
Color Space	(0028,2002)	SRGB

9.1.1.1.22 SOP Common Module

Attribute Name	Tag	Supported Values
SOP Class UID	(0008,0016)	SOP specific UID
SOP Instance UID	(0008,0018)	set by creator
Specific Character Set	(0008,0005)	set by creator
Instance Creation Date	(0008,0012)	date the SOP instance was created
Instance Creation Time	(0008,0013)	time the SOP instance was created

9.1.1.1.23 Common Instance Reference Module

Attribute Name	Tag	Supported Values
Referenced Series Sequence	(0008,1115)	set by creator
>Series Instance UID	(0020,000E)	set by creator
> Referenced Instance Sequence	(0008,114A)	set by creator
>>Referenced SOP Class UID	(0008,1150)	set by creator
>> Referenced SOP Instance UID	(0008,1155)	set by creator

9.1.1.2 Enhanced MR Color Image IOD

The Enhanced MR Color Image IOD supports the same DICOM attributes as the Enhanced MR Image IOD except for the Photometric Interpretation which is RGB. Also, Supplemental Palette Color Lookup Table module, Pixel Value Transformation Macro, Frame VOI LUT Macro, and Real World Value Mapping Macro are not part of this IOD.

IE	Module	Reference	Usage
Patient	Patient	see chapter 9.1.1.1.1	always
Study	General Study	see chapter 9.1.1.1.2	always
	Patient Study	see chapter 9.1.1.1.3	always
Series	General Series	see chapter 9.1.1.1.4	always
	MR Series	see chapter 9.1.1.1.5	always
Frame of Reference	Frame of Reference	see chapter 9.1.1.1.6	always
Equipment	General Equipment	see chapter 9.1.1.1.7	always
	Enhanced General Equipment	see chapter 9.1.1.1.8	always
Image	Image Pixel	see chapter 9.1.1.2.1	always
	Enhanced Contrast/Bolus	see chapter 9.1.1.1.10	always
	Multi-frame Functional Groups	see chapter 9.1.1.1.11	always
	Multi-frame Dimension	see chapter 9.1.1.1.12	always
	Cardiac Synchronization	see chapter 9.1.1.1.14	in case of cardiac triggering
	Respiratory Synchronization	see chapter 9.1.1.1.15	in case of respiratory triggering
	Bulk Motion Synchronization	see chapter 9.1.1.1.16	in case of bulk motion triggering
	Acquisition Context	see chapter 9.1.1.1.18	always
	Enhanced MR Image	see chapter 9.1.1.2.2	always
	MR Pulse Sequence	see chapter 9.1.1.1.20	always
	ICC Profile	see chapter 9.1.1.1.21	always
	SOP Common	see chapter 9.1.1.1.22	always (with SOP Class UID for Enhanced MR Color Image)
	Common Instance Reference	see chapter 9.1.1.1.23	always
	SIEMENS MR Common	see chapter 9.2.1.7	always

9.1.1.2.1 Image Pixel Module

Attribute Name	Tag	Supported Values
Samples per Pixel	(0028,0002)	3
Photometric Interpretation	(0028,0004)	RGB

Attribute Name	Tag	Supported Values
Rows	(0028,0010)	set by creator
Columns	(0028,0011)	set by creator
Bits Allocated	(0028,0100)	8
Bits Stored	(0028,0101)	8
High Bit	(0028,0102)	7
Pixel Representation	(0028,0103)	0
Planar Configuration	(0028,0006)	0
Pixel Data	(7FE0,0010)	set by creator

9.1.1.2.2 Enhanced MR Image Module (for Enhanced MR Color Image)

See chapter 9.1.1.1.19, different attribute values for Enhanced MR Color Images are listed below.

Attribute Name	Tag	Supported Values
Samples per Pixel	(0028,0002)	3
Photometric Interpretation	(0028,0004)	RGB
Bits Allocated	(0028,0100)	8
Bits Stored	(0028,0101)	8
High Bit	(0028,0102)	7
Pixel Presentation	(0008,9205)	TRUE_COLOR
Presentation LUT Shape	(2050,0020)	not available

9.1.1.3 MR Spectroscopy IOD

This chapter describes the DICOM attributes of MR Spectroscopy Instances performed by the MR acquisition.

IE	Module	Reference	Usage
Patient	Patient	see chapter 9.1.1.1.1	always
Study	General Study	see chapter 9.1.1.1.2	always
	Patient Study	see chapter 9.1.1.1.3	always
Series	General Series	see chapter 9.1.1.1.4	always
	MR Series	see chapter 9.1.1.1.5	always
Frame of Reference	Frame of Reference	see chapter 9.1.1.1.6	always
Equipment	General Equipment	see chapter 9.1.1.1.7	always
	Enhanced General Equipment	see chapter 9.1.1.1.8	always
MR Spectroscopy	Enhanced Contrast/Bolus	see chapter 9.1.1.1.10	always
	Multi-frame Functional Groups	see chapter 9.1.1.1.11	always

IE	Module	Reference	Usage
	Multi-frame Dimension	see chapter 9.1.1.1.12	always
	Cardiac Synchronization	see chapter 9.1.1.1.14	in case of cardiac triggering
	Respiratory Synchronization	see chapter 9.1.1.1.15	in case of respiratory triggering
	Bulk Motion Synchronization	see chapter 9.1.1.1.16	in case of bulk motion triggering
	Acquisition Context	see chapter 9.1.1.1.18	always
	MR Spectroscopy	see chapter 9.1.1.3.2	always
	MR Spectroscopy Pulse Sequence	see chapter 9.1.1.3.3	always
	MR Spectroscopy Data	see chapter 9.1.1.3.4	always
	SOP Common	see chapter 9.1.1.1.22	always (with SOP Class UID for MR Spectroscopy)
	Common Instance Reference	see chapter 9.1.1.1.23	always
	SIEMENS MR Common	see chapter 9.2.1.7	always

9.1.1.3.1 MR Spectroscopy Functional Groups

Functional Group Macro	Attribute Name	Tag	Supported Values
Pixel Measures	Pixel Measures Sequence	(0028,9110)	set by creator
	>Pixel Spacing	(0018,0030)	set by creator
	>Slice Thickness	(0028,0050)	set by creator
Frame Content	Frame Content Sequence	(0020,9111)	set by creator
	>Frame Acquisition Number	(0020,9156)	set by creator
	>Frame Reference Date Time	(0018,9151)	set by creator
	>Frame Acquisition Date Time	(0018,9074)	set by creator
	>Frame Acquisition Duration	(0018,9220)	set by creator
	>Dimension Index Values	(0020,9157)	set by creator
	>Temporal Position Index	(0020,9128)	set by creator
	>Stack ID	(0020,9056)	set by creator
	>In-Stack Position Number	(0020,9057)	set by creator
	>Frame Comments	(0020,9158)	set by creator
Plane Position	Plane Position Sequence	(0020,9113)	set by creator
	>Image Position (Patient)	(0020,0032)	set by creator
Plane Orientation	Plane Orientation Sequence	(0020,9116)	set by creator
	>Image Orientation (Patient)	(0020,0037)	set by creator

Functional Group Macro	Attribute Name	Tag	Supported Values
Referenced Image	Referenced Image Sequence	(0008,1140)	set by creator
	>Referenced SOP Class UID	(0008,1150)	set by creator
	>Referenced SOP Instance UID	(0008,1155)	set by creator
	>Referenced Frame Number	(0008,1160)	set by creator
	>Purpose of Referenced Code Sequence	(0040,A170)	set by creator
	>>Code Value	(0008,0100)	set by creator
	>>Coding Scheme Designator	(0008,0102)	set by creator
	>>Code Meaning	(0008,0104)	set by creator
Derivation Image	Derivation Image Sequence	(0008,9124)	set by creator
	>Derivation Code Sequence	(0008,9215)	set by creator
	>>Code Value	(0008,0100)	set by creator
	>>Coding Scheme Designator	(0008,0102)	set by creator
	>>Code Meaning	(0008,0104)	set by creator
	>Source Image Sequence	(0008,2112)	set by creator
	>>Referenced SOP Class UID	(0008,1150)	set by creator
	>>Referenced SOP Instance UID	(0008,1155)	set by creator
	>>Referenced Frame Number	(0008,1160)	set by creator
	>>Purpose of Referenced Code Sequence	(0040,A170)	set by creator
	>>>Code Value	(0008,0100)	set by creator
	>>>Coding Scheme Designator	(0008,0102)	set by creator
	>>>Code Meaning	(0008,0104)	set by creator
Frame Anatomy	Frame Anatomy Sequence	(0020,9071)	set by creator
	>Frame Laterality	(0020,9072)	set by creator
	>Anatomic Region Sequence	(0008,2218)	set by creator
	>>Code Value	(0008,0100)	set by creator
	>>Coding Scheme Designator	(0008,0102)	set by creator
	>>Code Meaning	(0008,0104)	set by creator
Contrast/Bolus Usage	Contrast/Bolus Usage Sequence	(0018,9341)	set by creator
	>Contrast/Bolus Agent Number	(0018,9337)	1
	>Contrast/Bolus Agent Administered	(0018,9342)	set by creator
	>Contrast/Bolus Agent Detected	(0018,9343)	set by creator
	>Contrast/Bolus Agent Phase	(0018,9344)	set by creator
MR Spectroscopy Frame Type	MR Spectroscopy Frame Type Sequence	(0018,9227)	set by creator
	>Frame Type	(0008,9007)	set by creator

Functional Group Macro	Attribute Name	Tag	Supported Values
	>Volumetric Properties	(0008,9206)	set by creator
	>Volume Based Calculation Technique	(0008,9207)	set by creator
	>Complex Image Component	(0008,9208)	set by creator
	>Acquisition Contrast	(0008,9209)	set by creator
MR Timing and Related Parameters	MR Timing and Related Parameters Sequence	(0018,9112)	set by creator
	>Repetition Time	(0018,0080)	set by creator
	>Flip Angle	(0018,1314)	set by creator
	>Echo Train Length	(0018,0091)	set by creator
	>RF Echo Train Length	(0018,9240)	set by creator
	>Gradient Echo Train Length	(0018,9241)	set by creator
	>Specific Absorption Rate Sequence	(0018,9239)	set by creator
	>>Specific Absorption Rate Definition	(0018,9179)	set by creator
	>>Specific Absorption Rate Value	(0018,9181)	set by creator
	>Gradient Output Type	(0018,9180)	set by creator
	>Gradient Output	(0018,9182)	set by creator
	>Operation Mode Sequence	(0018,9176)	set by creator
	>>Operating Mode Type	(0018,9177)	set by creator
	>>Operating Mode	(0018,9178)	set by creator
MR Spectroscopy FOV/Geometry	MR Spectroscopy FOV/Geometry Sequence	(0018,9103)	set by creator
	>Spectroscopy Acquisition Data Columns	(0018,9127)	set by creator
	>Spectroscopy Acquisition Phase Rows	(0018,9095)	set by creator
	>Spectroscopy Acquisition Phase Columns	(0018,9234)	set by creator
	>Spectroscopy Acquisition Out-of-Plane Phase Steps	(0018,9159)	set by creator
	>Percent Sampling	(0018,0093)	set by creator
	>Percent Phase Field of View	(0018,0094)	set by creator
MR Echo	MR Echo Sequence	(0018,9114)	set by creator
	>Effective Echo Time	(0018,9082)	set by creator
MR Modifier	MR Modifier Sequence	(0018,9115)	set by creator
	>Inversion Recovery	(0018,9009)	set by creator
	>Inversion Times	(0018,9079)	set by creator
	>Flow Compensation	(0018,9010)	set by creator
	>Flow Compensation Direction	(0018,9183)	set by creator
	>Spoiling	(0018,9016)	set by creator
	>T2 Preparation	(0018,9021)	set by creator

Functional Group Macro	Attribute Name	Tag	Supported Values
	>Spectrally Selected Excitation	(0018,9026)	set by creator
	>Spatial Pre-saturation	(0018,9027)	set by creator
	>Partial Fourier	(0018,9081)	set by creator
	>Partial Fourier Direction	(0018,9036)	set by creator
	>Parallel Acquisition	(0018,9077)	set by creator
	>Parallel Acquisition Technique	(0018,9078)	set by creator
	>Parallel Reduction Factor In-plane	(0018,9069)	set by creator
	>Parallel Reduction Factor out-of-plane	(0018,9155)	set by creator
MR Receive Coil	MR Receive Coil Sequence	(0018,9042)	set by creator
	>Receive Coil Name	(0018,1250)	set by creator
	>Receive Coil Manufacturer Name	(0018,9041)	set by creator
	>Receive Coil Type	(0018,9043)	set by creator
	>Quadrature Receive Coil	(0018,9044)	set by creator
	>Multi-Coil Definition Sequence	(0018,9045)	set by creator
	>>Multi-Coil Element Name	(0018,9047)	set by creator
	>>Multi-Coil Element Used	(0018,9048)	set by creator
MR Transmit Coil	MR Transmit Coil Sequence	(0018,9049)	set by creator
	>Transmit Coil Name	(0018,1251)	set by creator
	>Transmit Coil Manufacturer Name	(0018,9050)	set by creator
	>Transmit Coil Type	(0018,9051)	set by creator
MR Averages	MR Averages Sequence	(0018,9119)	set by creator
	>Number of Averages	(0018,0083)	set by creator
SIEMENS MR Shared	<i>include Table 91: Attributes of SIEMENS MR Shared Macro</i>		
SIEMENS MR Frame	<i>include Table 93: Attributes of SIEMENS MR Frame Macro</i>		

9.1.1.3.2 MR Spectroscopy Module

Attribute Name	Tag	Supported Values
Acquisition Number	(0020,0012)	set by creator
Acquisition Date Time	(0018,002A)	set by creator
Acquisition Duration	(0018,9073)	set by creator
Referenced Raw Data Sequence	(0008,9121)	set by creator
Content Qualification	(0018,9004)	set by creator
Resonant Nucleus	(0018,9100)	set by creator

Attribute Name	Tag	Supported Values
k-space Filtering	(0018,9064)	set by creator
Magnetic Field Strength	(0018,0087)	set by creator
Applicable Safety Standard Agency	(0018,9174)	set by creator
Image Comments	(0020,4000)	set by creator
Image Type	(0008,0008)	set by creator
Volumetric Properties	(0008,9206)	set by creator
Volume Based Calculation Technique	(0008,9207)	set by creator
Complex Image Component	(0008,9208)	set by creator
Acquisition Contrast	(0008,9209)	set by creator
Transmitter Frequency	(0018,9098)	set by creator
Spectral Width	(0018,9052)	set by creator
Chemical Shift Reference	(0018,9053)	set by creator
Volume Localisation Technique	(0018,9054)	set by creator
Volume Localization Sequence	(0018,9126)	set by creator
>Slab Thickness	(0018,9104)	set by creator
>Slab Orientation	(0018,9105)	set by creator
>Mid SlabPosition	(0018,9106)	set by creator
De-coupling	(0018,9059)	set by creator
De-coupling Nucleus	(0018,9060)	set by creator
De-coupling Frequency	(0018,9061)	set by creator
De-coupling Method	(0018,9062)	set by creator
De-coupling Chemical Shift Reference	(0018,9063)	set by creator
Time Domain Filtering	(0018,9065)	set by creator
Number Of Zero Fills	(0018,9066)	set by creator
Baseline Correction	(0018,9067)	set by creator
Frequency Correction	(0018,9101)	set by creator
First Order Phase Correction	(0018,9198)	set by creator
Water Referenced Phase Correction	(0018,9199)	set by creator
Water Reference Acquisition	(0018,9297)	set by creator
Referenced Instance Sequence	(0008,114A)	set by creator
>Purpose of Reference Code Sequence	(0040,A170)	set by creator

9.1.1.3.3 MR Spectroscopy Pulse Sequence Module

Attribute Name	Tag	Supported Values
Pulse Sequence Name	(0018,9005)	set by creator
MR Spectroscopy Acquisition Type	(0018,9200)	set by creator
Echo Pulse Sequence	(0018,9008)	set by creator

Attribute Name	Tag	Supported Values
Multi Spin Echo	(0018,9011)	set by creator
Multi-planar Excitation	(0018,9012)	set by creator
Steady State Pulse Sequence	(0018,9017)	set by creator
Echo Planar Pulse Sequence	(0018,9018)	set by creator
Spectrally Selected Suppression	(0018,9025)	set by creator
Geometry of k-Space Traversal	(0018,9032)	set by creator
Rectilinear Phase Encode Reordering	(0018,9034)	set by creator
Segmented k-Space Traversal	(0018,9033)	set by creator
Coverage of k-Space	(0018,9094)	set by creator
Number of k-Space Trajectories	(0018,9093)	set by creator
Echo Peak Position	(0018,9298)	set by creator

9.1.1.3.4 MR Spectroscopy Data Module

Attribute Name	Tag	Supported Values
Rows	(0028,0010)	set by creator
Columns	(0028,0011)	set by creator
Data Point Rows	(0028,9001)	set by creator
Data Point Columns	(0028,9002)	set by creator
Data Representation	(0028,9108)	set by creator
Signal Domain Columns	(0028,9003)	set by creator
Signal Domains Rows	(0028,9235)	set by creator
First Order Phase Correction Angle	(5600,0010)	set by creator
Spectroscopy Data	(5600,0020)	set by creator

9.1.1.4 MR Image

This chapter describes the DICOM attributes of MR Image instances created in interoperability mode. The following table lists the modules created by syngo® MR.

IE	Module	Reference	Usage
Patient	Patient	see chapter 9.1.1.1.1	always
Study	General Study	see chapter 9.1.1.1.2	always
	Patient Study	see chapter 9.1.1.1.3	always
Series	General Series	see chapter 9.1.1.1.4	always
Frame of Reference	Frame of Reference	see chapter 9.1.1.1.6	always
Equipment	General Equipment	see chapter 9.1.1.1.7	always

IE	Module	Reference	Usage
Image	General Image	see chapter 9.1.1.4.1	always
	General Reference	see chapter 9.1.1.4.2	always
	Image Plane	see chapter 9.1.1.4.3	always
	Image Pixel	see chapter 9.1.1.1.9	always
	Contrast/Bolus	see chapter 9.1.1.4.4	always
	MR Image	see chapter 9.1.1.4.5	always
	Overlay Plane	see chapter 9.1.1.4.6	always
	VOI LUT	see chapter 9.1.1.4.7	always
	SOP Common	see chapter 9.1.1.1.22	always (with SOP Class UID for MR Image)
	Common Instance Reference	see chapter 9.1.1.1.23	always
	SIEMENS MR Series	see chapter 9.2.1.2	always
	SIEMENS MR Image/Frame	see chapter 9.2.1.5	always
	SIEMENS MR Common	see chapter 9.2.1.7	always
	SIEMENS MR HEADER	see chapter 9.2.1.8	always

9.1.1.4.1 General Image Module

Attribute Name	Tag	Supported Values
Instance Number	(0020,0013)	set by creator
Patient Orientation	(0020,0020)	set by creator
Content Date	(0008,0023)	set by creator
Content Time	(0008,0033)	set by creator
Image Type	(0008,0008)	set by creator
Acquisition Number	(0020,0012)	set by creator
Acquisition Date	(0008,0022)	set by creator
Acquisition Time	(0008,0032)	set by creator
Acquisition DateTime	(0008,002A)	set by creator
Image Comments	(0020,4000)	set by creator
Presentation LUT Shape	(2050,0020)	set by creator

9.1.1.4.2 General Reference Module

Attribute Name	Tag	Supported Values
Referenced Image Sequence	(0008,1140)	set by creator
>Referenced SOP Class UID	(0008,1150)	set by creator

Attribute Name	Tag	Supported Values
>Referenced SOP Instance UID	(0008,1155)	set by creator
>Referenced Frame Number	(0008,1160)	If referenced SOP Instance is a multi-frame image

9.1.1.4.3 Image Plane Module

Attribute Name	Tag	Supported Values
Pixel Spacing	(0028,0030)	set by creator
Image Orientation (Patient)	(0020,0037)	set by creator
Image Position (Patient)	(0020,0032)	set by creator
Slice Thickness	(0018,0050)	set by creator
Slice Location	(0020,1041)	set by creator

9.1.1.4.4 Contrast/Bolus Module

Attribute Name	Tag	Supported Values
Contrast/Bolus Agent	(0018,0010)	set by creator
Contrast/Bolus Agent Sequence	(0018,0012)	set by creator
>Code Value	(0008,0100)	set by creator
>Coding Scheme Designator	(0008,0102)	set by creator
>Coding Scheme Version	(0008,0103)	set by creator
>Code Meaning	(0008,0104)	set by creator
Contrast/Bolus Route	(0018,1040)	set by creator
Contrast/Bolus Administration Route Sequence	(0018,0014)	set by creator
>Code Value	(0008,0100)	set by creator
>Coding Scheme Designator	(0008,0102)	set by creator
>Coding Scheme Version	(0008,0103)	set by creator
>Code Meaning	(0008,0104)	set by creator
Contrast/Bolus Volume	(0018,1041)	set by creator
Contrast/Bolus Start Time	(0018,1042)	set by creator
Contrast/Bolus Stop Time	(0018,1043)	set by creator
Contrast/Bolus Total Dose	(0018,1044)	set by creator
Contrast Flow Rate	(0018,1046)	set by creator
Contrast Flow Duration	(0018,1047)	set by creator
Contrast/Bolus Ingredient	(0018,1048)	set by creator
Contrast/Bolus Ingredient Concentration	(0018,1049)	set by creator

9.1.1.4.5 MR Image Module

Attribute Name	Tag	Supported Values
Image Type	(0008,0008)	set by creator
Samples per Pixel	(0028,0002)	set by creator
Photometric Interpretation	(0028,0004)	set by creator
Bits Allocated	(0028,0100)	set by creator
Bits Stored	(0028,0101)	set by creator
High Bit	(0028,0102)	set by creator
Scanning Sequence	(0018,0020)	set by creator
Sequence Variant	(0018,0021)	set by creator
Scan Options	(0018,0022)	set by creator
MR Acquisition Type	(0018,0023)	set by creator
Repetition Time	(0018,0080)	set by creator
Echo Time	(0018,0081)	set by creator
Echo Train Length	(0018,0091)	set by creator
Inversion Time	(0018,0082)	set by creator
Trigger Time	(0018,1060)	set by creator
Sequence Name	(0018,0024)	set by creator
Angio Flag	(0018,0025)	set by creator
Number of Averages	(0018,0083)	set by creator
Imaging Frequency	(0018,0084)	set by creator
Imaged Nucleus	(0018,0085)	set by creator
Echo Number(s)	(0018,0086)	set by creator
Magnetic Field Strength	(0018,0087)	set by creator
Spacing Between Slices	(0018,0088)	set by creator
Number of Phase Encoding Steps	(0018,0089)	set by creator
Percent Sampling	(0018,0093)	set by creator
Percent Phase Field of View	(0018,0094)	set by creator
Pixel Bandwidth	(0018,0095)	set by creator
Nominal Interval	(0018,1062)	set by creator
Beat Rejection Flag	(0018,1080)	set by creator
Low R-R Value	(0018,1081)	set by creator
High R-R Value	(0018,1082)	set by creator
Intervals Acquired	(0018,1083)	set by creator
Intervals Rejected	(0018,1084)	set by creator
PVC Rejection	(0018,1085)	set by creator
Skip Beats	(0018,1086)	set by creator
Heart Rate	(0018,1088)	set by creator
Cardiac Number of Images	(0018,1090)	set by creator

Attribute Name	Tag	Supported Values
Trigger Window	(0018,1094)	set by creator
Reconstruction Diameter	(0018,1100)	set by creator
Receive Coil Name	(0018,1250)	set by creator
Transmit Coil Name	(0018,1251)	set by creator
Acquisition Matrix	(0018,1310)	set by creator
In-plane Phase Encoding Direction	(0018,1312)	set by creator
Flip Angle	(0018,1314)	set by creator
SAR	(0018,1316)	set by creator
Variable Flip Angle Flag	(0018,1315)	set by creator
dB/dt	(0018,1318)	set by creator
Temporal Position Identifier	(0020,0100)	set by creator
Number of Temporal Positions	(0020,0105)	set by creator
Temporal Resolution	(0020,0110)	set by creator
B1rms	(0018,1320)	set by creator

9.1.1.4.6 Overlay Plane Module

Attribute Name	Tag	Supported Values
Overlay Rows	(60xx,0010)	set by creator
Overlay Columns	(60xx,0011)	set by creator
Overlay Type	(60xx,0040)	set by creator
Overlay Origin	(60xx,0050)	set by creator
Overlay Bits Allocated	(60xx,0100)	set by creator
Overlay Bit Position	(60xx,0102)	set by creator
Overlay Data	(60xx,3000)	set by creator
Overlay Description	(60xx,0022)	set by creator
Overlay Subtype	(60xx,0045)	set by creator
Overlay Label	(60xx,1500)	set by creator
ROI Area	(60xx,1301)	set by creator
ROI Mean	(60xx,1302)	set by creator
ROI Standard Deviation	(60xx,1303)	set by creator

9.1.1.4.7 VOI LUT Module

Attribute Name	Tag	Supported Values
VOI LUT Sequence	(0028,3010)	set by creator
>LUT Descriptor	(0028,3002)	set by creator

Attribute Name	Tag	Supported Values
>LUT Explanation	(0028,3003)	set by creator
>LUT Data	(0028,3006)	set by creator
Window Center	(0028,1050)	set by creator
Window Width	(0028,1051)	set by creator
Window Center and Width Explanation	(0028,1055)	set by creator
VOI LUT Function	(0028,1056)	set by creator

9.1.1.5 Raw Data

Neuro Diffusion Tensor Imaging data are encoded in the Raw Data SOP Class.

IE	Module	Reference	Usage
Patient	Patient	see chapter 9.1.1.1.1	always
Study	General Study	see chapter 9.1.1.1.2	always
	Patient Study	see chapter 9.1.1.1.3	always
Series	General Series	see chapter 9.1.1.1.4	always
Frame of Reference	Frame of Reference	see chapter 9.1.1.1.6	always
Equipment	General Equipment	see chapter 9.1.1.1.7	always
Image	Acquisition Context	see chapter 9.1.1.1.18	always
	Raw Data	see chapter 9.1.1.5.1	always
	SIEMENS MR Raw Data	see chapter 9.2.1.9	always
	SOP Common	see chapter 9.1.1.1.22	always (with SOP Class UID for Raw Data)
	SIEMENS MR Series	see chapter 9.2.1.2	always
	SIEMENS MR Image/Frame	see chapter 9.2.1.5	always
	SIEMENS MR Common	see chapter 9.2.1.7	always

9.1.1.5.1 Raw Data Module

Attribute Name	Tag	Supported Values
Instance Number	(0020,0013)	set by creator
Content Date	(0008,0023)	set by creator
Content Time	(0008,0033)	set by creator
Image Type	(0008,0008)	set by creator
Acquisition DateTime	(0008,002A)	set by creator
Creator_Version UID	(0008,9123)	set by creator

9.1.1.6 Multi-frame Grayscale Word Secondary Capture Image

For some use cases Multi-frame Grayscale Word SC Image instances are created for documentation and reporting purposes. The following table lists the modules created by *syngo*® MR XA51A.

IE	Module	Reference	Presence of Module
Patient	Patient	see chapter 9.1.1.1.1	always
Study	General Study	see chapter 9.1.1.1.2	always
	Patient Study	see chapter 9.1.1.1.3	always
Series	General Series	see chapter 9.1.1.1.4	always
Frame of Reference	Frame of Reference	see chapter 9.1.1.1.6	always
Equipment	General Equipment	see chapter 9.1.1.1.7	always
	SC Equipment	see chapter 9.1.1.6.1	always
Image	General Image	see chapter 9.1.1.4.1	always
	Image Pixel	see chapter 9.1.1.1.9	always
	Cine	n. a.	not used
	Multi-frame	see chapter 9.1.1.6.2	always
	Frame Pointers	see chapter 9.1.1.6.3	always
	Multi-frame Functional Groups	see chapter 9.1.1.6.4	always
	SC Image	see chapter 9.1.1.6.6	always
	SC Multi-frame Image	see chapter 9.1.1.6.7	always
	SC Multi-frame Vector	see chapter 9.1.1.6.8	always
	VOI LUT	see chapter 9.1.1.4.6	always
	SOP Common	see chapter 9.1.1.1.22	always (with SOP Class UID for Multi-frame Grayscale Word Secondary Capture Image)
	Common Instance Reference	see chapter 9.1.1.1.23	always
	SIEMENS MR Common	see chapter 9.2.1.7	always

9.1.1.6.1 SC Equipment Module

Attribute Name	Tag	Supported Values
Conversion Type	(0008,0064)	set by creator
Modality	(0008,0060)	MR

9.1.1.6.2 Multi-frame Module

Attribute Name	Tag	Supported Values
Number of Frames	(0028,0008)	set by creator
Frame Increment Pointer	(0028,0009)	set by creator

9.1.1.6.3 Frame Pointers Module

Attribute Name	Tag	Supported Values
Representative Frame Number	(0028,6010)	set by creator
Frame Numbers of Interest (FOI)	(0028,6020)	set by creator
Frame of Interest Description	(0028,6022)	set by creator
Frame of Interest Type	(0028,6023)	set by creator

9.1.1.6.4 Multi-frame Functional Groups Module

Attribute Name	Tag	Supported Values
Shared Functional Groups Sequence	(5200,9229)	set by creator
> Include one or more Functional Group Macros		
Per-frame Functional Groups Sequence	(5200,9230)	set by creator
> Include one or more Functional Group Macros		
Instance Number	(0020,0013)	set by creator
Content Date	(0008,0023)	set by creator
Content Time	(0008,0033)	set by creator
Number of Frames	(0028,0008)	set by creator
Representative Frame Number	(0028,6010)	set by creator

9.1.1.6.5 Multi-frame Grayscale Word SC Image Functional Group Macros

Functional Group Macro	Attribute Name	Tag	Supported Values
Pixel Measures (if Plane Position (Patient) or Plane Orientation (Patient) Macros Present)	Pixel Measures Sequence	(0028,9110)	set by creator
	>Pixel Spacing	(0018,0030)	set by creator
	>Slice Thickness	(0028,0050)	set by creator
Plane Position (Patient) (if Pixel Measures or Plane Orientation (Patient) Macros Present)	Plane Position Sequence	(0020,9113)	set by creator
	>Image Position (Patient)	(0020,0032)	set by creator
Plane Orientation (Patient) (if Pixel Measures or Plane Position (Patient) Macros Present)	Plane Orientation Sequence	(0020,9116)	set by creator
	>Image Orientation (Patient)	(0020,0037)	set by creator

Functional Group Macro	Attribute Name	Tag	Supported Values
SIEMENS MR Shared	include Table 91: Attributes of SIEMENS MR Shared Macro		
SIEMENS MR Frame	include Table 93: Attributes of SIEMENS MR Frame MacroTable 93: Attributes of SIEMENS MR		

9.1.1.6.6 SC Image Module

Attribute Name	Tag	Supported Values
Date of Secondary Capture	(0018,1012)	set by creator
Time of Secondary Capture	(0018,1014)	set by creator
Nominal Scanned Pixel Spa	(0018,2010)	set by creator
Pixel Spacing	(0028,0030)	set by creator
Pixel Spacing Calibration Type	(0028,0A02)	set by creator
Pixel Spacing Calibration Description	(0018,1012)	set by creator

9.1.1.6.7 SC Multi-frame Image Module

Attribute Name	Tag	Supported Values
Burned In Annotation	(0028,0301)	set by creator
Recognizable Visual Features	(0028,0302)	set by creator
Presentation LUT Shape	(2050,0020)	set by creator
Illumination	(2010,015E)	set by creator
Reflected Ambient Light	(2010,0160)	set by creator
Rescale Intercept	(0028,1052)	set by creator
Rescale Slope	(0028,1053)	set by creator
Rescale Type	(0028,1054)	set by creator
Frame Increment Pointer	(0028,0009)	set by creator
Nominal Scanned Pixel Spacing	(0018,2010)	set by creator
Pixel Spacing	(0028,0030)	set by creator
Pixel Spacing Calibration Type	(0028,0A02)	set by creator
Pixel Spacing Calibration Description	(0028,0A04)	set by creator
Digitizing Device Transport Direction	(0018,2020)	set by creator
Rotation of Scanned Film	(0018,2030)	set by creator

9.1.1.6.8 SC Multi-frame Vector Module

Attribute Name	Tag	Supported Values
Frame Time Vector	(0018,1065)	set by creator
Page Number Vector	(0018,2001)	set by creator
Frame Label Vector	(0018,2002)	set by creator
Frame Primary Angle Vector	(0018,2003)	set by creator
Frame Secondary Angle Vector	(0018,2004)	set by creator
Slice Location Vector	(0018,2005)	set by creator
Display Window Label Vector	(0018,2006)	set by creator

9.1.1.7 Secondary Capture Image

This chapter describes the DICOM attributes of Secondary Capture Image instances created in interoperability mode. The following table lists the modules created by *syngo*® MR XA51A.

IE	Module	Reference	Usage
Patient	Patient	see chapter 9.1.1.1.1	always
Study	General Study	see chapter 9.1.1.1.2	always
	Patient Study	see chapter 9.1.1.1.3	always
Series	General Series	see chapter 9.1.1.1.4	always
Frame of Reference	Frame of Reference	see chapter 9.1.1.1.6	always
Equipment	General Equipment	see chapter 9.1.1.1.7	always
	SC Equipment	see chapter 9.1.1.6.1	always
Image	General Image	see chapter 9.1.1.4.1	always
	Image Pixel	see chapter 9.1.1.1.9	always
	SC Image	see chapter 9.1.1.6.6	always
	Overlay Plane	see chapter 9.1.1.4.6	always
	Modality LUT	see chapter 9.1.1.7.1	always
	VOI LUT	see chapter 9.1.1.4.7	always
	SOP Common	see chapter 9.1.1.1.22	always (with SOP Class UID for Secondary Capture Image)
	Common Instance Reference	see chapter 9.1.1.1.23	always
	SIEMENS MR Series	see chapter 9.2.1.2	always
	SIEMENS MR Image/Frame	see chapter 9.2.1.5	always
	SIEMENS MR Common	see chapter 9.2.1.7	always

9.1.1.7.1 Modality LUT Module

Attribute Name	Tag	Supported Values
Rescale Intercept	(0028,1052)	set by creator
Rescale Slope	(0028,1053)	set by creator
Rescale Type	(0028,1054)	set by creator

9.1.1.8 Grayscale Softcopy Presentation State

For some usecases Grayscale Softcopy Presentation State instances are created referencing Enhanced MR Image or Multi-frame Grayscale Word SC Image instances. The following table lists the modules created by the *syngo*® MR XA51A.

IE	Module	Reference	Usage
Patient	Patient	see chapter 9.1.1.1.1	always
Study	General Study	see chapter 9.1.1.1.2	always
	Patient Study	see chapter 9.1.1.1.3	always
Series	General Series	see chapter 9.1.1.1.4	always
	Presentation Series	see chapter 9.1.1.8.1	always
Equipment	General Equipment	see chapter 9.1.1.1.7	always
Presentation State	Presentation State Identification	see chapter 9.1.1.8.2	always
	Presentation State Relationship	see chapter 9.1.1.8.3	always
	Presentation State Shutter	see chapter 9.1.1.8.4	always
	Presentation State Mask	see chapter 9.1.1.8.5	always
	Displayed Area	see chapter 9.1.1.8.4	always
	Graphic Annotation	see chapter 9.1.1.8.7	in case of Graphic Annotations
	Spatial Transformation	see chapter 9.1.1.8.8	always
	Graphic Layer	see chapter 9.1.1.8.9	in case of Graphic Annotations
	Modality LUT	see chapter 9.1.1.7.1	always
	Softcopy VOI LUT	see chapter 9.1.1.8.11	always
	Softcopy Presentation LUT	see chapter 9.1.1.8.12	always
	SOP Common	see chapter 9.1.1.1.22	always (with SOP Class UID for Grayscale Softcopy Presentation State)
	SIEMENS MR Common	see chapter 9.2.1.7	always

9.1.1.8.1 Presentation Series Module

Attribute Name	Tag	Supported Values
Modality	(0008,0060)	PR

9.1.1.8.2 Presentation State Identification Module

Attribute Name	Tag	Supported Values
Presentation Creation Date	(0070,0082)	set by creator
Presentation Creation Time	(0070,0083)	set by creator
Instance Number	(0020,0013)	set by creator
Content Label	(0070,0080)	set by creator
Content Description	(0070,0081)	set by creator
Content Creator's Name	(0070,0084)	set by creator

9.1.1.8.3 Presentation State Relationship Module

Attribute Name	Tag	Supported Values
Referenced Series Sequence	(0008,1115)	set by creator
>Series Instance UID	(0020,000E)	set by creator
>Referenced Image Sequence	(0008,1140)	set by creator
>>Referenced SOP Class UID	(0008,1150)	set by creator
>>Referenced SOP Instance UID	(0008,1155)	set by creator
>>Referenced Frame Number	(0008,1160)	set by creator

9.1.1.8.4 Presentation State Shutter

No attributes are available because Display Shutter Module and Bitmap Display Shutter Module are not used.

9.1.1.8.5 Presentation State Mask

No attributes are available because Mask Module is not used.

9.1.1.8.6 Displayed Area Module

Attribute Name	Tag	Supported Values
Displayed Area Selection Sequence	(0070,005A)	set by creator
>Referenced Image Sequence	(0008,1140)	set by creator

Attribute Name	Tag	Supported Values
>>Referenced SOP Class UID	(0008,1150)	set by creator
>>Referenced SOP Instance UID	(0008,1155)	set by creator
>>Referenced Frame Number	(0008,1160)	set by creator
>Pixel Origin Interpretation	(0048,0301)	set by creator
>Displayed Area Top Left Hand Corner	(0070,0052)	set by creator
>Displayed Area Bottom Right Hand Corner	(0070,0053)	set by creator
>Presentation Size Mode	(0070,0100)	set by creator
>Presentation Pixel Spacing	(0070,0101)	set by creator
>Presentation Pixel Aspect Ratio	(0070,0102)	set by creator
>Presentation Pixel Magnification Ratio	(0070,0103)	set by creator

9.1.1.8.7 Graphic Annotation Module

Attribute Name	Tag	Supported Values
Graphic Annotation Sequence	(0070,0001)	set by creator
>Referenced Image Sequence	(0008,1140)	set by creator
>>Referenced SOP Class UID	(0008,1150)	set by creator
>>Referenced SOP Instance UID	(0008,1155)	set by creator
>>Referenced Frame Number	(0008,1160)	set by creator
>Graphic Layer	(0070,0002)	set by creator
>Text Object Sequence	(0070,0008)	set by creator
>>Bounding Box Annotation Units	(0070,0003)	set by creator
>>Anchor Point Annotation Units	(0070,0004)	set by creator
>>Unformatted Text Value	(0070,0006)	set by creator
>>Text Style Sequence	(0070,0231)	set by creator
>>>Font Name	(0070,0227)	set by creator
>>>Font Name Type	(0070,0228)	set by creator
>>>CSS Font Name	(0070,0229)	set by creator
>>>Text Color CIELab Value	(0070,0241)	set by creator
>>>Horizontal Alignment	(0070,0242)	set by creator
>>>Vertical Alignment	(0070,0243)	set by creator
>>>Shadow Style	(0070,0244)	set by creator
>>>Shadow Offset X	(0070,0245)	set by creator
>>>Shadow Offset Y	(0070,0246)	set by creator
>>>Shadow Color CIELab Val	(0070,0247)	set by creator
>>>Shadow Opacity	(0070,0258)	set by creator
>>>Underlined	(0070,0248)	set by creator
>>>Bold	(0070,0249)	set by creator

Attribute Name	Tag	Supported Values
>>>Italic	(0070,0250)	set by creator
>>Bounding Box Top Left Hand Corner	(0070,0010)	set by creator
>>Bounding Box Bottom Right Hand Corner	(0070,0011)	set by creator
>>Bounding Box Text Horizontal Justification	(0070,0012)	set by creator
>>Anchor Point	(0070,0014)	set by creator
>>Anchor Point Visibility	(0070,0015)	set by creator
>>Compound Graphic Instance ID	(0070,0226)	set by creator
>>Graphic Group ID	(0070,0295)	set by creator
>Graphic Object Sequence	(0070,0009)	set by creator
>>Graphic Annotation Units	(0070,0005)	set by creator
>>Graphic Dimensions	(0070,0020)	set by creator
>>Number of Graphic Points	(0070,0021)	set by creator
>>Graphic Data	(0070,0022)	set by creator
>>Graphic Type	(0070,0023)	set by creator
>>Line Style Sequence	(0070,0232)	set by creator
>>>Pattern On Color CIELab Value;	(0070,0251)	set by creator
>>>Pattern Off Color CIELab Value	(0070,0252)	set by creator
>>>Pattern On Opacity	(0070,0284)	set by creator
>>>Pattern Off Opacity	(0070,0285)	set by creator
>>>Line Thickness	(0070,0253)	set by creator
>>>Line Dashing Style	(0070,0254)	set by creator
>>>Line Pattern	(0070,0255)	set by creator
>>>Shadow Style	(0070,0244)	set by creator
>>>Shadow Offset X	(0070,0245)	set by creator
>>>Shadow Offset Y	(0070,0246)	set by creator
>>>Shadow Color CIELab Value	(0070,0247)	set by creator
>>>Shadow Opacity	(0070,0258)	set by creator
>>Graphic Filled	(0070,0024)	set by creator
>>Fill Style Sequence	(0070,0233)	set by creator
>>>Pattern On Color CIELab Value;	(0070,0251)	set by creator
>>>Pattern Off Color CIELab Value	(0070,0252)	set by creator
>>>Pattern On Opacity	(0070,0284)	set by creator
>>>Pattern Off Opacity	(0070,0285)	set by creator
>>>Fill Mode	(0070,0257)	set by creator
>>>Fill Pattern	(0070,0256)	set by creator
>>Compound Graphic Instance ID	(0070,0226)	set by creator
>>Graphic Group ID	(0070,0295)	set by creator
>Compound Graphic Sequence	(0070,0209)	set by creator
>>Compound Graphic Instance	(0070,0226)	set by creator

Attribute Name	Tag	Supported Values
>>Compound Graphic Units	(0070,0282)	set by creator
>>Graphic Dimensions	(0070,0020)	set by creator
>>Number of Graphic Points	(0070,0021)	set by creator
>>Graphic Data	(0070,0022)	set by creator
>>Compound Graphic Type	(0070,0294)	set by creator
>Text Style Sequence	(0070,0231)	set by creator
>>>Font Name	(0070,0227)	set by creator
>>>Font Name Type	(0070,0228)	set by creator
>>>CSS Font Name	(0070,0229)	set by creator
>>>Text Color CIELab Value	(0070,0241)	set by creator
>>>Horizontal Alignment	(0070,0242)	set by creator
>>>Vertical Alignment	(0070,0243)	set by creator
>>>Shadow Style	(0070,0244)	set by creator
>>>Shadow Offset X	(0070,0245)	set by creator
>>>Shadow Offset Y	(0070,0246)	set by creator
>>>Shadow Color CIELab Value	(0070,0247)	set by creator
>>>Shadow Opacity	(0070,0258)	set by creator
>>>Underlined	(0070,0248)	set by creator
>>>Bold	(0070,0249)	set by creator
>>>Italic	(0070,0250)	set by creator
>>Line Style Sequence	(0070,0232)	set by creator
>>>Pattern On Color CIELab Value;	(0070,0251)	set by creator
>>>Pattern Off Color CIELab Value	(0070,0252)	set by creator
>>>Pattern On Opacity	(0070,0284)	set by creator
>>>Pattern Off Opacity	(0070,0285)	set by creator
>>>Line Thickness	(0070,0253)	set by creator
>>>Line Dashing Style	(0070,0254)	set by creator
>>>Line Pattern	(0070,0255)	set by creator
>>>Shadow Style	(0070,0244)	set by creator
>>>Shadow Offset X	(0070,0245)	set by creator
>>>Shadow Offset Y	(0070,0246)	set by creator
>>>Shadow Color CIELab Value	(0070,0247)	set by creator
>>>Shadow Opacity	(0070,0258)	set by creator
>>Rotation Angle	(0070,0230)	set by creator
>>Rotation Point	(0070,0273)	set by creator
>>Gap Length	(0070,0261)	set by creator
>>Diameter of Visibility	(0070,0262)	set by creator
>>Major Ticks Sequence	(0070,0287)	set by creator
>>>Tick Position	(0070,0288)	set by creator

Attribute Name	Tag	Supported Values
>>>Tick Label	(0070,0289)	set by creator
>>Tick Alignment	(0070,0274)	set by creator
>>Tick Label Alignment	(0070,0279)	set by creator
>>Show Tick Label	(0070,0278)	set by creator
>>Graphic Filled	(0070,0024)	set by creator
>>Fill Style Sequence	(0070,0233)	set by creator
>>>Pattern On Color CIElab Value;	(0070,0251)	set by creator
>>>Pattern Off Color CIElab Value	(0070,0252)	set by creator
>>>Pattern On Opacity	(0070,0284)	set by creator
>>>Pattern Off Opacity	(0070,0285)	set by creator
>>>Fill Mode	(0070,0257)	set by creator
>>>Fill Pattern	(0070,0256)	set by creator
>>Graphic Group ID	(0070,0295)	set by creator

9.1.1.8.8 Spatial Transformation Module

Attribute Name	Tag	Supported Values
Image Rotation	(0070,0042)	0, 90, 180, 270
Image Horizontal Flip	(0070,0041)	Y, N

9.1.1.8.9 Graphic Layer Module

Attribute Name	Tag	Supported Values
Graphic Layer Sequence	(0070,0060)	set by creator
>Graphic Layer	(0070,0002)	set by creator
>Graphic Layer Order	(0070,0062)	set by creator
>Graphic Layer Recommended Display Grayscale Value	(0070,0066)	set by creator
>Graphic Layer Recommended Display CIElab Value	(0070,0401)	set by creator
>Graphic Layer Description	(0070,0068)	set by creator

9.1.1.8.10 Graphic Group Module

Attribute Name	Tag	Supported Values
Graphic Group Sequence	(0070,0234)	set by creator
> Graphic Group ID	(0070,0295)	set by creator
> Graphic Group Label	(0070,0207)	set by creator

Attribute Name	Tag	Supported Values
> Graphic Group Description	(0070,0208)	set by creator

9.1.1.8.11 Softcopy VOI LUT Module

Attribute Name	Tag	Supported Values
Softcopy VOI LUT Sequence	(0028,3110)	set by creator
>Referenced Image Sequence	(0008,1140)	set by creator
>>Referenced SOP Class UID	(0008,1150)	set by creator
>>Referenced SOP Instance UID	(0008,1155)	set by creator
>>Referenced Frame Number	(0008,1160)	set by creator
>VOI LUT Sequence	(0028,3010)	set by creator
>>LUT Descriptor	(0028,3002)	set by creator
>>LUT Explanation	(0028,3003)	set by creator
>>LUT Data	(0028,3006)	set by creator
>Window Center	(0028,1050)	set by creator
>Window Width	(0028,1051)	set by creator
>Window Center and Width Explanation	(0028,1055)	set by creator
>VOI LUT Function	(0028,1056)	set by creator

9.1.1.8.12 Softcopy Presentation LUT Module

Attribute Name	Tag	Supported Values
Presentation LUT Shape	(2050,0020)	IDENTITY, INVERSE

9.1.1.9 Color Softcopy Presentation State

For some use cases Color Softcopy Presentation State instances are created referencing Enhanced MR Color Image or Multi-frame True Color SC Image instances. The following table lists the modules created by the *syngo*® MR XA51A.

IE	Module	Reference	Usage
Patient	Patient	see chapter 9.1.1.1.1	always
Study	General Study	see chapter 9.1.1.1.2	always
	Patient Study	see chapter 9.1.1.1.3	always
Series	General Series	see chapter 9.1.1.1.4	always
	Presentation Series	see chapter 9.1.1.8.1	always
Equipment	General Equipment	see chapter 9.1.1.1.7	always

IE	Module	Reference	Usage
Presentation State	Presentation State Identification	see chapter 9.1.1.8.2	always
	Presentation State Relationship	see chapter 9.1.1.8.3	always
	Presentation State Shutter	see chapter 9.1.1.8.4	always
	Displayed Area	see chapter 9.1.1.8.69.1.1.8.4	always
	Graphic Annotation	see chapter 9.1.1.8.79.1.1.8.7	in case of Graphic Annotations
	Spatial Transformation	see chapter 9.1.1.8.89.1.1.8.8	always
	Graphic Layer	see chapter 9.1.1.8.99.1.1.8.9	in case of Graphic Annotations
	ICC Profile	see chapter 9.1.1.1.21	always
	SOP Common	see chapter 9.1.1.1.22	always (with SOP Class UID for Color Softcopy Presentation State)
	SIEMENS MR Common	see chapter 9.2.1.7	always

9.1.1.10 Pseudo-color Softcopy Presentation State

For some use cases Pseudo-color Softcopy Presentation State instances are created referencing Enhanced MR Image or Multi-frame Grayscale Word SC Image instances e. g. if a palette color LUT has to be applied to the images. The following table lists the modules created by the *syngo*® MR XA51A.

IE	Module	Reference	Usage
Patient	Patient	see chapter 9.1.1.1.1	always
Study	General Study	see chapter 9.1.1.1.2	always
	Patient Study	see chapter 9.1.1.1.3	always
Series	General Series	see chapter 9.1.1.1.4	always
	Presentation Series	see chapter 9.1.1.8.1	always
Equipment	General Equipment	see chapter 9.1.1.1.7	always
Presentation State	Presentation State Identification	see chapter 9.1.1.8.2	always
	Presentation State Relationship	see chapter 9.1.1.8.3	always
	Presentation State Shutter	see chapter 9.1.1.8.4	always
	Presentation State Mask	see chapter 9.1.1.8.5	always
	Displayed Area	see chapter 9.1.1.8.6	always
	Graphic Annotation	see chapter 9.1.1.8.7	in case of Graphic Annotations
	Spatial Transformation	see chapter 9.1.1.8.8	always
	Graphic Layer	see chapter 9.1.1.8.9	in case of Graphic Annotations
	Modality LUT	see chapter 9.1.1.7.1	always

IE	Module	Reference	Usage
	Softcopy VOI LUT	see chapter 9.1.1.8.11	always
	Palette Color Lookup Table	see chapter 9.1.1.10.1	always
	ICC Profile	see chapter 9.1.1.1.21	always
	SOP Common	see chapter 9.1.1.1.22	always (with SOP Class UID for Pseudo-color Softcopy Presentation State)
	SIEMENS MR Common	see chapter 9.2.1.7	always

9.1.1.10.1 Palette Color Lookup Table Module

Attribute Name	Tag	Supported Values
Red Palette Color Lookup Table Descriptor	(0028,1101)	set by creator
Green Palette Color Lookup Table Descriptor	(0028,1102)	set by creator
Blue Palette Color Lookup Table Descriptor	(0028,1103)	set by creator
Red Palette Color Lookup Table Data	(0028,1201)	set by creator
Green Palette Color Lookup Table Data	(0028,1202)	set by creator
Blue Palette Color Lookup Table Data	(0028,1203)	set by creator

9.1.1.11 Enhanced and Comprehensive SR IOD

Enhanced and Comprehensive SR SOP Classes are used by applications e. g. cardiac analysis to store evaluated results in an Evidence Document.

IE	Module	Reference	Usage
Patient	Patient	see chapter 9.1.1.1.1	always
Study	General Study	see chapter 9.1.1.1.2	always
	Patient Study	see chapter 9.1.1.1.3	always
Series	SR Document Series	see chapter 9.1.1.11.1	always
Frame of Reference	Frame of Reference	see chapter 9.1.1.1.6	always
Equipment	General Equipment	see chapter 9.1.1.1.7	always
Document	SR Document General	see chapter 9.1.1.11.2	always
	SR Document Content	see chapter 9.1.1.11.3	always
	SOP Common	see chapter 9.1.1.1.22	always (with SOP Class UID for Enhanced SR or Comprehensive SR)
	SIEMENS MR Common	see chapter 9.2.1.7	always

9.1.1.11.1 SR Document Series Module

Attribute Name	Tag	Supported Values
Modality	(0008,0060)	SR
Series Instance UID	(0020,000E)	set by creator
Series Number	(0020,0011)	set by creator
Series Date	(0008,0021)	set by creator
Series Time	(0008,0031)	set by creator
Protocol Name	(0018,1030)	set by creator
Series Description	(0008,103E)	set by creator
Referenced Performed Procedure Step Sequence	(0008,1111)	set by creator
>Referenced SOP Class UID	(0008,1150)	set by creator
>Referenced SOP Instance UID	(0008,1155)	set by creator

9.1.1.11.2 SR Document General Module

Attribute Name	Tag	Supported Values
Series Number	(0020,0011)	set by creator
Preliminary Flag	(0040,A496)	set by creator (PRELIMINARY/FINAL)
Completion Flag	(0040,A491)	set by creator (PARTIAL/FINAL)
Completion Flag Description	(0040,A492)	set by creator
Verification Flag	(0040,A493)	set by creator (UNVERIFIED)
Content Date	(0008,0023)	set by creator
Content Time	(0008,0033)	set by creator

9.1.1.11.3 SR Document Content Module

Attribute Name	Tag	Supported Values
<i>Include Table 85: Document Content Macro Attributes</i>		With a Value Type (0040,A040) of CONTAINER
<i>Include Table 86: Document Relationship Macro Attributes</i>		

Table 85: Document Content Macro Attributes

Attribute Name	Tag	Supported Values
Value Type	(0040,A040)	AUTO
Concept Name Code Sequence	(0040,A043)	AUTO
>Include Table 87: Code Sequence Macro Attributes		
Text Value	(0040,A160)	if Value Type is TEXT; AUTO
DateTime	(0040,A120)	if Value Type is DATETIME; AUTO
Date	(0040,A121)	if Value Type is DATE; AUTO
Time	(0040,A122)	if Value Type is TIME; AUTO
Person Name	(0040,A123)	if Value Type is PNAME; AUTO
Measured Value Sequence	(0040,A300)	if Value Type is NUM
>Numeric Value	(0040,A30A)	set by creator
>Floating Point Value	(0040,A161)	set by creator
>Rational Numerator Value	(0040,A162)	set by creator
>Rational Denominator Value	(0040,A163)	set by creator
>Measurement Units Code Sequence	(0040,08EA)	if Value Type is NUM
>>Include Table 87: Code Sequence Macro Attributes		
Concept Code Sequence	(0040,A168)	if Value Type is CODE
>Include Table 87: Code Sequence Macro Attributes		
Referenced SOP Sequence	(0008,1199)	if Value Type is COMPOSITE or IMAGE
>Referenced SOP Class UID	(0008,1150)	
>Referenced SOP Instance UID	(0008,1155)	
>Referenced Frame Number	(0008,1160)	if Value Type is IMAGE
Graphic Data	(0070,0022)	if Value Type is SCOORD
Graphic Type	(0070,0023)	if Value Type is SCOORD
Pixel Origin Interpretation	(0048,0301)	if Value Type is SCOORD
Referenced Frame of Referenced UID	(3006,0024)	if Value Type is SCOORD3D
Graphic Data	(0070,0022)	if Value Type is SCOORD3D
Graphic Type	(0070,0023)	if Value Type is SCOORD3D
Temporal Range Type	(0040,A130)	if Value Type is TCOORD
Referenced Sample Positions	(0040,A132)	if Value Type is TCOORD
Referenced Time Offsets	(0040,A138)	if Value Type is TCOORD
Referenced DateTime	(0040,A13A)	if Value Type is TCOORD
Include Table 88: Container Macro Attributes if Value Type is CONTAINER		

Table 86: Document Relationship Macro Attributes

Attribute Name	Tag	Supported Values
Observation DateTime	(0040,A032)	AUTO (if different from Content Date (0008,0023) and Content Time (0008,0033))
Content Sequence	(0040,A730)	set by creator
>Relationship Type	(0040,A010)	set by creator
>Include Table 85: Document Content Macro Attributes		
>Include Table 86: Document Relationship Macro Attributes		
>Referenced Content Item Identifier	(0040,DB73)	AUTO

Table 87: Code Sequence Macro Attributes

Attribute Name	Tag	Supported Values
Code Value	(0008,0100)	AUTO
Coding Scheme Designator	(0008,0102)	AUTO
Coding Scheme Version	(0008,0103)	AUTO
Code Meaning	(0008,0104)	AUTO

Table 88: Container Macro Attributes

Attribute Name	Tag	Supported Values
Continuity of Content	(0008,A050)	AUTO (SEPARATE/CONTINUOUS)
Content Template Sequence	(0040,A504)	set by creator
>Mapping Resource	(0008,0105)	set by creator
>Mapping Resource UID	(0008,0118)	set by creator
>Template Identifier	(0040,DB00)	set by creator

Table 89: Table Content Item Macro Attributes

Attribute Name	Tag	Supported Values
Tabulated Values Sequence	(0040,A801)	
>Number of Table Rows	(0040,A802)	set by creator
>Number of Table Columns	(0040,A803)	set by creator

Attribute Name	Tag	Supported Values
>Table Row Definition Sequence	(0040,A806)	set by creator
>>Table Row Number	(0040,A804)	
>>Concept Name Code	(0040,A043)	
>>>Include Table 87: Code Sequence Macro Attributes		
>>Measurement Units Code Sequence	(0040,08EA)	
>>>Include Table 87: Code Sequence Macro Attributes		
>Table Column Definition Sequence	(0040,A807)	set by creator
>>Table Column Number	(0040,A805)	
>>Concept Name Code Sequence	(0040,A043)	
>>>Include Table 87: Code Sequence Macro Attributes		
>>Measurement Units Code Sequence	(0040,08EA)	
>>>Include Table 87: Code Sequence Macro Attributes		
>Cell Values Sequence	(0040,A808)	
>>Table Row Number	(0040,A804)	
>>Table Column Number	(0040,A805)	
>>Referenced Content Item Identifier	(0040,DB73)	
>>Selector DS Value	(0072,0072)	
>>Selector DT Value	(0072,0063)	
>>Selector FD Value	(0072,0074)	
>>Selector FL Value	(0072,0076)	
>>Selector IS Value	(0072,0064)	
>>Selector SL Value	(0072,007C)	
>>Selector SS Value	(0072,007E)	
>>Selector SV Value	(0072,0082)	
>>Selector UC Value	(0072,006F)	
>>Selector UL Value	(0072,0078)	
>>Selector US Value	(0072,007A)	
>>Concept Code Sequence	(0040,A168)	
>>>Include Table 87: Code Sequence Macro Attributes		
>>Measurement Units Code Sequence	(0040,08EA)	
>>>Include Table 87: Code Sequence Macro Attributes		
>>Numeric Value Quantifier Code Sequence	(0040,A301)	
>>>Include Table 87: Code Sequence Macro Attributes		

9.1.1.11.4 Evidence Document Templates

The finding related results of applications are stored into the Content Sequence of a Structured Evidence Document. The Content Items of a Content Sequence are specified in Structured Reporting Templates.

Examples of Structured Reporting Templates are:

- BI-RADS reporting
- Cardiac reporting
- PI-RADS 2 reporting
- PhoenixZip documentation.

9.1.1.11.5 99_3000 Phoenix ZIP Document Template

Table 90: 99_3000 Phoenix ZIP Document Parameters

NL	Rel. with Parent	Value Type	Concept Name	VM	Req. Type	Condition	Value Set Constraint
1	HAS CONCEPT MOD	CODE	113011, DCM, Document Title Modifier	1	M		MR-20, 99SMS_CTMR, "Phoenix ZIP Document"
2	HAS CONCEPT MOD	CODE	121049, DCM, Language of Content Item and Descendents	1	M		
3	HAS OBS CONTEXT	CODE	121005, DCM, Observer Type	1	M		121006, DCM, Person
4	HAS OBS CONTEXT	PNAME	121008, DCM, Observer Name	1	M		
5	CONTAINS	CONTAINER	121064, DCM, Current Procedure Description	1	M		
6	>	CONTAINS	111004, DCM, Modality	1	M		MR, DCM, Magnetic Resonance
7	>	CONTAINS	TEXT	113016, DCM, Performed Procedure Step	1	M	
8	>	CONTAINS	CONTAINER	125203, DCM, Acquisition Protocol	1	M	
9	>>	CONTAINS	CONTAINER	A-30, 99SMS_CTMR, Protocol Header	1	M	
10	>>>	CONTAINS	TEXT	A-92, 99SMS_CTMR, System Type	1	M	
11	>>>	CONTAINS	TEXT	A-90, 99SMS_CTMR, Software Version	1	M	
12	>>>	CONTAINS	TEXT	A-84, 99SMS_CTMR, Field Strength	1	M	
13	>>>	CONTAINS	TEXT	A-86, 99SMS_CTMR, Protocol Name	1	M	
14	>>>	CONTAINS	TEXT	A-88, 99SMS_CTMR, Sequence Name	1	M	

	NL	Rel. with Parent	Value Type	Concept Name	VM	Req. Type	Condition	Value Set Constraint
14	>>>	CONTAINS	TEXT	A-80, 99SMS_CTMR, Acquisition Time	1	M		
15	>>>	CONTAINS	TEXT	A-98, 99SMS_CTMR, Orientation	1	M		
16	>>>	CONTAINS	TEXT	A-100, 99SMS_CTMR, Resolution Matrix	1	M		
17	>>>	CONTAINS	NUM	A-76, 99SMS_CTMR, Number Of Slices	1	M		UNITS = unary, no units
18	>>>	CONTAINS	NUM	A-78, 99SMS_CTMR, FoV Read	1	M		UNITS = millimeter
19	>>>	CONTAINS	NUM	A-70, 99SMS_CTMR, FoV Phase	1	M		UNITS = millimeter
20	>>>	CONTAINS	NUM	A-94, 99SMS_CTMR, Slice Thickness	1	M		UNITS = millimeter
21	>>>	CONTAINS	NUM	A-96, 99SMS_CTMR, Slice Gap	1	M		UNITS = percent
22	>>>	CONTAINS	NUM	A-74, 99SMS_CTMR, Repetition Time	1	M		UNITS = milliseconds
23	>>>	CONTAINS	NUM	A-72, 99SMS_CTMR, Echo Time	1	M		UNITS = milliseconds
24	>>>	CONTAINS	NUM	A-82, 99SMS_CTMR, Flip Angle	1	M		UNITS = degree
25	>>>	CONTAINS	TEXT	A-102, 99SMS_CTMR, Fat Suppression	1	M		
26	>>>	CONTAINS	TEXT	A-104, 99SMS_CTMR, Flow Compensation	1	M		
27	>>>	CONTAINS	TEXT	A-106, 99SMS_CTMR, Water Suppression	1	M		
28	>>>	CONTAINS	TEXT	A-108, 99SMS_CTMR, Subtraction	1	M		
29	>>>	CONTAINS	TEXT	A-110, 99SMS_CTMR, First Signal Mode	1	M		
30	>>>	CONTAINS	TEXT	A-112, 99SMS_CTMR, Contrast Agent	1	M		
31	>>	CONTAINS	CONTAINER	121138, DCM, Image Acquired	1	M		
32	>>>	HAS ACQ CONTEXT	TEXT	121141, DCM, Image Type	1	M		

9.1.2 Usage of Attributes from received IODs

N/A

9.1.3 Attribute mapping

The following table describes the mapping from attributes received in DICOM Modality Worklist to attributes of the created SOP instances:

Attribute Name	Tag	Mapped attribute / Notes
SOP Common		
Specific Character Set	(0008,0005)	
Scheduled Procedure Step		
Scheduled Procedure Step Sequence	(0040,0100)	Request Attributes Sequence (0040,0275)
>Scheduled Performing Physician's Name	(0040,0006)	default for "Performing Physician's Name" (0008,1050)
>Scheduled Procedure Step Description	(0040,0007)	Scheduled Procedure Step Description, default for "Performed Procedure Step Description" (0040,0254)
>Scheduled Procedure Step ID	(0040,0009)	"Scheduled Procedure Step ID" default for "Performed Procedure Step ID" (0040,0253)
>Scheduled Procedure Step Location	(0040,0011)	"Scheduled Procedure Step Location" is taken as default for "Performed Location"
Requested Procedure		
Referenced Study Sequence	(0008,1110)	Referenced Study Sequence (0008,1110)
>Referenced SOP Class UID	(0008,1150)	>Referenced SOP Class UID (0008,1150)
Study Instance UID	(0020,000D)	Study Instance UID
Requested Procedure Description	(0032,1060)	Requested Procedure Description in Request Attributes Sequence (0040,0275). Used to preselect examination program in scheduler (favourite list).
Requested Procedure Code Sequence	(0032,1064)	"Requested Procedure Code Sequence" in Request Attributes Sequence (0040,0275). Default for "Procedure Code Sequence" Used to preselect examination program in scheduler (favourite list).
>Code Value	(0008,0100)	mapped
>Coding Scheme Designator	(0008,0102)	mapped
>Coding Scheme Version	(0008,0103)	mapped
>Code Meaning	(0008,0104)	mapped
Requested Procedure ID	(0040,1001)	"Requested Procedure ID" in Request Attributes Sequence (0040,0275) default for "Study ID"
Reason for the Requested Procedure	(0040,1002)	Reason for the Requested Procedure
Reporting Priority	(0040,1009)	Reporting Priority
Requested Procedure Comments	(0040,1400)	Requested Procedure Comments
Imaging Service Request		

Attribute Name	Tag	Mapped attribute / Notes
Accession Number	(0008,0050)	mapped
Referring Physician's Name	(0008,0090)	mapped
Requesting Physician	(0032,1032)	mapped
Placer Order Number / Imaging Service Request	(0040,2016)	mapped
Filler Order Number / Imaging Service Request	(0040,2017)	mapped
Visit Identification		
Admission ID	(0038,0010)	mapped
Institution Name	(0008,0080)	default for Institution Name
Institution Address	(0008,0081)	default for Institution Address
Visit Status		
Visit Status ID	(0038,0008)	mapped
Institution Address	(0008,0081)	mapped
Current Patient Location	(0038,0300)	mapped
Patient's Institution Residence	(0038,0400)	mapped
Visit Admission		
Admitting Diagnosis Description	(0008,1080)	mapped
Admitting Date	(0038,0020)	mapped
Patient Identification		
Patient's Name	(0010,0010)	mapped
Patient ID	(0010,0020)	mapped
Issuer of Patient ID	(0010,0021)	mapped
Other Patient IDs	(0010,1000)	mapped
Other Patient Names	(0010,1001)	mapped
Patient Demographic		
Patient's Birth Date	(0010,0030)	mapped
Patient's Birth Time	(0010,0032)	mapped
Patient's Sex	(0010,0040)	mapped
Patient's Size	(0010,1020)	mapped
Patient's Weight	(0010,1030)	mapped
Patient's Address	(0010,1040)	mapped
Military Rank	(0010,1080)	mapped
Ethnic Group	(0010,2160)	mapped
Patient Comments	(0010,4000)	mapped
Patient Medical		
Medical Alerts	(0010,2000)	mapped
Allergies	(0010,2110)	mapped
Pregnancy Status	(0010,21C0)	mapped

Attribute Name	Tag	Mapped attribute / Notes
Smoking Status	(0010,21A0)	mapped
Special Needs	(0038,0050)	mapped

9.1.4 Coerced / Modified fields

N/A

9.2 Data Dictionary of Private Attributes

9.2.1 MR Related Private Attributes

9.2.1.1 SIEMENS MR Shared Macro

The private SIEMENS MR Shared Macro contains attributes that are shared by a set of frames, i.e. there values are constant for all frames of all images within a series or within the whole acquisition.

Table 91: Attributes of SIEMENS MR Shared Macro

DICOM Tag	Name	VR	VM
(0021, SIEMENS MR SDS 01, FE)	Siemens MR SDS Sequence	SQ	1
> Include Table 92: Attributes of SIEMENS MR Series and Shared Macro			

9.2.1.2 SIEMENS MR Series Module

DICOM Tag	Name	VR	VM
> Include Table 92: Attributes of SIEMENS MR Series and Shared Macro			

9.2.1.3 SIEMENS MR Series and Shared Macro

Table 92: Attributes of SIEMENS MR Series and Shared Macro

DICOM Tag	Name	VR	VM
(0021, SIEMENS MR SDS 01, 04)	SliceArrayConcatenations	DS	1
(0021, SIEMENS MR SDS 01, 05)	RelTablePosition	IS	3
(0021, SIEMENS MR SDS 01, 06)	CoilForGradient	LO	1
(0021, SIEMENS MR SDS 01, 07)	LongModelName	LO	1
(0021, SIEMENS MR SDS 01, 08)	GradientMode	SH	1

DICOM Tag	Name	VR	VM
(0021, SIEMENS MR SDS 01, 09)	PATModeText	LO	1
(0021, SIEMENS MR SDS 01, 0A)	SW_korr_faktor	DS	1
(0021, SIEMENS MR SDS 01, 0B)	RfPowerErrorIndicator	DS	1
(0021, SIEMENS MR SDS 01, 0C)	PositivePCSDirections	SH	1
(0021, SIEMENS MR SDS 01, 0D)	ProtocolChangeHistory	US	1
(0021, SIEMENS MR SDS 01, 0F)	Stim_lim	DS	3
(0021, SIEMENS MR SDS 01, 10)	MrProtocolVersion	IS	1
(0021, SIEMENS MR SDS 01, 11)	PhaseGradientAmplitude	DS	1
(0021, SIEMENS MR SDS 01, 12)	ReadoutOS	FD	1
(0021, SIEMENS MR SDS 01, 13)	t_puls_max	DS	1
(0021, SIEMENS MR SDS 01, 14)	NumberOfPrescans	IS	1
(0021, SIEMENS MR SDS 01, 16)	dBdt_thresh	DS	1
(0021, SIEMENS MR SDS 01, 17)	SelectionGradientAmplitude	DS	1
(0021, SIEMENS MR SDS 01, 18)	RFSWDMostCriticalAspect	SH	1
(0021, SIEMENS MR SDS 01, 19)	MrPhoenixProtocol	OB	1
(0021, SIEMENS MR SDS 01, 1A)	CoilString	LO	1
(0021, SIEMENS MR SDS 01, 1B)	SliceResolution	DS	1
(0021, SIEMENS MR SDS 01, 1C)	Stim_max_online	DS	3
(0021, SIEMENS MR SDS 01, 1D)	Operation_mode_flag	IS	1
(0021, SIEMENS MR SDS 01, 22)	SequenceFileOwner	SH	1
(0021, SIEMENS MR SDS 01, 23)	RfWatchdogMask	IS	1
(0021, SIEMENS MR SDS 01, 25)	TablePositionOrigin	SL	3
(0021, SIEMENS MR SDS 01, 26)	MiscSequenceParam	IS	1-n
(0021, SIEMENS MR SDS 01, 27)	Isocentered	US	1
(0021, SIEMENS MR SDS 01, 2A)	CoilId	IS	1-n
(0021, SIEMENS MR SDS 01, 2B)	PatReinPattern	ST	1
(0021, SIEMENS MR SDS 01, 2C)	Sed	DS	3
(0021, SIEMENS MR SDS 01, 2D)	SARMostCriticalAspect	DS	3
(0021, SIEMENS MR SDS 01, 2E)	Stim_mon_mode	IS	1
(0021, SIEMENS MR SDS 01, 2F)	GradientDelayTime	DS	3
(0021, SIEMENS MR SDS 01, 30)	ReadoutGradientAmplitude	DS	1
(0021, SIEMENS MR SDS 01, 31)	AbsTablePosition	IS	3
(0021, SIEMENS MR SDS 01, 32)	RFSWDOperationMode	SS	1
(0021, SIEMENS MR SDS 01, 33)	CoilForGradient2	SH	1
(0021, SIEMENS MR SDS 01, 34)	Stim_faktor	DS	1
(0021, SIEMENS MR SDS 01, 35)	Stim_max_ges_norm_online	DS	1

DICOM Tag	Name	VR	VM
(0021, SIEMENS MR SDS 01, 36)	dBdt_max	DS	1
(0021, SIEMENS MR SDS 01, 37)	FlowCompensation	SH	1
(0021, SIEMENS MR SDS 01, 38)	TransmitterCalibration	DS	1
(0021, SIEMENS MR SDS 01, 3D)	PhaseSliceOversampling	CS	1
(0021, SIEMENS MR SDS 01, 44)	B1rms	DS	2
(0021, SIEMENS MR SDS 01, 45)	B1rmsSupervision	CS	1
(0021, SIEMENS MR SDS 01, 46)	TalesReferencePower	DS	1
(0021, SIEMENS MR SDS 01, 48)	DICOMImageFlavor	CS	1
(0021, SIEMENS MR SDS 01, 49)	DICOMAcquisitionContrast	CS	1
(0021, SIEMENS MR SDS 01, 50)	RFEchoTrainLength	US	1
(0021, SIEMENS MR SDS 01, 51)	GradientEchoTrainLength	US	1
(0021, SIEMENS MR SDS 01, 53)	Laterality4MF	CS	1
(0021, SIEMENS MR SDS 01, 5A)	ScanningSequence	CS	1-n
(0021, SIEMENS MR SDS 01, 5B)	SequenceVariant	CS	1-n
(0021, SIEMENS MR SDS 01, 5C)	MeasurementOptions	CS	1-n
(0021, SIEMENS MR SDS 01, 5D)	ScanRegionPositionIso	SL	1
(0021, SIEMENS MR SDS 01, 5E)	FieldOfViewText	LO	1
(0021, SIEMENS MR SDS 01, 5F)	RelativeTablePositionText	SH	1

9.2.1.4 SIEMENS MR Frame Macro

The private SIEMENS MR Frame Macro contains attributes that are specific for a frame.

Table 93: Attributes of SIEMENS MR Frame Macro

DICOM Tag	Name	VR	VM
(0021, SIEMENS MR SDI 02, FE)	Siemens MR SDI Sequence	SQ	1

> Include Table 94: Attributes of SIEMENS MR Image/Frame Macro

9.2.1.5 SIEMENS MR Image/Frame Module

DICOM Tag	Name	VR	VM
> Include Table 94: Attributes of SIEMENS MR Image/Frame Macro			

9.2.1.6 SIEMENS MR Image/Frame Macro

Table 94: Attributes of SIEMENS MR Image/Frame Macro

DICOM Tag	Name	VR	VM
(0021, SIEMENS MR SDI 02, 03)	SliceMeasurementDuration	DS	1
(0021, SIEMENS MR SDI 02, 04)	TimeAfterStart	DS	1
(0021, SIEMENS MR SDI 02, 06)	ICE_Dims	LO	1
(0021, SIEMENS MR SDI 02, 1A)	RFSWDDDataType	SH	1
(0021, SIEMENS MR SDI 02, 1B)	PhaseEncodingDirectionPositive	IS	1
(0021, SIEMENS MR SDI 02, 22)	VoxelThickness	DS	1
(0021, SIEMENS MR SDI 02, 24)	MultistepIndex	IS	1
(0021, SIEMENS MR SDI 02, 33)	EchoColumnPosition	IS	1
(0021, SIEMENS MR SDI 02, 41)	GSWDDDataType	SH	1
(0021, SIEMENS MR SDI 02, 42)	RealDwellTime	IS	1
(0021, SIEMENS MR SDI 02, 45)	ImaAbsTablePosition	SL	3
(0021, SIEMENS MR SDI 02, 48)	EchoPartitionPosition	IS	1
(0021, SIEMENS MR SDI 02, 49)	EchoLinePosition	IS	1
(0021, SIEMENS MR SDI 02, 4F)	ImaCoilString	LO	1
(0021, SIEMENS MR SDI 02, 51)	SequenceMask	UL	1
(0021, SIEMENS MR SDI 02, 56)	ImaPATModeText	LO	1
(0021, SIEMENS MR SDI 02, 58)	AcquisitionMatrixText	SH	1
(0021, SIEMENS MR SDI 02, 59)	ImaRelTablePosition	IS	3
(0021, SIEMENS MR SDI 02, 5B)	SlicePosition_PCS	IS	3
(0021, SIEMENS MR SDI 02, 5E)	ProtocolSliceNumber	IS	1
(0021, SIEMENS MR SDI 02, 67)	ExamDataRole	ST	1
(0021, SIEMENS MR SDI 02, 70)	DataSetInfo	OB	1
(0021, SIEMENS MR SDI 02, 71)	UsedChannelString	UT	1
(0021, SIEMENS MR SDI 02, 75)	ImageType4MF	CS	1-n
(0021, SIEMENS MR SDI 02, 76)	ImageHistory	LO	1-n
(0021, SIEMENS MR SDI 02, 77)	SequenceInfo	LO	1
(0021, SIEMENS MR SDI 02, 78)	ImageTypeVisible	CS	1-n
(0021, SIEMENS MR SDI 02, 79)	DistortionCorrectionType	CS	1
(0021, SIEMENS MR SDI 02, 88)	SliceCenterDistancefromIsoCenter	DS	1
(0021, SIEMENS MR SDI 02, 89)	FrameInversionTime	DS	1
(0021, SIEMENS MR SDI 02, 8A)	FrameNumberInSeries	IS	1
(0021, SIEMENS MR SDI 02, 8B)	SlicePositionText	SH	1
(0021, SIEMENS MR SDI 02, 8C)	MorphoQCThreshold	FD	1

DICOM Tag	Name	VR	VM
(0021, SIEMENS MR SDI 02, 8D)	MorphoQCIndex	FD	1
(0021, SIEMENS MR SDI 02, 8E)	DICOM_Dims	LO	1

9.2.1.7 SIEMENS MR Common Module

The SIEMENS MR Common Module is intended to specify the creating component of the SOP instance. The SOP instances can be created during acquisition (Creator Identifier "ACQUISITION") or by a post-processing application (Creator Identifier "APPLICATION"). The creating application shall be specified in attribute Application Identifier (SOP instances created during acquisition shall be tagged with "ACQUISITION").

Table 95: Attributes of SIEMENS MR Common Module

DICOM Tag	Name	VR	VM	Supported Values
(0021, SIEMENS MR SDR 01, 01)	Creator Identifier	LO	1	Enumerated values: ACQUISITION, APPLICATION
(0021, SIEMENS MR SDR 01, 02)	Application Identifier	LO	1-n	Defined terms: ACQUISITION, ModalityViewer, MRBasic, MRBreast, MRBreastBiopsy, MRNeuro3D, MRCardiacAnalysis
(0021, SIEMENS MR SDR 01, 03)	Cause Identifier	LO	1	set by creator

9.2.1.8 SIEMENS MR HEADER Module

The intention of the private attributes of SIEMENS MR HEADER in private group 51 is to support image text related information to DICOM viewers to display it directly and do not need to calculate it from several DICOM attributes.

Table 96: Attributes of private group SIEMENS MR HEADER

DICOM Tag	Name	VR	VM
(0051, SIEMENS MR HEADER, 08)	Header Type	CS	1
(0051, SIEMENS MR HEADER, 09)	Header Version	LO	1
(0051, SIEMENS MR HEADER, 0A)	Meas Duration	LO	1
(0051, SIEMENS MR HEADER, 0C)	Field Of View	LO	1
(0051, SIEMENS MR HEADER, 0D)	Slice Position	SH	1
(0051, SIEMENS MR HEADER, 12)	Rel Table Position	SH	1
(0051, SIEMENS MR HEADER, 13)	Positive PCS Directions	SH	1

9.2.1.9 SIEMENS MR Raw Data Module

Table 97: Attributes of private SIEMENS MR Raw Data Module

DICOM Tag	Name	VR	VM
(7FE1,SIEMENS MR IMA, 10)	Siemens MR Raw Data	OB/OF	1

9.3 Coded Terminology and Templates

9.3.1 Context Groups

N/A

9.3.2 Template Specifications

N/A

9.3.3 Private Code definitions

N/A

9.4 Grayscale Image Consistency

The high resolution TFT display monitor option of syngo® MR XA51A comes with a DICOM Grayscale Standard Display Function (GSDF) compliant factory pre-setting. A typical working environment setup is assumed for ambient light.

9.5 Standard Extended / Specialized / Private SOP Classes

9.5.1 Enhanced MR Image Storage SOP Class

DICOM Tag	Attribute Name	VR	VM
(0018,0086)	Echo Numbers (s)	IS	1-n

9.6 Private Transfer Syntaxes

No private Transfer Syntaxes are defined for or requested by syngo® MR XA51A DICOM application.

9.7 DICOM Print SCU – detailed status displays

The following tables document the behavior of the syngo® MR XA51A DICOM Print AE in response to messages received for the printer SOP class and the print job SOP class.

Definitions of camera symbols:

- Idle: Camera is installed and ready; idle icon is displayed.
- Interact: The user has to react in near future, but not immediately.
Example: A camera was low in 8x10 clear sheets: LOW 8x10 CLR was sent by N-EVENT-REPORT.

- Queue Stopped: The user has to react immediately. Either the camera needs immediate interaction or a job has been aborted.
Example: A camera is out of 8x10 clear sheets, or camera is down, or a film job is aborted.

Note: different camera symbols are displayed according to the Printer Status Info.

9.7.1 Common Status Information

Table 98: Common Printer Status Information

Printer Status Info / Execution Status Info	Description	Message string visible in 'Status Bar'	Other action for UI / 'camera symbol'
NORMAL	Camera is ready	Camera is ready	<None>/idle
BAD RECEIVE MGZ	There is a problem with the film receive magazine. Films from the printer cannot be transported into the magazine.	Problem with receive magazine.	<None>/interact
BAD SUPPLY MGZ	There is a problem with the film supply magazine. Films from this magazine cannot be transported into the printer.	Problem with supply magazine.	<None>/interact
CALIBRATING	Printer is performing self-calibration, it is expected to be available for normal operation shortly.	Self-calibration. Please wait.	<None>/idle
CALIBRATION ERR	An error in the printer calibration has been detected, quality of processed films may not be optimal.	Problem in calibration. Film quality may not be optimal.	<None>/interact
CHECK CHEMISTRY	A problem with the processor chemicals has been detected, quality of processed films may not be optimal.	Problem with chemistry. Film quality may not be optimal.	<None>/interact
CHECK SORTER	There is an error in the film sorter	Error in film sorter.	<None>/interact
CHEMICALS EMPTY	There are no processing chemicals in the processor, films will not be printed and processed until the processor is back to normal.	Camera chemistry empty. Please check.	<None>/interact
CHEMICALS LOW	The chemical level in the processor is low, if not corrected, it will probably shut down soon.	Camera chemistry low. Please check.	<None>/interact
COVER OPEN	One or more printer or processor covers, drawers, doors are open.	Camera cover, drawer or door open.	<None>/interact
ELEC CONFIG ERR	Printer configured improperly for this job.	Camera configured improperly for this job. Queue stopped.	Queue for this camera will be STOPPED/ Queue stopped
ELEC DOWN	Printer is not operating due to some unspecified electrical hardware problem.	Camera electrical hardware Problem.	<None>/interact
ELEC SW ERROR	Printer not operating for some unspecified software error.	Camera software problem. Queue stopped.	Queue for this camera will be STOPPED/ Queue stopped
EMPTY 8X10	The 8x10 inch film supply magazine is empty.	8x10 film supply empty.	<None>/interact

Printer Status Info / Execution Status Info	Description	Message string visible in 'Status Bar'	Other action for UI / 'camera symbol'
EMPTY 8X10 BLUE	The 8x10 inch blue film supply magazine is empty.	8x10 blue film supply empty.	<None>/interact
EMPTY 8X10 CLR	The 8x10 inch clear film supply magazine is empty.	8x10 clear film supply empty.	<None>/interact
EMPTY 8X10 PAPR	The 8x10 inch paper supply magazine is empty.	8x10 paper supply empty.	<None>/interact
EMPTY 10X12	The 10x12 inch film supply magazine is empty.	10x12 film supply empty.	<None>/interact
EMPTY 10X12 BLUE	The 10x12 inch blue film supply magazine is empty.	10x12 blue film supply empty.	<None>/interact
EMPTY 10X12 CLR	The 10x12 inch clear film supply magazine is empty.	10x12 clear film supply empty.	<None>/interact
EMPTY 10X12 PAPR	The 10x12 inch paper supply magazine is empty.	10x12 paper supply empty.	<None>/interact
EMPTY 10X14	The 10x14 inch film supply magazine is empty.	10x14 film supply empty.	<None>/interact
EMPTY 10X14 BLUE	The 10x14 inch blue film supply magazine is empty.	10x14 blue film supply empty.	<None>/interact
EMPTY 10X14 CLR	The 10x14 inch clear film supply magazine is empty.	10x14 clear film supply empty.	<None>/interact
EMPTY 10X14 PAPR	The 10x14 inch paper supply magazine is empty.	10x14 paper supply empty.	<None>/interact
EMPTY 11X14	The 11x14 inch film supply magazine is empty.	11x14 film supply empty.	<None>/interact
EMPTY 11X14 BLUE	The 11x14 inch blue film supply magazine is empty.	11x14 blue film supply empty.	<None>/interact
EMPTY 11X14 CLR	The 11x14 inch clear film supply magazine is empty.	11x14 clear film supply empty.	<None>/interact
EMPTY 11X14 PAPR	The 11x14 inch paper supply magazine is empty.	11x14 paper supply empty.	<None>/interact
EMPTY 14X14	The 14x14 inch film supply magazine is empty.	14x14 film supply empty.	<None>/interact
EMPTY 14X14 BLUE	The 14x14 inch blue film supply magazine is empty.	14x14 blue film supply empty.	<None>/interact
EMPTY 14X14 CLR	The 14x14 inch clear film supply magazine is empty.	14x14 clear film supply empty.	<None>/interact
EMPTY 14X14 PAPR	The 14x14 inch paper supply magazine is empty.	14x14 paper supply empty.	<None>/interact
EMPTY 14X17	The 14x17 inch film supply magazine is empty.	14x17 film supply empty.	<None>/interact
EMPTY 14X17 BLUE	The 14x17 inch blue film supply magazine is empty.	14x17 blue film supply empty.	<None>/interact
EMPTY 14X17 CLR	The 14x17 inch clear film supply magazine is empty.	14x17 clear film supply empty.	<None>/interact
EMPTY 14X17 PAPR	The 14x17 inch paper supply magazine is empty.	14x17 paper supply empty.	<None>/interact

Printer Status Info / Execution Status Info	Description	Message string visible in 'Status Bar'	Other action for UI / 'camera symbol'
EMPTY 24X24	The 24x24 inch film supply magazine is empty.	24x24 film supply empty.	<None>/interact
EMPTY 24X24 BLUE	The 24x24 inch blue film supply magazine is empty.	24x24 blue film supply empty.	<None>/interact
EMPTY 24X24 CLR	The 24x24 inch clear film supply magazine is empty.	24x24 clear film supply empty.	<None>/interact
EMPTY 24X24 PAPR	The 24x24 inch paper supply magazine is empty.	24x24 paper supply empty	<None>/interact
EMPTY 24X30	The 24x30 inch film supply magazine is empty.	24x30 film supply empty.	<None>/interact
EMPTY 24X30 BLUE	The 24x30 inch blue film supply magazine is empty.	24x30 blue film supply empty.	<None>/interact
EMPTY 24X30 CLR	The 24x30 inch clear film supply magazine is empty.	24x30 clear film supply empty.	<None>/interact
EMPTY 24X30 PAPR	The 24x30 inch paper supply magazine is empty.	24x30 paper supply empty.	<None>/interact
EMPTY A4 PAPR	The A4 paper supply magazine is empty.	A4 paper supply empty	<None>/interact
EMPTY A4 TRANS	The A4 transparency supply magazine is empty.	A4 transparency supply empty.	<None>/interact
EXPOSURE FAILURE	The exposure device has failed due to some unspecified reason.	Exposure device has failed.	<None>/interact
FILM JAM	A film transport error has occurred and a film is jammed in the printer or processor.	Film jam.	<None>/interact
FILM TRANSP ERR	There is a malfunction with the film transport, there may or may not be a film jam.	Film transport problem.	<None>/interact
FINISHER EMPTY	The finisher is empty.	Finisher is empty.	<None>/interact
FINISHER ERROR	The finisher is not operating due to some unspecified reason	Finisher problem.	<None>/interact
FINISHER LOW	The finisher is low on supplies.	Finisher low.	<None>/interact
LOW 8X10	The 8x10 inch film supply magazine is low.	8x10 film supply low.	<None>/interact
LOW 8X10 BLUE	The 8x10 inch blue film supply magazine is low.	8x10 blue film supply low.	<None>/interact
LOW 8X10 CLR	The 8x10 inch clear film supply magazine is low.	8x10 clear film supply low.	<None>/interact
LOW 8X10 PAPR	The 8x10 inch paper supply magazine is low.	8x10 paper supply low.	<None>/interact
LOW 10X12	The 10x12 inch film supply magazine is low.	10x12 film supply low.	<None>/interact
LOW 10X12 BLUE	The 10x12 inch blue film supply magazine is low.	10x12 blue film supply low.	<None>/interact
LOW 10X12 CLR	The 10x12 inch clear film supply magazine is low.	10x12 clear film supply low.	<None>/interact
LOW 10X12 PAPR	The 10x12 inch paper supply magazine is low.	10x12 paper supply low.	<None>/interact
LOW 10X14	The 10x14 inch film supply magazine is low.	10x14 film supply low.	<None>/interact

Printer Status Info / Execution Status Info	Description	Message string visible in 'Status Bar'	Other action for UI / 'camera symbol'
LOW 10X14 BLUE	The 10x14 inch blue film supply magazine is low.	10x14 blue film supply low.	<None>/interact
LOW 10X14 CLR	The 10x14 inch clear film supply magazine is low.	10x14 clear film supply low.	<None>/interact
LOW 10X14 PAPR	The 10x14 inch paper supply magazine is low.	10x14 paper supply low.	<None>/interact
LOW 11X14	The 11x14 inch film supply magazine is low.	11x14 film supply low.	<None>/interact
LOW 11X14 BLUE	The 11x14 inch blue film supply magazine is low.	11x14 blue film supply low.	<None>/interact
LOW 11X14 CLR	The 11x14 inch clear film supply magazine is low.	11x14 clear film supply low.	<None>/interact
LOW 11X14 PAPR	The 11x14 inch paper supply magazine is low.	11x14 paper supply low.	<None>/interact
LOW 14X14	The 14x14 inch film supply magazine is low.	14x14 film supply low.	<None>/interact
LOW 14X14 BLUE	The 14x14 inch blue film supply magazine is low.	14x14 blue film supply low.	<None>/interact
LOW 14X14 CLR	The 14x14 inch clear film supply magazine is low.	14x14 clear film supply low.	<None>/interact
LOW 14X14 PAPR	The 14x14 inch paper supply magazine is low.	14x14 paper supply low.	<None>/interact
LOW 14X17	The 14x17 inch film supply magazine is low.	14x17 film supply low.	<None>/interact
LOW 14X17 BLUE	The 14x17 inch blue film supply magazine is low.	14x17 blue film supply low.	<None>/interact
LOW 14X17 CLR	The 14x17 inch clear film supply magazine is low.	14x17 clear film supply low.	<None>/interact
LOW 14X17 PAPR	The 14x17 inch paper supply magazine is low.	14x17 paper supply low.	<None>/interact
LOW 24X24	The 24x24 inch film supply magazine is low.	24x24 film supply low.	<None>/interact
LOW 24X24 BLUE	The 24x24 inch blue film supply magazine is low.	24x24 blue film supply low.	<None>/interact
LOW 24X24 CLR	The 24x24 inch clear film supply magazine is low.	24x24 clear film supply low.	<None>/interact
LOW 24X24 PAPR	The 24x24 inch paper supply magazine is low.	24x24 paper supply low.	<None>/interact
LOW 24X30	The 24x30 inch film supply magazine is low.	24x30 film supply low.	<None>/interact
LOW 24X30 BLUE	The 24x30 inch blue film supply magazine is low.	24x30 blue film supply low.	<None>/interact
LOW 24X30 CLR	The 24x30 inch clear film supply magazine is low.	24x30 clear film supply low.	<None>/interact
LOW 24X30 PAPR	The 24x30 inch paper supply magazine is low.	24x30 paper supply low.	<None>/interact
LOW A4 PAPR	The A4 paper supply magazine is low.	A4 paper supply low.	<None>/interact
LOW A4 TRANS	The A4 transparency supply magazine is low.	A4 transparency supply low.	<None>/interact
NO RECEIVE MGZ	The film receive magazine is not available.	Film receiver not available.	<None>/interact
NO RIBBON	The ribbon cartridge needs to be replaced.	Replace ribbon cartridge.	<None>/interact

Printer Status Info / Execution Status Info	Description	Message string visible in 'Status Bar'	Other action for UI / 'camera symbol'
NO SUPPLY MGZ	The film supply magazine is not available.	Film supply not available.	<None>/interact
CHECK PRINTER	The printer is not ready at this time, operator intervention is required to make the printer available.	Check camera.	<None>/interact
CHECK PROC	The processor is not ready at this time, operator intervention is required to make the printer available.	Check processor.	<None>/interact
PRINTER DOWN	The printer is not operating due to some unspecified reason.	Camera down.	<None>/interact
PRINTER INIT	The printer is not ready at this time, it is expected to become available without intervention. For example, it may be in a normal warm-up state.	Camera initializing.	<None>/Idle
PRINTER OFFLINE	The printer has been disabled by an operator or service person.	Camera off-line.	<None>/interact
PROC DOWN	The processor is not operating due to some unspecified reason.	Processor down.	<None>/interact
PROC INIT	The processor is not ready at this time, it is expected to become available without intervention. For example, it may be in a normal warm-up state.	Processor initializing.	<None>/Idle
PROC OVERFLOW FL	Processor chemicals are approaching the overflow full mark.	Processor chemicals near overflow.	<None>/interact
PROC OVERFLOW HI	Processor chemicals have reached the overflow full mark.	Processor chemicals overflow.	<None>/interact
QUEUED	Print job in Queue	--	<None>/Idle
RECEIVER FULL	The film receive magazine is full.	Receiver full.	<None>/interact
REQ MED NOT INST	The requested film, paper, or other media supply magazine is installed in the printer but may be available with operator intervention.	Install media supply.	<None>/interact
REQ MED NOT AVAI	The requested film, paper, or other media requested is not available on this printer.	Media supply not available on this camera. Queue stopped. Change camera.	Queue for this camera will be STOPPED/ Queue stopped
RIBBON ERROR	There is an unspecified problem with the print ribbon.	Error with print ribbon.	<None>/interact
SUPPLY EMPTY	The printer is out of film.	Camera out of film.	<None>/interact
SUPPLY LOW	The film supply is low.	Film supply low.	<None>/interact
UNKNOWN	There is an unspecified problem.	Unspecified problem with camera.	<None>/interact

9.7.2 Additional DICOM Execution Status Information

Printer Status Info and Execution Status Info are defined terms and can therefore be extended or reduced by camera manufacturers. Therefore *syngo*® MR XA51A shall be flexible.

If any other printer status info or execution status info is received (as described in Table Table 99, *syngo*® MR XA51A will react as shown in the following table:

Table 99: Additional Printer Status Information

Printer Status / Execution	Printer / Execution Status Info	Description	Message string visible in the Job status bar	Other action for syngo / camera symbol
WARNING	<any other>	<not defined status info>	Camera info: <status info>	<None>/Interact
FAILURE	<any other>	<not defined status info>	Camera info: <status info> Queue stopped.	Queue for this camera will be STOPPED/Queue stopped

Annex A: Index of Tables

Table 1: Network Services.....	2
Table 2: Media Services	6
Table 3: Implementation Identifying Information	7
Table 4: Association Policies.....	20
Table 5: Asynchronous Nature as an Association Initiator.....	20
Table 6: Presentation Context Table "Verification"	21
Table 7: Presentation Context Table "Verification"	21
Table 8: Association Policy.....	22
Table 9: Asynchronous Nature as an Association Initiator.....	22
Table 10: Proposed Presentation Contexts for Storage.....	23
Table 11: DICOM Command Response Status Handling Behavior.....	24
Table 12: DICOM Command Communication Failure Behavior	24
Table 13: Storage C-STORE Response Status	26
Table 14: Association Policies.....	26
Table 15: Asynchronous Nature as an Association Initiator.....	27
Table 16: Proposed Presentation Contexts for Storage Commitment	27
Table 17: DICOM Command Response Status Handling Behavior.....	28
Table 18: DICOM Command Communication Failure Behavior	28
Table 19: Presentation Context Table "Update Flag Information"	29
Table 20: Storage Commitment Failure Behaviour	29
Table 21: Acceptable Presentation Contexts for Activity "Receive Commitment Request"	30
Table 22: DICOM Command Response Status Handling Behavior.....	30
Table 23: Association Policies.....	31
Table 24: Asynchronous Nature as an Association Initiator.....	31
Table 25: Proposed Presentation Contexts for Query.....	32
Table 26: Extended Negotiation as an SCU.....	32
Table 27: DICOM Command Response Status Handling Behavior.....	32
Table 28: DICOM Command Communication Failure Behavior	33
Table 29: Attributes supported for Study/Series Query - SCU.....	33
Table 30: Proposed Presentation Contexts for Retrieve and Activity "Send Move Request"	34
Table 31: DICOM Command Response Status Handling Behavior.....	35
Table 32: DICOM Command Communication Failure Behavior	35
Table 33: Acceptable Presentation Contexts for "Receive Query Request"	36
Table 34: Extended Negotiation as an SCP.....	36
Table 35: DICOM Command Response Status Handling Behavior.....	37
Table 36: Attributes supported for Study/Series Query – SCP	37
Table 37: Acceptable Presentation Contexts for Retrieve and Activity "MOVE SCP"	39
Table 38: DICOM Command Response Status Handling Behavior.....	39
Table 39: Association Policies.....	40
Table 40: Asynchronous Nature as an Association Initiator.....	40
Table 41: Proposed Presentation Contexts for Worklist	41
Table 42: Broad Query search keys.....	41
Table 43: Modality Worklist C-Find Return keys	42
Table 44: DICOM Command Response Status Handling Behavior.....	46
Table 45: DICOM Command Communication Failure Behavior	46
Table 46: Association Policies.....	46
Table 47: Asynchronous Nature as an Association Initiator.....	47
Table 48: Acceptable Presentation Contexts Activity "Create MPPS"	47
Table 49: MPPS N-CREATE-RSP Status Handling Behavior	48
Table 50: Modality PPS Discontinuation Reasons supported	48
Table 51: Acceptable Presentation Contexts Activity "Update MPPS"	49
Table 52: MPPS N-SET Response Status Handling Behavior	49
Table 53: Association Policies.....	49
Table 54: Asynchronous Nature as an Association Initiator.....	50
Table 55: Presentation Contexts for the Activity "Print Film"	50
Table 56: Attributes for the N-CREATE-RQ of the Basic Film Session	51
Table 57: N-CREATE-RSP Status Handling Behavior for the Basic Film Session.....	51
Table 58: Attributes for the N-CREATE-RQ of the Basic Film Session	52
Table 59: N-CREATE-RSP Status Handling Behavior for Basic Film Box.....	53

Table 60: N-ACTION-RSP Status Handling Behavior for Basic Film Box.....	53
Table 61: Attributes for N-SET-RQ of Basic Grayscale Image Box	54
Table 62: N-SET-RSP Status Handling Behavior for the Basic Grayscale Image Box SOP Class	54
Table 63: Attributes for N-SET-RQ of Basic Color Image Box.....	55
Table 64: N-SET-RSP Status Handling Behavior for the Color Grayscale Image Box	55
Table 65: Attributes for N-CREATE-RQ of Presentation LUT SOP Class	56
Table 66: N-CREATE-RSP Status Handling Behavior for the Presentation LUT SOP Class	56
Table 67: Attributes for N-GET-RQ of the Printer SOP Class	56
Table 68: DICOM Command Communication Failure Behavior	57
Table 69: Presentation Contexts for the Activity "Print Film"	57
Table 70: Attributes for the N-EVENT-REPORT-RQ of the Printer SOP Class	57
Table 71: Presentation Contexts for the Activity "Print Management"	58
Table 72: Attributes for the N-EVENT-REPORT-RQ of the Print Job SOP Class	58
Table 73: AE Titles	59
Table 74: Parameter List	60
Table 75: Implementation Class/Version Name - Media Interchange	62
Table 76: Media - Application Profiles and Real-World Activities	63
Table 77: Transfer Syntaxes for STD-GEN-DVD-J2K and STD-GEN-USB-J2K	64
Table 78: Single-Byte Character Sets without Code Extension	65
Table 79: Single-Byte Characters Sets with Code Extension	66
Table 80: Multi-Byte Character Sets without Code Extension	66
Table 81: Multi-Byte Character Sets with Code Extension	66
Table 82: Application Level Confidentiality Profile attributes (standard tags)	68
Table 83: Application Level Confidentiality Profile Attributes (private tags)	77
Table 84: Secure Transport Connection Profiles	80
Table 85: Document Content Macro Attributes	121
Table 86: Document Relationship Macro Attributes	122
Table 87: Code Sequence Macro Attributes	122
Table 88: Container Macro Attributes	122
Table 89: Table Content Item Macro Attributes.....	122
Table 90: 99_3000 Phoenix ZIP Document Parameters.....	124
Table 91: Attributes of SIEMENS MR Shared Macro	128
Table 92: Attributes of SIEMENS MR Series and Shared Macro	128
Table 93: Attributes of SIEMENS MR Frame Macro	130
Table 94: Attributes of SIEMENS MR Image/Frame Macro	131
Table 95: Attributes of SIEMENS MR Common Module	132
Table 96: Attributes of private group SIEMENS MR HEADER	132
Table 97: Attributes of private SIEMENS MR Raw Data Module	133
Table 98: Common Printer Status Information	134
Table 99: Additional Printer Status Information	139

Annex B: Table of Figures

Figure 1: <i>syngo</i> ® MR XA51A DICOM Data Flow diagram	15
Figure 4: Sequence Diagram for Real World Activities - System Configuration	17
Figure 5: Sequence Diagram for Real World Activities -Acquisition workflow	18
Figure 6: Sequence Diagram for Real World Activities - Printing.....	19
Figure 6: Media Interchange Application Data Flow Diagram	61
Figure 8: Sequence diagram – Media creation	62

On account of certain regional limitations of sales rights and service availability, we cannot guarantee that all products included in this brochure are available through the Siemens sales organization worldwide. Availability and packaging may vary by country and are subject to change without prior notice.

Some / All of the features and products described herein may not be available in the United States or other countries.

The information in this document contains general technical descriptions of specifications and options as well as standard and optional features that do not always have to be present in individual cases.

Siemens Healthineers reserves the right to modify the design, packaging, specifications and options described herein without prior notice. Please contact your local Siemens sales representative for the most current information.

In the interest of complying with legal requirements concerning the environmental compatibility of our products (protection of natural resources and waste conservation), we recycle certain components. Using the same extensive quality assurance measures as for factory-new components, we guarantee the quality of these recycled components.

Siemens Healthineers Headquarters
Siemens Healthineers AG
Siemensstr. 3
91301 Forchheim, Germany
Phone: +49 9191 18-0
siemens-healthineers.com

QR700012452 | © Siemens Healthineers AG, 09.2024